www.tehencom.com Product Brochure

Anritsu envision : ensure

Signal Analyzer

MS2840A

MS2840A-044: 9 kHz to 26.5 GHz MS2840A-046: 9 kHz to 44.5 GHz « MS2840A-040: 9 kHz to 3.6 GHz^{*} » « MS2840A-041: 9 kHz to 6.0 GHz^{*} »



-123

Close-in Phase Noise Measurement Frequency 1 GHz 10 kHz offset

dBc/Hz

(meas.)

-1000 Millimeter Wave Band Close-in Phase Noise Measurement Frequency 79 GHz 10 kHz offset

*: Refer to the separate brochure "MS2840A-040/041".



As Pure As Diamond

ООО "Техэнком" Контрольно-измерительные приборы и оборудование www.tehencom.com



The Pure Signal Analyzer TMS2840A

The Pure Signal Analyzer 🗊

Excellent Phase Noise Performance using New Synthesizer Design

Based on more than 120 years of technological excellence, Anritsu has built a new synthesizer design into the MS2840A, offering never-seen-before, high, close-in phase noise performance.

For R&D and Manufacturing of Wireless Equipment, Radar and Transmitter Device

The MS2840A series (26.5 GHz /44.5 GHz models) close-in phase noise performance is –123 dBc/Hz (10 kHz offset) at a measurement frequency of 1 GHz. Additionally, this excellent fundamental performance is leveraged at millimeter-wave-band measurements (50 GHz to 90 GHz). With the High Performance Waveguide Mixer connected, an extremely high performance of –100 dBc/Hz (10 kHz offset, meas.*) is achieved at a measurement frequency of 79 GHz.

The MS2840A series (26.5 GHz/44.5 GHz models) with high, close-in phase-noiseperformance spectrum and signal analyzers is ideal for developing and manufacturing radio and radar equipment as well as transmitters, etc., at every measurement frequency.

*: Value measured at design but not guaranteed specification.



| Cal -300 -400 - | Cal -300 | Cal -300 -400 -700 - | Cal Save Save Save Save Copy SSD SSD SSD SSD SSD SSD SSD SS | | Ancritsu MS2840A Signal Analyzer 9kHz-44.5GHz Remote Local | MS2340A Spectrum Analyzer MKR ^D 1.000 000 000 00 GHz 1 Reference Level 0.00dBm 00 100 100 | O.63 dBm D RBW 10Hz D ATT 0c O.63 dBm D VBW 1Hz SWT 800n FFT Sample 10001 points | ns Spectrum Analyzer | |
|--|---|--|--|--|---|--|--|-----------------------------------|--|
| Recall -800 | Recall -800 -100 | Recall | Recall Copy SSD 0 1st Local Output Span 25.000kHz Trace Trace <td< th=""><th></th><th></th><th>-40.0</th><th></th><th></th><th></th></td<> | | | -40.0 | | | |
| | 1st Local Output Image: State of the st | 13t Local Output Image: Center 1.000 000 000GHz Span 25.000kHz Time/Sweep F8 | 1st Local Output Image: Conter 1000 000 000GHz Image: Conter 1000 000 000GH | | Сору | -80.0 | | 49 Trace F6 Trigger/Gate F7 | |
| 1st Local Ime/sweep Output Ime/sweep | | | | | 1st Local | Center 1.000 000 000GHz | Span 25.000kH | Z Time/Sweep F8 | |

The Pure Signal Analyzer MS2840A

Better Than Expected Close-in Phase Noise Performance

Close-in Phase Noise Performance



Measurement Frequency 1GHz 10 kHz Offset

-123_{dBc/Hz}

The MS2840A series (26.5 GHz and 44.5 GHz models) has the excellent phase noise performance required for measuring narrowband wireless, wireless backhaul, etc.



Millimeter Wave Band Phase Noise Performance



Measurement Examples*1

Measurement Frequency 79GHz 10 kHz Offset -1000dBc/Hz^{*1}

Excellent phase-noise performance is achieved even with the High Performance Waveguide Mixer connected to the MS2840A series (26.5 GHz and 44.5 GHz models). For example, phase noise exceeding -100 dBc/Hz can be measured quickly at a measurement frequency of 79 GHz.

Display High Sensitivity Measurement in Micro and Millimeter Wave Bands



Faster Measurement Speed

The MS2840A has a much faster Intel Core i5-4400, 2.7 GHz than its predecessor MS2830A along with expanded main memory of 8 GB and uses an SSD for internal storage. As a result, the start-up time and measurement speed are greatly increased.

Spectrum Analyzer Functions (1000 averagings*3)



Signal Analyzer Functions (Spctrogram Display*4)



*1: Actual data for measuring instrument selected at random; not guaranteed performance for

all shipped instruments.

*2: Preamp: ON

*3: Measurement Conditions: 1 GHz Frequency/SPAN; 1 MHz RBW/VBW; 1 ms Sweep Speed

*4: Measurement Conditions: 1 GHz Frequency; 25 MHz SPAN; Signal Capture Time: 10 ms

MS2840A

Better Than Expected Close-in Phase Noise Performance

Since 2000 most spectrum analyzers have been designed for mobile communications and the phase noise performance has been optimized for offset frequencies of several MHz. Consequently, customers requiring good close-in phase noise performance have been limited to a narrow choice of usable spectrum analyzers, causing problems. This new MS2840A series (26.5 GHz/44.5 GHz models) has been designed with emphasis on offering a spectrum analyzer with excellent close-in phase noise performance at offset frequencies of just several kHz. This performance surpasses that of first-generation high-end spectrum analyzers and has sufficient margin for evaluating the closein spurious of narrowband communications equipment in the shortwave, VHF, and UHF bands. Furthermore, this excellent phase noise performance proves its usefulness in the microwave and millimeter wave bands for evaluating microwave wireless equipment, aerospace equipment, weather radar, 79 GHz band automotive collision-prevention radar, and other devices requiring oscillator measurements. It supports measurements previously requiring large, expensive phase noise measuring instruments while offering excellent noise performance in a middle-price-range spectrum analyzer.

Measurement Examples



Spectrum Display 150 MHz Measurement Frequency, Preamp Off



Spectrum Display 40 GHz Measurement Frequency, Preamp Off

Close-in Phase Noise Performance

Specification at 1 GHz Measurement Frequency (Spectrum Analyzer Function)

| Carrier Offset | SSB Phase Noise |
|----------------|--------------------|
| 10 Hz | –80 dBc/Hz (nom.) |
| 100 Hz | –92 dBc/Hz (nom.) |
| 1 kHz | –117 dBc/Hz (nom.) |
| 10 kHz | –123 dBc/Hz |
| 100 kHz | –123 dBc/Hz |
| 1 MHz | –135 dBc/Hz |
| 10 MHz | –148 dBc/Hz (nom.) |



Phase Noise Measurement 150 MHz Measurement Frequency, Preamp Off



Phase Noise Measurement 40 GHz Measurement Frequency, Preamp Off

Better Than Expected Close-in Phase Noise Performance (High-Performance Waveguide Mixer)

The MS2840A series (26.5 GHz/44.5 GHz models) is supported by two types of mixer: the high-performance waveguide mixers (50 GHz to 90 GHz) for measurements in the millimeter wave band, and external harmonic mixers (26.5 GHz to 325 GHz). In particular, the high-performance waveguide mixers make maximum use of the excellent phase noise performance of the MS2840A to monitor the actual spectrum floor of millimeter-wave-band transmitters and oscillators, playing a key role in evaluating their phase noise performance.



High-Performance Waveguide Mixers

| Model | Name | Frequency Band | Frequency Range | Waveguide | Flange |
|---------|---|----------------|------------------|-----------|----------|
| MA2806A | High Performance Waveguide Mixer (50 to 75 GHz) | V band | 50 GHz to 75 GHz | WR15 | UG-385/U |
| MA2808A | High Performance Waveguide Mixer (60 to 90 GHz) | E band | 60 GHz to 90 GHz | WR12 | UG-387/U |

Measurement Examples



Spectrum Display 79 GHz Measurement Frequency (Using High-Performance Waveguide Mixer MA2808A



Phase Noise Measurement 79 GHz Measurement Frequency (Using High-Performance Waveguide Mixer MA2808A)

High-Sensitivity Measurements in Microwave and Millimeter Wave Bands

The MS2840A has excellent display average noise level (DANL) as well as high dynamic range performance. When the built-in preamplifier is on, the DANL supports a high sensitivity measurement performance of better than –160 dBm/Hz in the frequency range from 0.03 GHz to 34 GHz.*¹ Even when connected with either of the MA2806A and MS2808A high-performance waveguide mixers (50 GHz to 90 GHz), the MS2840A maintains a performance of –150 dBm/Hz (meas.*²) at 75 GHz, supporting high-sensitivity measurements over a wide frequency range. This performance proves its usefulness in capturing low-level signals and antenna side lobes in test systems with large coupling losses, such as free-space propagation measurements at antenna coupling.

Displayed Average Noise Level (DANL)

Spectrum Analyzer Function

Preamp: None, Microwave Preselector Bypass: None

| | | DANL | |
|-----------|-----------------|---------------------|------------------|
| Frequency | 26 .5 GHz Model | 44 .5 GHz Model | (MS2840A-046) |
| | (MS2840A-044) | Without MS2840A-019 | With MS2840A-019 |
| 30 MHz | –153 dBm/Hz | –153 dBm/Hz | –153 dBm/Hz |
| 400 MHz | –153 dBm/Hz | –153 dBm/Hz | –153 dBm/Hz |
| 1 GHz | –150 dBm/Hz | –150 dBm/Hz | –150 dBm/Hz |
| 3 GHz | –147 dBm/Hz | –147 dBm/Hz | –147 dBm/Hz |
| 13 GHz | –151 dBm/Hz | –151 dBm/Hz | –150 dBm/Hz |
| 20 GHz | –146 dBm/Hz | –146 dBm/Hz | –146 dBm/Hz |
| 30 GHz | — | –146 dBm/Hz | –146 dBm/Hz |
| 40 GHz | — | –144 dBm/Hz | –142 dBm/Hz |
| 44 GHz | — | –140 dBm/Hz | –137 dBm/Hz |

Preamp: On, Microwave Preselector Bypass: None

| | | 5.4.1.1 | |
|-----------|---|---------------------|------------------|
| | | DANL | |
| Frequency | uency 26 .5 GHz Model 44 .5 GHz Model (MS | | (MS2840A-046) |
| | (MS2840A-044) | Without MS2840A-019 | With MS2840A-019 |
| 30 MHz | –166 dBm/Hz | –166 dBm/Hz | –166 dBm/Hz |
| 400 MHz | –166 dBm/Hz | –166 dBm/Hz | –166 dBm/Hz |
| 1 GHz | –164 dBm/Hz | –164 dBm/Hz | –164 dBm/Hz |
| 3 GHz | –163 dBm/Hz | –163 dBm/Hz | –163 dBm/Hz |
| 13 GHz | –163 dBm/Hz | –163 dBm/Hz | –163 dBm/Hz |
| 20 GHz | –157 dBm/Hz | –160 dBm/Hz | –160 dBm/Hz |
| 30 GHz | _ | –160 dBm/Hz | –159 dBm/Hz |
| 40 GHz | _ | –157 dBm/Hz | –156 dBm/Hz |
| 44 GHz | _ | –149 dBm/Hz | –149 dBm/Hz |

Using High-Performance Waveguide Mixer MA2806A/MA2808A

| Frequency | DANL |
|-----------|-----------------------|
| 75 GHz | –150 dBm/Hz (meas.*²) |

*1: 44.5 GHz (MS2840A-046)

*****2: Value measured at design but not guaranteed specification.

Faster Measurement Speeds

With a built-in high-performance Intel Core i5-4400E, 2.7 GHz CPU and 8 GB of main memory supporting the 64-bit Windows 7 OS, the MS2840A is much faster than its predecessor MS2830A, offering greatly improved averaging processing times for screen displays and much faster processing when displaying the results of signal analyzer and software analysis functions.

Dynamic Range

| Frequency | Dynamic Range | DANL/TOI |
|-----------|------------------|--|
| 1 GHz | 166 dB | Displayed Average Noise Level (DANL): –150 dBm/Hz Third Order Intercept (TOI): +16 dBm |
| 20 GHz | 159 dB | Displayed Average Noise Level (DANL): –146 dBm/Hz Third Order Intercept (TOI): +13 dBm |
| 40 GHz | 157 dB | Displayed Average Noise Level (DANL): –144 dBm/Hz Third Order Intercept (TOI): +13 dBm (nom.) |

The dynamic range is assumed to be the simple difference between the TOI and DANL.

Noise Floor Reduction (MS2840A-051)

The Noise Floor Reduction (NFR) function increases the measurement accuracy for low-level signals. It subtracts the internal noise components (11 dB max. nominal) of the measuring instrument itself from the displayed measurement result.

The Signal Analyzer MS2840A is available as two series with two models in each series: 26.5 GHz and 44.5 GHz, and 3.6 GHz and 6 GHz; different options can be installed in each series. The 26.5 GHz and 44.5 GHz models described in this brochure support various measurement functions required for evaluating the Tx characteristics of wireless and transmission devices as well as millimeter- waveband spectrum measurements using a connected mixer.



Signal Analyzer MS2840A

Standard Functions

Spectrum Analyzer Signal Analyzer (31.25 MHz Analysis Bandwidth) Power Meter (Connected to USB Power Sensor)

Options

Signal Analyzer (Analysis Bandwidth Expansion: 62.5 MHz, 125 MHz) Built-in Preamplifier Phase Noise Measurement Precompliance EMI Measurement Noise Figure Measurement BER Measurement Modulation Analysis

Optional Parts

High Performance Waveguide Mixer (50 GHz to 90 GHz) External Mixer (Harmonic Mixer, 26.5 GHz to 325 GHz) USB Power Sensor

Typical Measurement Items for Evaluating Tx Characteristics (26.5 GHz and 44.5 GHz models)

✓: Supported

| Supported Standard | St | andard Functio | ns | |
|---|----------------------|--------------------|--------|---|
| Functions/Options Typical Measurement | Spectrum Analyzer | Signal Analyzer | Others | Options/Optional Parts |
| Spectrum Trace | √ | √ | | |
| Channel Power | ✓ | ✓ | | |
| Occupied Bandwidth | ✓ | ~ | | |
| Adjacent Channel Leakage Power | ✓ | ✓ | | |
| Spectrum Emission Mask | ✓ | | | |
| Burst Average Power | ✓ | ✓ | | |
| Spurious Emission | ✓ | | | |
| AM Depth | | ~ | | ✓ Analog Measurement Software MX269018A |
| FM Deviation | | ~ | | ✓ Analog Measurement Software MX269018A |
| Multi-marker & Marker List | ✓ | ~ | | |
| Highest 10 Markers | ✓ | ~ | | |
| Limit Line | ✓ | | | |
| Frequency Counter | ✓ | | | |
| TOI | ✓ | | | |
| Hide Settings and Numeric Results | ✓ | | | |
| Power Meter Function (connected to USB Power Sensor) | | | ~ | |
| Phase Noise Measurement | | | | ✓ Phase Noise Measurement Function MS2840A-010 |
| EMI Measurement | | | | ✓ Precompliance EMI Function MS2840A-016 |
| Vector Modulation Analysis (EVM, etc.) | | | | ✓ Vector Modulation Analysis Software MX269017A |
| Analog Modulation Analysis (ΑΜ/FΜ/ΦΜ) (FM Deviation, Demodulation Frequency, etc.) | | | | ✓ Analog Measurement Software MX269018A |
| Millimeter-wave Band Spectrum Measurement using Connected Mixer | | | | ✓ High Performance Waveguide Mixer MA2806A/MS2808A (50 GHz to 90 GHz) ✓ External Mixer (Harmonic Mixer) MA2740C/MA2750C series (26.5 GHz to 325 GHz) |

Other Measurement Items (26.5 GHz and 44.5 GHz models)

 Supported Standard Functions/Options
 Standard Functions
 Options/Optional Parts

 Typical Measurement
 Spectrum Analyzer
 Signal Analyzer
 Others
 Options/Optional Parts

 Noise Figure Measurement

 BER Measurement

✓: Supported

Versatile Standard Functions

The built-in spectrum and signal analyzer functions can be used to evaluate the Tx characteristics of wireless devices and transmitters by running easy tests, etc., in accordance with specifications.

| Measure Function | Spectrum Analyzer (Standard) | Signal Analyzer (Standard) |
|-----------------------------------|------------------------------------|----------------------------------|
| Spectrum Trace | \checkmark | ~ |
| Channel Power | ✓ | ~ |
| Occupied Bandwidth | ✓ | ~ |
| Adjacent Channel Leakage Power | ✓ | ~ |
| Spectrum Emission Mask | ✓ | |
| Burst Average Power | ✓ | ~ |
| Spurious Emission | ✓ | |
| AM Depth | | ~ |
| FM Deviation | | ~ |
| Multi-marker & Marker List | ✓ | ~ |
| Highest 10 Markers | ✓ | ~ |
| Limit Line | ✓ | |
| Frequency Counter | ✓ | |
| TOI | ✓ | |
| Hide Settings and Numeric Results | ✓ | |

Power Meter Function (USB Power Sensor Connection)

Connecting the optional USB Power Sensor to the MS2840A supports Power and Relative Power measurements.

Compatible USB power sensors.

| Model | Frequency Range | Dynamic Range |
|-----------|------------------|------------------|
| MA24104A* | 600 MHz to 4 GHz | +3 to +51.76 dBm |
| MA24105A | 350 MHz to 4 GHz | +3 to +51.76 dBm |
| MA24106A | 50 MHz to 6 GHz | –40 to +23 dBm |
| MA24108A | 10 MHz to 8 GHz | –40 to +20 dBm |
| MA24118A | 10 MHz to 18 GHz | –40 to +20 dBm |
| MA24126A | 10 MHz to 26 GHz | –40 to +20 dBm |

*: MA24104A has been discontinued.

Spurious Emission

This function splits the frequency range into up to 20 segments for sweeping; the measurement parameters and limit lines can be specified to measure the peak power and margin for each segment. The results are tabulated below the trace and marked PASS/FAIL.



Burst Average Power

The average power for the range specified by two markers is displayed in the time domain. Measurement only requires setting the measurement start and stop positions on the screen. True performance is measured using the noise cancellation function to subtract main-frame noise from the measurement result. Pre-installed templates for each standard support easy parameter setting.



Multi-marker & Marker List

Up to 10 markers can be set for this function. Markers may be either a spot or a zone. Using a zone marker, the peak of a signal with an unstable variable frequency can be tracked and measured. Not only can the 10 markers be listed below the trace but the differences between markers can be calculated and displayed using the delta setting.



Highest 10 Markers

This function sets the threshold level and auto-detects peaks in the X (frequency) and Y (level/time) directions.



Signal Analyzer (Standard)

The MS2840A has a built-in 31.25 MHz bandwidth Fast Fourier Transformation (FFT) analysis function supporting multi-domain analysis of captured measured signals. Since it can capture phenomena such as spectrum transients that cannot be captured by conventional sweep-type spectrum analyzers, it improves the efficiency of troubleshooting. The analysis bandwidth can be expanded to either 62.5 MHz or 125 MHz as options. In addition, add the Microwave Preselector Bypass (MS2840A-067) option when using the signal analyzer measurement function at a bandwidth of >31.25 MHz and a frequency of >6 GHz.

Measurement Functions

- Spectrum trace
- Frequency vs. Time
- CCDF/APD

Power vs. TimePhase vs. Time





Analysis Bandwidth:

31.25 MHz (Standard)

50 MHz max. sampling rate = 20 ns resolution, ADC resolution 16 bits) 62.5 MHz (MS2840A-077)

(100 MHz max. sampling rate = 10 ns resolution, ADC resolution 14 bits) 125 MHz (MS2840A-077/078)

(200 MHz max. sampling rate = 5 ns resolution, ADC resolution 14 bits)

Max. Capture Time: 0.5 s to 2000 s

Max. Number of Samples: 100 Msamples

Note: An image response is received when setting the bandwidth to more than 31.25 MHz. This can be used when not inputting a signal frequency outside the MS2840A analysis bandwidth (125 MHz max.).

Option

Analysis Bandwidth Extension to 62.5 MHz (MS2840A-077) Extends analysis bandwidth to 62.5 MHz.

Analysis Bandwidth Extension to 125 MHz (MS2840A-078*)

Extends analysis bandwidth to 125 MHz.

*****: Requires MS2840A-077.

Capture & Replay Function

Waveform data can be saved (captured) to the internal memory. In addition, previously saved waveform data can be loaded (replayed) to reproduce result displays whenever necessary using measurement functions.

The following chart shows the maximum capture time per frequency span.

| Span | Sampling Rate | Capture Time | Max. Sampling Data |
|-----------|---------------|--------------|--------------------|
| 1 kHz | 2 kHz | 2000 s | 4M |
| 2.5 kHz | 5 kHz | 2000 s | 10M |
| 5 kHz | 10 kHz | 2000 s | 20M |
| 10 kHz | 20 kHz | 2000 s | 40M |
| 25 kHz | 50 kHz | 2000 s | 100M |
| 50 kHz | 100 kHz | 1000 s | 100M |
| 100 kHz | 200 kHz | 500 s | 100M |
| 250 kHz | 500 kHz | 200 s | 100M |
| 500 kHz | 1 MHz | 100 s | 100M |
| 1 MHz | 2 MHz | 50 s | 100M |
| 2.5 MHz | 5 MHz | 20 s | 100M |
| 5 MHz | 10 MHz | 10 s | 100M |
| 10 MHz | 20 MHz | 5 s | 100M |
| 25 MHz | 50 MHz | 2 s | 100M |
| 31.25 MHz | 50 MHz | 2 s | 100M |
| 50 MHz | 100 MHz | 500 ms | 50M |
| 62.5 MHz | 100 MHz | 500 ms | 50M |
| 100 MHz | 200 MHz | 500 ms | 100M |
| 125 MHz | 200 MHz | 500 ms | 100M |

Replay Usage Examples

- Sharing data between development and manufacturing sections at separate locations
- Transferring signals captured onsite for later in-house analysis
- Saving product shipping data for later warranty-claim confirmation



Captured Waveform Data: Selection Screen

Signal Analyzer (Standard)

Spectrum trace

The CCDF trace displays the power variation probability on the y-axis and power variation on the y-axis to confirm the CCDF and APD of measured signals.



Power vs. Time

The Power vs. Time trace displays a graph with amplitude on the y-axis and time on the x-axis to confirm changes in power with time of measured signals.



Frequency vs. Time

The Frequency vs. Time trace displays a graph with frequency on the y-axis and time on the x-axis to confirm time variation of the measured signal frequency.



Phase vs. Time

The Phase vs. Time trace displays a graph with phase on the y-axis and time on the x-axis to confirm time variation of the measured signal phase.



CCDF/APD

The CCDF trace displays the power variation probability on the y-axis and power variation on the y-axis to confirm the CCDF and APD of measured signals.

CCDF (Complementary Cumulative Distribution Function):

The CCDF display indicates the cumulative distribution of transient power variations compared to average power.

APD (Amplitude Probability Density):

The APD display indicates the probability distribution of transient power.



Spectrogram

The Spectrogram trace displays the level as color with frequency on the y-axis and time on the x-axis. The captured IQ data is FFT processed to confirm time variations in the continuous spectrum. It is useful for monitoring frequency hopping and transient signals.

| A MEDBARA Signal Analyzer | |
|--|-------------------|
| Spectrogram | Trace Mode |
| MKR10 3.460 000 s CRAnaysis StartTime 0 s 1599 990 6230 05 GHz CRAnaysis StartTime Ing/th 10000 000 s .10.22 dBm RBW: 1 MHz Freq Trace Point: 513 Dt : Points Time Trace Point: 501 | Spectrum |
| 2 2000 100 G Mu 77 0 00 | Power vs Time |
| | Frequency vs Time |
| , | CCDF |
| 1 j 1 | Spectrogram |
| | |
| Connon | |
| Frequency and Time Center Freq. 2000 000 000 GHz Ref. Level O.00 dBm Trigger Freq. Spain 100 kHz Cepture Length 10.000 000 kHz Attenuator 10 dB | |

Other Measurement Functions

Phase Noise Measurement Function (MS2840A-010)

The excellent close-in phase noise performance of the MS2840A supports phase noise measurement of transmitters with a frequency offset range of 10 Hz to 10 MHz and also supports when connected to the High Performance Waveguide Mixer (MA2806A, MA2808A).

Measurement Results

- Carrier level
- Error between set frequency and carrier frequency
- Marker point phase noise level

There are four measurement modes using different loop filters, which are switched to match the DUT.

Auto:

This mode switches automatically to the best loop filter for measuring the carrier signal close-in and wide-offset phase noise characteristics

Best Close-in:

This mode uses the best loop filter for measuring the carrier signal close-in phase noise characteristics.

Best Wide-offset:

This mode uses the best loop filter for measuring the carrier signal wide-offset phase noise characteristics.

Balance

This mode uses the loop filter with a good balance for measuring both close-in and wide-offset phase noise characteristics of the carrier signal.



Measurement Screen

Precompliance EMI Function (MS2840A-016)

This option adds an EMI measurement detection mode and RBW to the spectrum analyzer function. Both the detection mode used for CISPR standards (Quasi-Peak, CISPR-AVG, RMS-AVG) and RBW (200 Hz (6 dB), 9 kHz (6 dB), 120 kHz (6 dB), 1 MHz (Imp)) as well as conventional settings can be selected.

Noise Figure Measurement Function (MS2840A-017)

Noise Figure is measured with the measurement method of Y-factor method which uses a Noise Source. The Noisecom NC346 series* of noise sources is supported. *: Refer to the MS2840A Data Sheet for more details.

Frequency Range (Noise sauce): 0.01 GHz to 40.0 GHz Frequency Mode: Fixed, List, Sweep DUT Mode: Amplifier, Down Converter, Up Converter Screen Layout: Graph, Table

Measurement Results Display • Graph/List/Spot

Displays measurement results for each trace (Trace1/Trace2).

- Noise Figure (NF) [dB]
- Noise Factor (F) [Linear]
- Gain
- Y-Factor: Power ratio when Noise Source is turned On/Off
- T effective: Effective noise temperature
- P Hot: Power measured when Noise Source is On.
- P Cold: Power measured when Noise Source is Off.



Measurement Result: Example of Graph display (Frequency Mode: Sweep, Screen Layout: Graph)

| A MERICALA | | 4 000 000Hz | ATT DUT T cold | | 0dB Amplifier 296.50K | Loss Status CAL Status | Before:Off After:Off OK | National States | • |
|-------------|-------------------------------|-------------|----------------------|--|-----------------------------|--|-------------------------------|----------------------------------|---------------------|
| Total Point | | 8 | | | | ENR Status | Table | Tra | ce |
| Result | Fr | equency | | Noise Figure | | Gain | | Stor | |
| | 100 0 | 000 000H | z | 10.66039dB 3.08945dB 2.05194dB | 1 | 7.40024d 6.59371d 4.53178d | в | Lay | not <u>Table</u> |
| | 2 000 0 3 000 0 6 000 0 | 000 000H | z z z | 2.93286dB 3.10655dB 5.07462dB 1.97577dB | 1 | 2.31772d 0.24146d 1.33644d 5.33487d | IB IB IB | EW | |
| | | 000 000H | | 2.81561dB | | 2.24213d | | 4.000 Analysis Mas Auto | Time |
| | | | | | | | | Analysia (Ava. 18.15 | (ime) |
| Frequenc | ay Min | 30 000 0 | 10Hz | Frequer | cy Max | 6 000 00 | 0 000Hz | Cal S | etup |
| Reflict | Pre Arro | 0n | _ | _ | _ | _ | _ | | - |

Measurement Result: Example of List display (Frequency Mode: List, Screen Layout: List)

| W 4 | TTA sH000 000 TUG T col | 0d8 Ampifer d 296.50K | Less Statue Belice: Off After: Off CAL Statue OK ENI Statue Table Average 50 J 10 | Trace Balact |
|--------------|-------------------------------|-----------------------------|---|-----------------------------|
| | quency 0 000Hz | Noise Figure 2.09268dB 1 | Gain 4.55470dB | Result Type Noise Figure |
| Noise Figure | | NF Max | 2.12025dB | |
| NF Current | 2.08287d | B NF Min | 2.06244dB | |
| NF Average | 2.09268d | B NF Max to Min | 0.05781dB | |
| | | | | Reference 3.00dfl |
| | | | | Scale/Div 1.000dB |

Measurement Result: Example of Spot display (Frequency Mode: Fixed)

Other Measurement Functions

BER Measurement Function (MS2840A-026)

The MS2840A with the BER Measurement Function MS2840A-026 supports measurement up to 10 Mbps.

It supports Rx sensitivity tests by inputting the receiverdemodulated Data/Clock/Enable to the back of the MS2840A.

- Input Signal: Data, Clock, Enable (Polarity reversal supported)
- Input Bit Rate: 100 bps to 10 Mbps
- Input Level: TTL 3.3 V
- Connector: Rear panel, AUX connector*

*****: Can convert to BNC by connecting AUX conversion adapter (J1556A).

• Measured Patterns:

PN9, PN11, PN15, PN20, PN23, ALL0, ALL1, Alternate (0101...), PN9Fix, PN11Fix, PN15Fix, PN20Fix, PN23Fix, UserDefine (4096 bits max.)

- Measurable Bit Count: 1000 to 4294967295 bits (2³² 1 bits)
- Measurable Error Bit Count: 1 to 2147483647 bits (2³¹ 1 bits)
- Count Mode

Data: Measures until specified Data count Error: Measures until specified Error count

Measurement Mode

Single: Measures specified measurement bit count once Continuous: Repeats Single measurement

Endless: Continues measurement to upper limit of measurement bits



BER Measurement Function Main Screen



BER Measurement Setup Example (using external vector signal generator)

Measurement Software Options

Vector Modulation Analysis Software (MX269017A)

This software measures the modulation accuracy, carrier frequency, Tx power, etc., for each type of digital radio.

Supported Modulation Methods

Standard

BPSK, QPSK, O-QPSK, π/4DQPSK, 8PSK, 16QAM, 32QAM, 64QAM, 128QAM, 256QAM, 2FSK, 4FSK, 2ASK, 4ASK, H-CPM*, MSK \star : Used for APCO-P25 Phase2 Inbound measurement APSK Analysis (MX269017A-001) 16APSK, 32APSK

Higher-Order QAM Analysis (MX269017A-011) 512QAM, 1024QAM, 2048QAM

Frequency Setting Range

100 kHz to 44.5 GHz (300 MHz to 6 GHz depending on measured symbol rate)



Measurement Screen

Analog Measurement Software (MX269018A)

When this software is installed in the MS2840A, the Tx performance (carrier frequency, Tx power, modulation rate/frequency deviation, demodulation frequency, demodulation signal distortion rate, etc.) of analog radios can be measured.

- * The Audio Analyzer and Analog Signal Generator cannot be installed in the MS2840A.
- * This software cannot be installed in the MS2830A 26.5 GHz/43 GHz models, but can be installed in the MS2840A 26.5 GHz/44.5 GHz models.

Supported Modulations AM, FM, ΦM

Frequency Range

100 kHz to 2700 MHz (At Wide Band FM measurement: 10 MHz to 2700 MHz)

Weighting Filter

CCITT, C-Message, CCIR 468, CCIR-ARM, A-Weighting

De-emphasis 25, 50, 75, 500, 750 µs



Refer to the MX2690xxA Series Measurement Software catalog for details.

Measurement Software Options/Other Options

Pulse Radar Measurement Function (MX284059A)

This function measures the transmission characteristics of a pulse radar device. (Transmission power, transmission frequency, pulse time, 40 dB bandwidth, spurious, occupied frequency bandwidth)

Pulse Type

Non-FM Pulse Radar/FM Pulse Radar

Measurement Frequency Range

MS2840A-044: 300 MHz to 26,500 MHz MS2840A-046: 300 MHz to 36,000 MHz

★ Spurious measurement range is from 30 MHz to the upper limit of the main unit frequency.

Pulse Width

0.5 µs to 500 µs

Pulse Repetition interval

0.05 ms to 5.0 ms (PRF = 200 Hz to 20,000 kHz)

Rubidium Reference Oscillator (MS2840A-001)

This option is a 10-MHz reference crystal oscillator with excellent frequency stability startup characteristics of $\pm 1 \times 10^{-9}$ at 7 minutes after power-on.

Aging Rate: $\pm 1 \times 10^{-10}$ /month, $\pm 1 \times 10^{-9}$ /year Start-up Characteristics: $\pm 1 \times 10^{-9}$ (7 minutes after power-on)

Rubidium Reference Oscillator (MS2840A-037)

This option is a 10-MHz reference crystal oscillator with excellent frequency stability startup characteristics of $\pm 1 \times 10^{-9}$ at 15 minutes after power-on.

Aging Rate: $\pm 1 \times 10^{-10}$ /month, $\pm 1 \times 10^{-9}$ /year Start-up Characteristics: $\pm 1 \times 10^{-9}$ (15 minutes after power-on)

Preamplifier (MS2840A-008)

This option is for the 26.5 GHz/44.5 GHz models (MS2840A-044/046) and the 3.6 GHz/6 GHz models (MS2840A-040/041).

The gain of about 20 dB improves the Displayed Average Noise Level (DANL). This preamplifier is used to measure low-level signals such as noise and interference.

Frequency Range: 100 kHz to 6 GHz

26.5 GHz Microwave Preamplifier (MS2840A-069)

This option is for the 26.5 GHz model (MS2840A-044). The gain of about 20 dB improves the Displayed Average Noise Level (DANL). This preamplifier is used to measure low-level signals, such as noise and interference.

Frequency Range: 100 kHz to 26.5 GHz

Microwave Preamplifier (MS2840A-068)

This option is for the 44.5 GHz model (MS2840A-046). The gain of about 20 dB improves the Displayed Average Noise Level (DANL). This preamplifier is used to measure low-level signals, such as noise and interference.

Frequency Range: 100 kHz to 44.5 GHz

2ndary SSD (MS2840A-011)

This removable SSD is for storing user data. It has no installed OS. It is shipped mounted in the Secondary HDD/ SSD slot of the MS2840A main unit.

Microwave Preselector Bypass (MS2840A-067)

Bypassing the preselector used for the microwave band improves RF frequency characteristics and in-band frequency characteristics. Add this option when the signal analyzer measurement function is set to a frequency band of >31.25 MHz and a frequency of >6 GHz.

2 dB Step Attenuator for Millimeter-wave (MS2840A-019)

This option is for the 44.5 GHz model (MS2840A-046). The attenuator resolution is expanded to 2 dB (Standard resolution is 10 dB) and input level to internal mixer can be adjusted with high resolution. As a result, the radio test products using micro and millimeter wave which require wide dynamic range can be measured with a sufficient margin.

Noise Floor Reduction (MS2840A-051)

The Noise Floor Reduction (NFR) function increases the measurement accuracy for low-level signals. It subtracts the internal noise components (11 dB max. nominal) of the measuring instrument itself from the displayed measurement result.

When the NFR function is used with a connected external mixer (High Performance Waveguide Mixer MA2806A/MA2808A), it measures V- and E-band millimeter waveband applications with high dynamic range.

<Main Applications>

- Spurious Emission
- Spectrum Mask
- Adjacent Channel Leakage Power (ACLR)
- Power ON/OFF ratio

Measurement times using the NFR function remain unchanged. The NFR function eliminates the procedure of measuring the instrument noise floor each time like using the earlier noise cancelling function. If the noise floor is measured once when an ambient temperature change affects the noise floor level or when an external mixer is connected, the NFR effect can be captured by the same operation as normal measurement, unless there is a change in these conditions.

[Notes]

The NFR function is enabled only by the Spectrum Analyzer function. The design value is nominal and is not a guaranteed specification.



Measurement Screen

ООО "Техэнком" Контрольно-измерительные приборы и оборудование www.tehencom.com

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models) Functions

High Performance Waveguide Mixer/External Mixers (Harmonic Mixers)

Two types of mixer can be connected to the MS2840A series (26.5 GHz/44.5 GHz models) for millimeter-wave-band measurements; spectrum measurements up to 325 GHz are supported using either a High-Performance Waveguide Mixer or an external harmonic mixer. In particular, the two High Performance Waveguide Mixer models are ideal for measuring wideband signals and the excellent phase noise performance of the MS2840A series (26.5 GHz/44.5 GHz models)plays a key role in analyzing the true spectrum of millimeter-wave-band transmitters.

High Performance Waveguide Mixer MA2806A/MA2808A

| Model | Name | Frequency Band | Frequency Range | Waveguide | Flange |
|---------|---|-------------------|---------------------|-----------|----------|
| MA2806A | High Performance Waveguide Mixer (50 to 75 GHz) | V band | 50 GHz to 75 GHz | WR15 | UG-385/U |
| MA2808A | High Performance Waveguide Mixer (60 to 90 GHz) | E band | 60 GHz to 90 GHz | WR12 | UG-387/U |

Features

- Wide dynamic range based on excellent minimum sensitivity and P1dB performance
- High phase noise performance connected to MS2840A
- Image-response-free measurement of wideband signals plus high IF frequency and PS function



The MA2806A and MA2808A have a dedicated multiplier, amplifier, bandpass filter, etc., supporting an excellent conversion loss of at least 10 dB better than conventional harmonic mixers, as well as P1dB performance exceeding 0 dBm. When used in combination with the MS2840A series (26.5 GHz/44.5 GHz models) the display average noise performance level is excellent at –150 dBm/Hz (meas.)* at 75 GHz. Due to this wide dynamic range, the MA2806A and MA2808A support evaluation of the true spurious performance of wider-band, millimeter-wave wireless transmitters as well as various types of millimeter-wave equipment, such as automotive radar, wireless backhaul and gigabit wireless LAN (IEEE 802.11ad/WiGig) etc., that cannot be evaluated accurately using conventional harmonic-mixer and down-converter methods.

Moreover, by using the high IF frequency (1.8755 GHz) of the MS2840A series (26.5 GHz/44.5 GHz models), spectrum mask measurements can be made over a wide measurement span with no impact from image-response effects. Spectrum mask measurements require measurement over a wider measurement span than the bandwidth of the signal to be measured. For example, when using the MA2806A and MA2808A to measure a signal with a bandwidth of 1 GHz, no image response occurs in a wide measurement span covering 6.5 GHz. Moreover, no image response occurs in a measurement span of 5.5 GHz for a signal with a bandwidth of 2 GHz. Additionally, use of the newly developed PS function supports image-response-free measurements over a measurement span of up to 7.5 GHz, irrespective of the measured signal bandwidth.

Additionally, connecting these mixers to the MS2840A series (26.5 GHz/44.5 GHz models) supports measurements using its excellent high phase noise performance of

-100 dBc/Hz in the 79 GHz band (10 kHz offset frequency, meas.*) for evaluating the intrinsic phase noise performance of millimeterwaveband devices, such as automotive radar.

Connection to the MS2840A series (26.5 GHz/44.5 GHz models) is as easy as simply connecting a cable to the IF port. Conversion loss data saved in a USB memory stick is loaded into the MS2840A series (26.5 GHz/44.5 GHz models) for reflection in the measured values.

*****: Value measured at design but not guaranteed specification.



Phase Noise Measurement 79 GHz Measurement Frequency (using High Performance Waveguide Mixer MA2808A)



Simple Connection



High Performance Waveguide Mixer/External Mixers (Harmonic Mixers)

Measurement Method Performance Comparison



*1: High noise floor level and narrow dynamic range due to high mixer conversion order

+2: Low IF frequency depending on spectrum analyzer causes occurrence of image response generated in measurement range

+3: Narrow dynamic range due to mixer P1dB performance of only -10 to -5 dBm

*4: Different calibration procedure depending on spectrum analyzer used

+5: Requires mixer conversion loss data for measurement range because any IF frequency can be set

External Mixers (Harmonic Mixers)

The MA2740C/MA2750C series of external mixers (harmonic mixers) supports spectrum measurements up to 325 GHz with excellent cost performance.

| Model | Name | Frequency Band | Frequency Range | Waveguide | Flange |
|---------|----------------|----------------|--------------------|-----------------------|----------------------|
| MA2741C | External Mixer | A Band | 26.5 GHz to 40 GHz | WR28 | MIL-DTL-3922/54-003 |
| MA2742C | External Mixer | Q Band | 33 GHz to 50 GHz | WR22 | MIL-DTL-3922/67D-006 |
| MA2743C | External Mixer | U Band | 40 GHz to 60 GHz | 40 GHz to 60 GHz WR19 | |
| MA2744C | External Mixer | V Band | 50 GHz to 75 GHz | WR15 | MIL-DTL-3922/67D-008 |
| MA2745C | External Mixer | E Band | 60 GHz to 90 GHz | WR12 | MIL-DTL-3922/67D-009 |
| MA2746C | External Mixer | W Band | 75 GHz to 110 GHz | WR10 | MIL-DTL-3922/67D-010 |
| MA2747C | External Mixer | F Band | 90 GHz to 140 GHz | WR08 | MIL-DTL-3922/67D-M08 |
| MA2748C | External Mixer | D Band | 110 GHz to 170 GHz | WR06 | MIL-DTL-3922/67D-M06 |
| MA2749C | External Mixer | G Band | 140 GHz to 220 GHz | WR05 | MIL-DTL-3922/67D-M05 |
| MA2750C | External Mixer | Y Band | 170 GHz to 260 GHz | WR04 | MIL-DTL-3922/67D-M04 |
| MA2751C | External Mixer | J Band | 220 GHz to 325 GHz | WR03 | MIL-DTL-3922/67D-M03 |

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models) Key Layout

Front Panel



Power switch

Press to switch between the standby state in which AC power is supplied and the Power On state in which the MS2840A is under operation. The Power lamp lights up orange in the standby state, and lights up green in the Power On state. Press the power switch for a reasonably long duration (for about two seconds).

2 1st Local Output connector

Supplies local signal and bias current to External Mixer and High Performance Waveguide Mixer and receives frequency-converted IF signals

SSD lamp

Lights when the MS2840A internal solid state drive is being accessed.

4 Copy key

Press to capture a screen image from the display and save it to a file.

5 Recall key

Press to recall a parameter file.

6 Save key

Press to save a parameter file.

🔽 Cal key

Press to display the calibration execution menu.

8 Local key

Press to return to local operation from remote control operation through GPIB, Ethernet or USB (B), and enable panel settings.

9 Remote lamp

Lights up when the MS2840A is in a remote control state.

10 Preset key

Resets parameters to their initial settings.

11 Function keys

Used for selecting or executing function menu displayed on the right of the screen. The function menu contents are provided in multiple pages and layers.

12 Application key

Press to switch between applications.

13 Shift key

Used to operate any keys with functions described in blue characters on the panel. First press the Shift key, then press the target key when the Shift key lamp lights up green.

14 Main function keys 2

Used to set or execute main functions of the MS2840A. Executable functions vary depending on the application currently selected.

Botary knob/Cursor keys/Enter key/Cancel key The rotary knob and cursor keys are used to select display items or change settings.

16 Main function keys 1

Used to set or execute main functions of the MS2840A. Executable functions vary depending on the application currently selected.

17 RF Input connector

Used for inputting RF signal. N-J, 50Ω (MS2840A-044) K-J, 50Ω (MS2840A-046)

18 Numeric keypad

Used to enter numbers on parameter setup screens.

19 USB connector (type A)

Used to connect a USB keyboard or mouse or the USB memory supplied with the MS2840A.

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models) Key Layout

Rear Panel



2 AC inlet

Used for supplying power.

21 USB connectors (type A)

Used to connect a USB keyboard or mouse or the USB memory supplied with the MS2840A.

- USB connector (type B) Used when controlling the MS2840A externally via USB.
- 23 LAN (Ethernet) connector Used for connecting to personal computer to implement external control over LAN or for Ethernet connection.

24 Monitor Out connector

Used for connection with an external display.

25 Primary HDD/SSD slot This is a solid state drive slot.

26 AUX connector (For MS2840A-026)

Composite connector for BER measurement function options with BER measurement Clock, Data, and Enable inputs. Converted to BNC using AUX Conversion Adapter*. *: The Aux Conversion Adapter J1556A is a standard accessory supplied with the BER Measurement Function MS2840A-026.

2 Secondary HDD/SSD slot

This is a solid state drive slot for options.

28 Ref Input connector

(reference frequency signal input connector) Inputs an external reference frequency signal (5/10/ 13 MHz). It is used for inputting reference frequency signals with accuracy higher than that of those inside the MS2840A, or for synchronizing the frequency of the MS2840A to that of other device.

29 Buffer Out connector

(reference frequency signal output connector)

Outputs the reference frequency signal (10 MHz) generated inside the MS2840A. It is used for synchronizing the frequencies between other devices and the MS2840A based on the reference frequency signal output from this connector.

30 SA Trigger Input connector

This is a BNC connector used to input the external trigger signal (TTL) for the Spectrum Analyzer or Signal Analyzer application.

31 Sweep Status Out connector

Outputs a signal that is enabled when an internal measurement is performed or measurement data is obtained.

32 GPIB connector

Used when controlling the MS2840A externally via GPIB.

33 Noise Source Drive connector

Supply (+28 V) of the Noise Source Drive. This is available when the MS2840A-017/117 is installed.

34 IF Output connector

Monitor output of internal IF signal Connector: SMA-J, 50Ω IF Output Frequency: 1.8755 GHz

Configuration List

| | Name | Remarks |
|-----------------|--|---|
| IS2840A Sig | gnal Analyzer | |
| IS2840A-044 26 | 5.5 GHz Signal Analyzer | Analysis Bandwidth 31.25 MHz installed as standard |
| IS2840A-046 44 | l.5 GHz Signal Analyzer | |
| IS2840A-001 Ru | Ibidium Reference Oscillator | Option |
| IS2840A-037 Ru | Ibidium Reference Oscillator | Option |
| IS2840A-077 An | alysis Bandwidth Extension to 62.5 MHz | Option |
| IS2840A-078 An | alysis Bandwidth Extension to 125 MHz | Option, requires MS2840A-077 |
| IS2840A-008 Pre | eamplifier | Option, Frequency Range: 100 kHz to 6 GHz |
| IS2840A-069 26 | 5.5 GHz Microwave Preamplifier | Option, For MS2840A-044, Frequency Range: 100 kHz to 26.5 GHz |
| IS2840A-068 Mi | icrowave Preamplifier | Option, For MS2840A-046, Frequency Range: 100 kHz to 44.5 GHz |
| IS2840A-010 Ph | nase Noise Measurement Function | Option |
| IS2840A-011 2n | ndary SSD | Option |
| IS2840A-016 Pre | ecompliance EMI Function | Option |
| IS2840A-017 No | pise Figure Measurement Function | Option |
| /S2840A-019 2 c | dB Step Attenuator for Millimeter-wave | Option, For MS2840A-046 |
| IS2840A-026 BE | R Measurement Function | Option, AUX Conversion Adapter J1556A as standard accessory |
| IS2840A-051 No | oise Floor Reduction | Option |
| 1S2840A-067 Mi | icrowave Preselector Bypass | Option, Add this option when the signal analyzer measurement function is set to a frequency band of >31.25 MHz and a frequency of >6 GHz. |

The following options are installed as standard and do not require separate orders when ordering the MS2840A-044. MX269000A

Standard Software

Analysis Bandwidth 10 MHz

Bandwidth Extension to 31.25 MHz

orders when ordering the MS2840A-046. Standard Software MX269000A Analysis Bandwidth 10 MHz MS2840A-006 Bandwidth Extension to 31.25 MHz for Millimeter Wave MS2840A-009

List of Retrofit Options

The following hardware options can be retrofitted. Add to the retrofit options at ordering and also order the Z1932A Retrofit Kit. In addition, the MS2840A main unit must be returned to the Anritsu plant for remodelling when retrofitting hardware options.

MS2840A-006

MS2840A-005

| Model | Name | Remarks |
|-------------|---|---|
| MS2840A-101 | Rubidium Reference Oscillator Retrofit | |
| MS2840A-137 | Rubidium Reference Oscillator Retrofit | |
| MS2840A-177 | Analysis Bandwidth Extension to 62.5 MHz Retrofit | |
| MS2840A-178 | Analysis Bandwidth Extension to 125 MHz Retrofit | Requires MS2840A-077 or -177 |
| MS2840A-108 | Preamplifier Retrofit | Frequency Range: 100 kHz to 6 GHz |
| MS2840A-169 | 26.5 GHz Microwave Preamplifier Retrofit | For MS2840A-044, Frequency Range: 100 kHz to 26.5 GHz |
| MS2840A-168 | Microwave Preamplifier Retrofit | For MS2840A-046, Frequency Range: 100 kHz to 44.5 GHz |
| MS2840A-110 | Phase Noise Measurement Function Retrofit | |
| MS2840A-111 | 2ndary SSD Retrofit | |
| MS2840A-116 | Precompliance EMI Function Retrofit | |
| MS2840A-117 | Noise Figure Measurement Function Retrofit | |
| MS2840A-119 | 2 dB Step Attenuator for Millimeter-wave Retrofit | Option, For MS2840A-046 |
| MS2840A-126 | BER Measurement Function Retrofit | AUX Conversion Adapter J1556A as standard accessory |
| MS2840A-151 | Noise Floor Reduction Retrofit | Option |
| | | Add this option when the signal analyzer measurement function is set to a frequency band of >31.25 MHz and a frequency of >6 GHz. |

Software

The following software can be retrofitted. Add to the required software at ordering and also order the Z1932A Retrofit Kit.

| Model | Name | Remarks |
|---|-------------------------------------|---|
| MX269017A | Vector Modulation Analysis Software | |
| MX269017A-001 | APSK Analysis | Requires Vector Modulation Analysis Software MX269017A |
| MX269017A-011 Higher-Order QAM Analysis | | Requires Vector Modulation Analysis Software MX269017A |
| MX269018A | Analog Measurement Software | Requires USB Audio A0086C |
| MX284059A | Pulse Radar Measurement Function | Unavailable to install simultaneously with MS2840A-069, MS2840A-068, MS2840A-067 (To keep a margin for spurious measurement) Requires MS2840A-019 when mounted on MS2840A-046 |

Mixer (External)

| Model | Name | Remarks |
|---------|---|----------------|
| MA2606A | High Performance Waveguide Mixer (50 to 75 GHz) | |
| MA2608A | High Performance Waveguide Mixer (60 to 90 GHz) | |
| MA2741C | External Mixer (26.5 to 40 GHz) | Harmonic Mixer |
| MA2742C | External Mixer (33 to 50 GHz) | Harmonic Mixer |
| MA2743C | External Mixer (40 to 60 GHz) | Harmonic Mixer |
| MA2744C | External Mixer (50 to 75 GHz) | Harmonic Mixer |
| MA2745C | External Mixer (60 to 90 GHz) | Harmonic Mixer |
| MA2746C | External Mixer (75 to 110 GHz) | Harmonic Mixer |
| MA2747C | External Mixer (90 to 140 GHz) | Harmonic Mixer |
| MA2748C | External Mixer (110 to 170 GHz) | Harmonic Mixer |
| MA2749C | External Mixer (140 to 220 GHz) | Harmonic Mixer |
| MA2750C | External Mixer (170 to 260 GHz) | Harmonic Mixer |
| MA2751C | External Mixer (220 to 325 GHz) | Harmonic Mixer |

Hardware Configuration

Frequency range (MS2840A-040/041/044/046) not upgradable.

| | | | | | | | | | | | | | | ✓ = | Can | ı be | insta | alled, | No : | = Ca | nno | t be | ins | talle | d, R | ≀ = R | lequi | re, l | J = U | pgra | ıde |
|------|---|----------|---------------------|---------------------|---------------------|---------------------|----------|-------------|-------------------------------|------------------------|------------------------|--------------|-----|-------------|----------|--------------|----------|--------|--------------|--------------|----------|----------|----------|----------|------|----------|------------|--------------|--------------|-----------|----------------------|
| | | | Ado | lition to | Main fra | ame | | | | | | | C | omb | oina | tion | with | n "Op | t." (F | Refe | r to | the | left | line) | | | | | | | |
| Opt. | Name | Retrofit | 040 (3.6 GHz) | 041 (6 GHz) | 044 (26.5 GHz) | 046 (44.5 GHz) | 001 | 037 | 002 005 (standard install) | 006 (standard install) | 009 (standard install) | 077 | 078 | 008 | 069 | 068 | 019 | 011 | 016 | 017 | 026 | 051 | 066 | 067 | 020 | 021 | 189 022 | 027 | 028 | 088 | 029 |
| 001 | Rubidium Reference Oscillator | Yes | ~ | ~ | ~ | ~ | \times | No | *4 | | | | | | | | | | | | | | | | | | | | | | |
| 037 | Rubidium Reference Oscillator | Yes | ✓ | ✓ | ~ | ✓ | No | \boxtimes | *4 | | | | | | | | | | | | | | | | | | | | | | |
| 002 | High Stability Reference Oscillator | Yes | ~ | ~ | | /alent installed | *4 | *4 | X | | No | | | | No | No | No | | | | | | | No | | | | | | | |
| 005 | Analysis Bandwidth Extension to 31.25 MHz | - | Standard install | Standard install | Standard install | No | | | | (| No | | | | | No | | | | | | | | | | | | | | | |
| 006 | Analysis Bandwidth 10 MHz | - | Standard install | Standard install | Standard install | Standard install | | | | (| \mathbb{N} | | | | | | | | | | | | | | | | | | | | |
| | Bandwidth Extension to 31.25 MHz for Millimeter-wave | - | No | No | No | Standard install | | | No N | ٥X | \mathbb{N} |] | | | | | | | | | | | No | Ν | 101 | NO | | oNc | No | No | No |
| 077 | Analysis Bandwidth Extension to 62.5 MHz*1 | Yes | ~ | ~ | ~ | ~ | | | | $\langle \rangle$ | \mathbb{X} | \mathbb{X} | | | | | | | | | | | | | | | | | | | |
| 078 | Analysis Bandwidth Extension to 125 MHz* ¹ | Yes | ~ | ~ | ~ | ~ | | | | $\langle \rangle$ | \mathbb{X} | R | Х | | | | | | | | | | | | | | | | | | |
| 008 | Preamplifier | Yes | ~ | ~ | ~ | ~ | | | Í | Ť | Ĩ | 1 | | \boxtimes | *2 | *2 | | | | | | | | | | | | T | | | |
| 069 | 26.5 GHz Microwave Preamplifier | Yes | No | No | √ | No | | | No | | No | | | *5 | \times | No | | | | | | | No | N | 101 | NON | No No | o No | No | Nol | No |
| 068 | Microwave Preamplifier | Yes | No | No | No | ~ | | | No | No | b | | | *5 | No | \mathbf{X} | | | | | | | No | N | 101 | NON | No No | οΝα | No | Nol | No |
| 019 | 2 dB Step Attenuator for Millimeter-wave | Yes | No | No | No | ✓ | | | No | No |) | | | | No | | \times | | | | | | No | Ν | 101 | NON | No No | o No | No | Nol | No |
| 010 | Preamplifier | Yes | ~ | ~ | ~ | ~ | | | | | | | | | | ľ | | | | | | | | | | | | T | | \square | |
| 011 | 2ndary SSD | Yes | ~ | ~ | √ | ✓ | | | | | | | | | | | Í | | 1 | | | | | | | | | | | | |
| 016 | Precompliance EMI Function | Yes | ~ | ~ | ~ | ~ | | | | | | | | | | | | Í | \mathbf{X} | | | | | | | | | T | | \square | |
| 017 | Noise Figure Measurement Function | Yes | ~ | ~ | ~ | ~ | | | | | | | | U | U | U | | | | \mathbf{X} | | | | | | | | | | | |
| 026 | BER Measurement Function | Yes | ~ | ~ | ~ | ~ | | | | | | | | | | | | | | | \times | | | | Т | Т | T | T | \square | | ٦ |
| 051 | Noise Floor Reduction | Yes | ✓ | ✓ | ✓ | ~ | | | | | | | | | | | | | | | | \times | | | | | | | | | |
| 066 | Low Phase Noise Performance | Yes | ~ | ~ | No | No | | | | | No | | | | No | No | | | | | | | \times | No | Т | Т | T | T | \square | | ٦ |
| 067 | Microwave Preselector Bypass | Yes | No | No | ✓ | ~ | | | No | | | | | | | | | | | | | | No | \times | 101 | NON | | o No | No | Nol | No |
| 020 | 3.6 GHz Vector Signal Generator | Yes | ~ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No | Źī | NoN | ٩o | T | \square | No | ٦ |
| 021 | 6 GHz Vector Signal Generator | Yes | ✓ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | NoN | 10 | \times | lo | | | No | |
| 189 | Vector Function Extension for Analog Signal Generator Retrofit | Yes | ~ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No N | 101 | NO | N | 0 | | RM | No |
| 022 | Low Power Extension for Vector Signal Generator | Yes | ✓ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No | R | N | Vol | | | No | |
| | ARB Memory Upgrade 256 Msa for Vector Signal Generator* ² | Yes | ~ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No | | R | | \mathbf{b} | | | |
| 028 | AWGN* ² | Yes | ✓ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No | | R | | Ť | \mathbf{X} | | |
| 088 | 3.6 GHz Analog Signal Generator* ³ | Yes | ~ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No N | 101 | No | No | 0 | | 1X | No |
| 029 | Analog Function Extension for Vector Signal Generator* ³ | Yes | ~ | ~ | No | No | | | | | No | | | | No | No | | | | | | | | No | R | ٢ | No R | | | No | $\overline{\langle}$ |

*****1: An image response is received when setting the bandwidth to more than 31.25 MHz.

This can be used when not inputting a signal frequency outside the MS2840A analysis bandwidth (125 MHz max.).

The Signal Analyzer series MS2690A/91A/92A is recommended for other measurement purposes.

+2: The ARB Memory Upgrade 256 Msa for Vector Signal Generator (MS2840A-027) and AWGN (MS2840A-028) are non-functional in the Analog Signal Generator (MS2840A-029/088).

+3: Requires Analog Measurement Software (MX269018A).

+4: The Rubidium Reference Oscillator can be retrofitted to the MS2840A-040/041 with installed High Stability Reference Oscillator.

In this case, the Rubidium Reference Oscillator is functional.

*5: The 26.5 GHz Microwave Preamplifier or Microwave Preamplifier can be retrofitted to the MS2840A-044/046 with installed Preamplifier. In this case, the 26.5 GHz Microwave Preamplifier or Microwave Preamplifier are functional.

Software Configuration

| \checkmark = Can be installed, No = Cannot be installed, R = Require, U = Upgrade | | | | | | | | | | | |
|---|-------------------------------------|---------------|-------------|----------------|-----------------------|----------------|---------------|--|--|--|--|
| Model | Name | | Addition to | | Analysis Bandwidth | | | | | | |
| | | 040 (3.6 GHz) | 041 (6 GHz) | 044 (26.5 GHz) | 046 (44.5 GHz) | 077 (62.5 MHz) | 078 (125 MHz) | | | | |
| MX269017A | Vector Modulation Analysis Software | ~ | ~ | ~ | ~ | ~ | ✓ | | | | |
| MX269017A-001 | APSK Analysis | ~ | ~ | ~ | ~ | ~ | ✓ | | | | |
| MX269017A-011 | Higher-Order QAM Analysis | √ | ~ | ~ | ~ | ~ | ✓ | | | | |
| MX269018A | Analog Measurement Software* | ✓ | ~ | ~ | ~ | | | | | | |
| MX284059A | Pulse Radar Measurement Function | No | No | ~ | ~ | | | | | | |

*: Requires USB Audio A0086C

Refer to the MS2840A Data Sheet for more details.

Frequency Range

9 kHz to 26 .5 GHz (MS2840A-044) 9 kHz to 44 .5 GHz (MS2840A-046)

Aging Rate

 $\pm 1 \times 10^{-7}$ /year (standard) $\pm 1 \times 10^{-10}$ /month, $\pm 1 \times 10^{-9}$ /year (with Rubidium Reference Oscillator MS2840A-001/037 installed)

Maximum Input Level

Average total power: +30 dBm (Input attenuator: ≥10 dB, Preamp: Off)

Resolution Bandwidth (RBW)

Spectrum Analyzer Function

Setting Range: 1 Hz to 3 MHz (1–3 sequence), 500 Hz, 50 kHz, 2 MHz, 5 MHz, 10 MHz, 20 MHz [At Zero SPAN: 30 Hz to 3 MHz (1–3 sequence), 50 kHz, 5 MHz,

10 MHz, 20 MHz, 31.25 MHz]

Video Bandwidth (VBW)

Spectrum Analyzer Function Setting Range: 1 Hz to 3 kHz (1-3 sequence), 5 kHz, 10 kHz to 10 MHz (1-3 sequence), off VBW Mode: Video Average, Power Average

SSB Phase Noise

Spectrum Analyzer Function

| Input Frequency | Carrier Offset | SSB Phase Noise | | | | | |
|-----------------|----------------|--------------------|--|--|--|--|--|
| | 10 Hz | –80 dBc/Hz (nom.) | | | | | |
| | 100 Hz | –92 dBc/Hz (nom.) | | | | | |
| | 1 kHz | –117 dBc/Hz (nom.) | | | | | |
| 1 GHz | 10 kHz | –123 dBc/Hz | | | | | |
| | 100 kHz | –123 dBc/Hz | | | | | |
| | 1 MHz | –135 dBc/Hz | | | | | |
| | 10 MHz | –148 dBc/Hz (nom.) | | | | | |



Phase Noise Performance (meas.)

Displayed Average Noise Level (DANL)

Spectrum Analyzer Function

Preamp: None, Microwave Preselector Bypass: None

| | | DANL | | | | | | |
|-----------|-----------------|--------------------------|------------------|--|--|--|--|--|
| Frequency | 26 .5 GHz Model | 44 .5 GHz Model | (MS2840A-046) | | | | | |
| | (MS2840A-044) | Without MS2840A-019 | With MS2840A-019 | | | | | |
| 30 MHz | –153 dBm/Hz | –153 dBm/Hz | –153 dBm/Hz | | | | | |
| 400 MHz | –153 dBm/Hz | –153 dBm/Hz | –153 dBm/Hz | | | | | |
| 1 GHz | –150 dBm/Hz | –150 dBm/Hz | –150 dBm/Hz | | | | | |
| 3 GHz | –147 dBm/Hz | –147 dBm/Hz | –147 dBm/Hz | | | | | |
| 13 GHz | –151 dBm/Hz | –151 dBm/Hz | –150 dBm/Hz | | | | | |
| 20 GHz | –146 dBm/Hz | –146 dBm/Hz | –146 dBm/Hz | | | | | |
| 30 GHz | — | –146 dBm/Hz | –146 dBm/Hz | | | | | |
| 40 GHz | — | — – –144 dBm/Hz –142 dBr | | | | | | |
| 44 GHz | — | –140 dBm/Hz | –137 dBm/Hz | | | | | |

Preamp: On, Microwave Preselector Bypass: None

| | DANL | | |
|-----------|----------------------------------|-------------------------------|------------------|
| Frequency | 26 .5 GHz Model (MS2840A-044) | 44 .5 GHz Model (MS2840A-046) | |
| | | Without MS2840A-019 | With MS2840A-019 |
| 30 MHz | –166 dBm/Hz | –166 dBm/Hz | –166 dBm/Hz |
| 400 MHz | –166 dBm/Hz | –166 dBm/Hz | –166 dBm/Hz |
| 1 GHz | –164 dBm/Hz | –164 dBm/Hz | –164 dBm/Hz |
| 3 GHz | –163 dBm/Hz | –163 dBm/Hz | –163 dBm/Hz |
| 13 GHz | –163 dBm/Hz | –163 dBm/Hz | –163 dBm/Hz |
| 20 GHz | –157 dBm/Hz | –160 dBm/Hz | –160 dBm/Hz |
| 30 GHz | — | –160 dBm/Hz | –159 dBm/Hz |
| 40 GHz | _ | –157 dBm/Hz | –156 dBm/Hz |
| 44 GHz | _ | –149 dBm/Hz | –149 dBm/Hz |

Noise Floor Reduction: On

It subtracts the internal noise components (11 dB max. nominal) of the measuring instrument itself from the displayed measurement result.

Total Absolute Amplitude Accuracy

Preamp: None $\pm 0.5 \text{ dB} (300 \text{ kHz} \le f < 4 \text{ GHz})$ $\pm 1.8 \text{ dB} (4 \text{ GHz} \le f < 13.8 \text{ GHz})$ $\pm 3.0 \text{ dB} (13.8 \text{ GHz} \le f < 40 \text{ GHz})$ $\pm 3.5 \text{ dB} (40 \text{ GHz} \le f < 44.5 \text{ GHz}, \text{ nom.})$

The MS2840A supports level calibration over a wide range of 300 kHz to 4 GHz using its built-in level calibration oscillator. The level accuracy standards include frequency characteristics, linearity and attenuator switching error. Consequently, the level including the above three errors can still be measured accurately even when the measurement frequency and built-in attenuator settings are changed.

2-tone 3rd-order Intermodulation Distortion

Preamp: None

| Frequency | 2-tone 3rd-order Intermodulation Distortion |
|-----------|---|
| 1 GHz | ≤-62 dBc (TOI = +16 dBm) |
| 20 GHz | ≤–56 dBc (TOI = +13 dBm) |
| 40 GHz | ≤–56 dBc (TOI = +13 dBm) (nom.) |

Second Harmonic Distortion

Preamp: None, Microwave Preselector Bypass: None, Frequency Band Mode: Spurious

| Input Frequency | Harmonic Distortion | SHI | Mixer Input Level |
|-----------------|------------------------|-----------------|-------------------|
| 400 MHz, 1 GHz | ≤–65 dBc | ≥+35 dBm | –30 dBm |
| 3 GHz | ≤-80 dBc | ≥+70 dBm | –10 dBm |
| 13 GHz | ≤-90 dBc | ≥+80 dBm | –10 dBm |
| 20 GHz | ≤–90 dBc (nom.) | ≥+80 dBm (nom.) | –10 dBm |

Analysis Bandwidth (Signal Analyzer Function)

31.25 MHz (Standard) 62.5 GHz (Option) 125 MHz (Option)

Connector

RF Input (Front panel) N–J, 50Ω (nom.): 26.5 GHz model (MS2840A-044) K–J, 50Ω (nom.): 44.5 GHz model (MS2840A-046) IF Output (Rear panel) SMA-J, 50Ω (nom.) Frequency: 1.8755 GHz Gain: –10 dB (nom., Input attenuator: 0 dB, Input frequency: 10 GHz) 1st Local Output (Front panel) For High Performance Waveguide Mixer and Harmonic Mixer SMA-J, 50Ω (nom.) Frequency: 5 GHz to 10 GHz (Local signal output) 1.8755 GHz (IF frequency) Local output level: ≥ +10 dBm (typ.) Bias current: Setting range 0.0 to 20.0 mA Resolution 0.1 mA

Dimensions and Mass

426 (W) × 177 (H) × 390 (D) mm (excluding projections) \leq 15.3 kg (with MS2840A-044 or 046 installed, excluding other options)

Power Supply

Power voltage: 100 V(ac) to 120 V(ac)/200 V(ac) to 240 V(ac) Frequency: 50 Hz to 60 Hz Power consumption: ≤350 VA (including all options) 220 VA (nom., with MS2840A-044 or 046 installed, excluding other options)

EU Standards (CE Marking)

EMC: 2014/30/EU, EN61326-1, EN61000-3-2 LVD: 2014/35/EU, EN61010-1 RoHS: 2011/65/EU, EN50581

OS

Windows 7 (64 bit)

 $\mathsf{Windows}^{\circledast}$ is a registered trademark of Microsoft Corporation in the USA and other countries.

Other company names, product names, service names, etc., are trademarks or registered trademarks of their respective owners.

High Performance Waveguide Mixer MA2806A/MA2808A Specifications

Frequency Range

MA2806A: 50 GHz to 75 GHz MA2808A: 60 GHz to 90 GHz

Maximum Input Level (CW)

+10 dBm

Conversion Loss

<15 dB (typ.)

1 dB Gain Compression (P1dB)

>0 dBm (typ.)

Connector

MA2806A: RF: Waveguide (WR15, UG-385/U), IF/LO: SMA-J MA2808A: RF: Waveguide (WR12, UG-387/U), IF/LO: SMA-J

Dimensions and Mass

134 (W) × 51 (H) × 229 (D) mm (excluding projections), <2 kg

Power Supply

Power voltage: 100 V(ac) to 120 V(ac)/200 V(ac) to 240 V(ac) Frequency: 50 Hz/60 Hz Power consumption: 40 VA

Typical (typ.): Performance not warranted. Most products meet typical performance.

Nominal (nom.): Values not warranted. Included to facilitate application of product.

Measured (meas.): Performance not warranted. Data actually measured from randomly selected measuring instruments.

Ordering Information

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models)

Please specify the model/order number, name and quantity when ordering. The names listed in the chart below are Order Names. The actual name of the item may differ from the Order Name.

| Model/Order No. | Name | |
|----------------------------|--|--|
| | Main frame | |
| MS2840A | Signal Analyzer | |
| | Standard accessories | |
| | Power Cord: 1 pc | |
| P0031A | USB Memory (≥ 1GB): 1 pc | |
| Z0541A | USB Mouse: 1 pc | |
| | Install DVD-ROM (Application software, | |
| | instruction manual DVD-ROM): 1 pc | |
| | Options | |
| MS2840A-044 | 26.5 GHz Signal Analyzer | |
| MS2840A-046 | 44.5 GHz Signal Analyzer | |
| MS2840A-001 | Rubidium Reference Oscillator Rubidium Reference Oscillator | |
| MS2840A-037 | | |
| MS2840A-077 | Analysis Bandwidth Extension to 62.5 MHz | |
| MS2840A-078 | Analysis Bandwidth Extension to 125 MHz (Requires MS2840A-077) | |
| MS2840A-008 | Preamplifier | |
| MS2840A-069 | 26.5 GHz Microwave Preamplifier (for MS2840A-044) | |
| MS2840A-068 | Microwave Preamplifier (for MS2840A-046) | |
| MS2840A-010 | Phase Noise Measurement Function | |
| MS2840A-011 | 2ndary SSD | |
| MS2840A-016 | Precompliance EMI Function | |
| MS2840A-017 | Noise Figure Measurement Function | |
| MS2840A-019 | 2 dB Step Attenuator for Millimeter-wave | |
| MC20404 051 | (for MS2840A-046) | |
| MS2840A-051 MS2840A-026 | Noise Floor Reduction BER Measurement Function | |
| WI32840A-020 | (AUX Conversion Adapter J1556A as standard accessory) | |
| MS2840A-067 | Microwave Preselector Bypass | |
| | Retrofit options | |
| MS2840A-101 | Rubidium Reference Oscillator Retrofit | |
| MS2840A-137 | Rubidium Reference Oscillator Retrofit | |
| MS2840A-177 | Analysis Bandwidth Extension to 62.5 MHz Retrofit | |
| MS2840A-178 | Analysis Bandwidth Extension to 125 MHz Retrofit (Requires MS2840A-077 or 177) | |
| NAC20404 400 | | |
| MS2840A-108 MS2840A-169 | Preamplifier Retrofit 26.5 GHz Microwave Preamplifier Retrofit | |
| WI32040A-109 | (for MS2840A-044) | |
| MS2840A-168 | Microwave Preamplifier Retrofit (for MS2840A-046) | |
| MS2840A-110 | Phase Noise Measurement Function Retrofit | |
| MS2840A-111 | 2ndary SSD Retrofit | |
| MS2840A-116 | Precompliance EMI Function Retrofit | |
| MS2840A-117 | Noise Figure Measurement Function Retrofit | |
| MS2840A-119 | 2 dB Step Attenuator for Millimeter-wave Retrofit | |
| | (for MS2840A-046) | |
| MS2840A-151 | Noise Floor Reduction Retrofit | |
| MS2840A-126 | BER Measurement Function Retrofit | |
| MS2840A-167 | (AUX Conversion Adapter J1556A as standard accessory) Microwave Preselector Bypass Retrofit | |
| | | |
| | Software options DVD-ROM with License and Operation manuals | |
| MX269017A | Vector Modulation Analysis Software | |
| MX269017A-001 | APSK Analysis | |
| MX269017A-011 | Higher-Order QAM Analysis | |
| MX269018A | Analog Measurement Software | |
| | (Requires USB Audio A0086C) | |
| MX284059A | Pulse Radar Measurement Function | |

| Model/Order No. | Name | |
|----------------------|---|--|
| | Warranty service | |
| MS2840A-ES210 | 2 years Extended Warranty Service | |
| MS2840A-ES310 | 3 years Extended Warranty Service | |
| MS2840A-ES510 | 5 years Extended Warranty Service | |
| | Manuals | |
| | Following operation manuals provided as hard copy | |
| W3812AE | MS2840A Operation Manual (Mainframe Operation) | |
| W2851AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual (Mainframe Remote Control) | |
| W3335AE | MS2830A/MS2840A Operation Manual | |
| | (Signal Analyzer Function Operation) | |
| W2853AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual | |
| | (Signal Analyzer Function Remote Control) | |
| W3336AE | MS2830A/MS2840A Operation Manual | |
| | (Spectrum Analyzer Function Operation) | |
| W2855AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual | |
| | (Spectrum Analyzer Function Remote Control) | |
| W3117AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual | |
| | (Phase Noise Measurement Function Operation) | |
| W3118AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual | |
| | (Phase Noise Measurement Function Remote Control) | |
| W3655AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual | |
| | (Noise Figure Measurement Function Operation) | |
| W3656AE | MS2690A/MS2691A/MS2692A/MS2830A and MS2840A | |
| | Operation Manual | |
| | (Noise Figure Measurement Function Remote control) | |
| W3305AE | MX269017A Operation Manual (Operation) | |
| W3306AE | MX269017A Operation Manual (Remote Control) | |
| W3555AE | MX269018A Operation Manual (Operation) | |
| W3556AE | MX269018A Operation Manual (Remote Control) | |
| W4029AE | MS2840A Signal Analyzer Operation Manual | |
| | (Pulse Radar Measurement) | |
| The following option | s are installed as standard and do not require separate | |
| orders when orderin | | |
| Standard Software | g the M320407 044. | |

Standard SoftwareMX269000AAnalysis Bandwidth 10 MHzMS2840A-006Bandwidth Extension to 31.25 MHzMS2840A-005

The following options are installed as standard and do not require separate orders when ordering the MS2840A-046.

| Standard Software | MX269000A |
|--|-------------|
| Analysis Bandwidth 10 MHz | MS2840A-006 |
| Bandwidth Extension to 31.25 MHz for Millimeter Wave | MS2840A-009 |

Ordering Information

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models)

| Model/Order No. | Name | | |
|-----------------|---|------|--|
| | High Performance Waveguide Mixer | | |
| MA2806A | High Performance Waveguide Mixer (50 to 75 GHz) | | |
| MA2808A | High Performance Waveguide Mixer (60 to 90 GHz) | | |
| | Standard accessories | | |
| Z1922A | MA2806A USB Memory | | |
| | (Saved conversion loss data, for MA2806A): | 1 pc | |
| Z1923A | MA2808A USB Memory | | |
| | (Saved conversion loss data, for MA2808A): | 1 pc | |
| Z1625A | AC Adapter: | 1 pc | |
| | Power Cord: | 1 рс | |
| J1692B | Coaxial Cord, 1 m | | |
| | (SMA-P · SUCOFLEX104PE · SMA-P, | | |
| | DC to 18 GHz, 50Ω): | 1 pc | |
| | External Mixer (Harmonic Mixer) | | |
| MA2741C | External Mixer (26.5 GHz to 40 GHz) | | |
| MA2742C | External Mixer (33 GHz to 50 GHz) | | |
| MA2743C | External Mixer (40 GHz to 60 GHz) | | |
| MA2744C | External Mixer (50 GHz to 75 GHz) | | |
| MA2745C | External Mixer (60 GHz to 90 GHz) | | |
| MA2746C | External Mixer (75 GHz to 110 GHz) | | |
| MA2747C | External Mixer (90 GHz to 140 GHz) | | |
| MA2748C | External Mixer (110 GHz to 170 GHz) | | |
| MA2749C | External Mixer (140 GHz to 220 GHz) | | |
| MA2750C | External Mixer (170 GHz to 260 GHz) | | |
| MA2751C | External Mixer (220 GHz to 325 GHz) | | |

| Model/Order No. | Name |
|-------------------------|--|
| | Application Parts |
| 34AKNF50 | Ruggedized K-to-Type N Adapter |
| | (DC to 20 GHz, 50Ω, Ruggedized K-M · N-F, |
| | SWR: 1.5 (max.), Insertion Loss: 0.4 dB (max.)) |
| K240B | Power Divider |
| | (K connector, DC to 26.5 GHz, 50Ω, K-J, 1 W max.) |
| MA1612A | Four-port Junction Pad (5 MHz to 3 GHz, N-J) |
| J1359A | Coaxial Adaptor (K-P · K-J, SMA) |
| J0576B | Coaxial Cord, 1 m (N-P · 5D-2W · N-P) |
| J0576D | Coaxial Cord, 2 m (N-P · 5D-2W · N-P) |
| J0127A | Coaxial Cord, 1 m (BNC-P · RG58A/U · BNC-P) |
| J0127B | Coaxial Cord, 2 m (BNC-P · RG58A/U · BNC-P) |
| J0127C | Coaxial Cord, 0.5 m (BNC-P · RG58A/U · BNC-P) |
| J0322A | Coaxial Cord, 0.5 m (DC to 18 GHz), |
| | (SMA-P · 50Ω SUCOFLEX104 · SMA-P) |
| J0322B | Coaxial Cord, 1 m (DC to 18 GHz), |
| | (SMA-P · 50Ω SUCOFLEX104 · SMA-P) |
| J0322C | Coaxial Cord, 1.5 m (DC to 18 GHz), |
| 100000 | $(SMA-P \cdot 50\Omega SUCOFLEX104 \cdot SMA-P)$ |
| J0322D | Coaxial Cord, 2 m (DC to 18 GHz), |
| 10005 | (SMA-P · 50Ω SUCOFLEX104 · SMA-P) |
| J0805 | DC Block, N type (MODEL 7003) |
| | (10 kHz to 18 GHz, N-P · N-J) |
| J1555A | DC Block, SMA type (MODEL 7006-1) |
| K261 | (9 kHz to 20 GHz, SMA-P · SMA-J) DC Block (10 kHz to 40 GHz, K-P · K-J) |
| J0004 | Coaxial Adapter (DC to 12.4 GHz, 50Ω , N-P · SMA-J) |
| J1398A | N-SMA Adapter (DC to 26.5 GHz, 50 Ω , N-P · SMA-J) |
| J0911 | Coaxial Cable, 1.0 m for 40 GHz |
| 10911 | (DC to 40 GHz, approx. 1 m, SF102A, 11K254/K254/1.0M) |
| J0912 | Coaxial Cable, 0.5 m for 40 GHz |
| 50512 | (DC to 40 GHz, approx. 0.5 m, SF102A, 11K254/K254/0.5M) |
| 41KC-3 | Fixed Attenuator (DC to 40 GHz, 3 dB) |
| J1261A | Ethernet Cable (Shield type, Straight, 1 m) |
| J1261B | Ethernet Cable (Shield type, Straight, 3 m) |
| J1261C | Ethernet Cable (Shield type, Cross, 1 m) |
| J1261D | Ethernet Cable (Shield type, Cross, 3 m) |
| J0008 | GPIB Cable, 2.0 m |
| J1556A | AUX Conversion Adapter |
| | (AUX \rightarrow BNC, for vector signal generator option and |
| | BER measurement function option, standard accessory |
| | with BER Measurement Function MS2840A-026) |
| A0086C | USB Audio (for MX269018A) |
| B0635A | Rack Mount Kit (EIA) |
| B0657A | Rack Mount Kit (JIS) |
| B0636C* | Carrying Case (Hard type, with casters) |
| B0671A* | Front Cover for 1MW4U |
| MA24105A | Inline Peak Power Sensor |
| NA2410CA | (350 MHz to 4 GHz, with USB A to mini B cable) |
| MA24106A | USB Power Sensor |
| MA24108A | (50 MHz to 6 GHz, with USB A to mini B cable) |
| IVIA24108A | Microwave USB Power Sensor |
| MA24118A | (10 MHz to 8 GHz, with USB A to Micro-B cable) Microwave USB Power Sensor |
| 1917424110A | (10 MHz to 18 GHz, with USB A to Micro-B cable) |
| MA24126A | Microwave USB Power Sensor |
| 1VIA24120A | (10 MHz to 26 GHz, with USB A to Micro-B cable) |
| Z0975A | Keyboard (USB) |
| Z1932A | Installation Kit |
| | (required when retrofitting options or installing software) |
| L. The Compliant Coop I | 30636C includes the Front Panel Protective Cover (B0671A) |

*****: The Carrying Case B0636C includes the Front Panel Protective Cover (B0671A).

Ordering Information

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models)



Ruggedized K-to-Type N Adapter 34AKNF50 This adapter converts the

MS2840A-046 RF Input connector (K-J) to N-J. It is used by attachment to the MS2840A main unit.



High Performance Waveguide Mixer MA2806A/MA2808A



Carrying Case B0636C (Hard type, with casters)



Front Cover for 1MW4U B0671A



USB Power Sensor MA24106A

Signal Analyzer MS2840A series (26.5 GHz/44.5 GHz models) Related Products

Signal Analyzer MS2830A

9 kHz to 3.6 GHz/6 GHz/13.5 GHz/26.5 GHz/43 GHz

This middle-range multi-function signal analyzer/spectrum analyzer has excellent cost performance.



Features

- Various measurement software for modulation analysis of digital (LTE/LTE-Advanced, WLAN, etc.) and analog (FM, ΦM, AM) devices.
- Built-in vector signal generator and analog signal generator options for all-in-one evaluations of digital and analog transmitters using Noise Factor (NF) measurement function, BER measurement function, audio analyzer, etc.
- Built-in vector signal generator for reproducing on-site waveform measurement environment using capture and playback functions.
- Like the MS2840A, frequency range expandable (≥325 GHz) up to millimeter-wave band by combined use with High Performance Waveguide Mixer and external mixer.

Signal Analyzer MS2840A (3.6 GHz/6 GHz models)

9 kHz to 3 .6 GHz/6 GHz

The MS2840A (3.6 GHz/6 GHz models) is a mid-range spectrum analyzer/signal analyzer with excellent multi-functions and narrow-band performance.

| Amritsu MS2840A MS2840 | |
|---|--|
| | |
| | |

Features

- Same excellent phase noise performance and display average noise level (DANL) as 26.5 GHz/44.5 GHz models
- Same phase noise performance as high-end instruments with installation of unique Low Phase Noise option
- Supports installation of vector signal generator and analog signal generator for all- in-one TRx tests of digital and analog wireless equipment using combined noise figure (NF) measurement and BER measurement functions
- Reproduces onsite radio-wave environment using vector signal generator Capture & Playback function

Signal Analyzer MS2690A/MS2691A/MS2692A

50 Hz to 6 GHz/13.5 GHz/26.5 GHz

This high-level signal analyzer/spectrum analyzer has excellent phase noise performance, dynamic range and measurement level accuracy.



Features

- Expandable to 6-GHz band with built-in calibration oscillator for excellent measurement level accuracy and modulation precision over frequency range from 50 Hz to 6 GHz.
- Various measurement software for LTE/LTE-Advanced, WLAN, etc.
- Built-in vector signal generator for all-in-one TRx evaluations of digital equipment using Noise Factor (NF) measurement function and BER measurement function.
- Built-in vector signal generator for reproducing on-site waveform measurement environment using capture and playback functions.
- Compact design with small footprint.

Signal Analyzer MS2850A

9 kHz to 32 GHz/44.5 GHz

The MS2850A is a spectrum analyzer/signal analyzer with 1 GHz (max.) analysis bandwidth and frequency range of 9 kHz to either 32 GHz or 44.5 GHz. The MS2850A contributes to reducing cost in R&D and manufacturing for micro/millimeter-wave and wideband communications systems, such as 5G and satellite communication. The MS2850A is available with built-in 5G Measurement Software and it has 1 GHz (max.) analysis bandwidth, excellent amplitude/ phase flatness and high measurement dynamic range. Moreover, it realizes shortening of measurement time by analyzing modulation bandwidth 800 MHz signal (1 carrier 100 MHz × 8 carriers) simultaneously.



Features

- Analysis bandwidth:
- 255 MHz (Standard), 510 MHz (Option), 1 GHz (Option) • EVM performance: <1% (100 MHz bandwidth of 5G single carrier at Center Frequency: 28 GHz)
- Phase flatness performance: (±500 MHz at Center Frequency: 28 GHz) In-band Frequency Characteristics: ±1.2 dB (nom.) In-band Phase Linearity: 5 deg. p-p (nom.)
- Measurement applications (option): 5G measurement, LTE/LTE-Advanced, Digital Modulation, etc.

| ООО "Техэнком" | Контрольно-измерительные приборы и оборудование | www.tehencom.com |
|----------------|---|------------------|
| | | |

Note

Anritsu envision : ensure

United States

Anritsu Americas Sales Company 450 Century Parkway, Suite 190, Allen, TX 75013, U.S.A. Phone: +1-800-Anritsu (1-800-267-4878)

• Canada

Anritsu Electronics Ltd. 700 Silver Seven Road, Suite 120, Kanata, Ontario K2V 1C3, Canada Phone: +1-613-591-2003 Fax: +1-613-591-1006

• Brazil Anritsu Eletronica Ltda.

Praça Amadeu Amaral, 27 - 1 Andar 01327-010 - Bela Vista - Sao Paulo - SP Brazil Phone: +55-11-3283-2511 Fax: +55-11-3288-6940

Mexico

Anritsu Company, S.A. de C.V. Blvd Miguel de Cervantes Saavedra #169 Piso 1, Col. Granada Mexico, Ciudad de Mexico, 11520, MEXICO Phone: +52-55-4169-7104

• United Kingdom

Anritsu EMEA Ltd. 200 Capability Green, Luton, Bedfordshire, LU1 3LU, U.K. Phone: +44-1582-433200 Fax: +44-1582-731303

France Anritsu S.A.

Allinisu J.A. 12 avenue du Québec, Bâtiment Iris 1- Silic 612, 91140 VILLEBON SUR YVETTE, France Phone: +33-1-60-92-15-50 Fax: +33-1-64-46-10-65

• Germany

Anritsu GmbH Nemetschek Haus, Konrad-Zuse-Platz 1 81829 München, Germany Phone: +49-89-442308-0 Fax: +49-89-442308-55

• Italy

Anritsu S.r.l. Via Elio Vittorini 129, 00144 Roma, Italy Phone: +39-6-509-9711 Fax: +39-6-502-2425 • Sweden Anritsu AB Isafjordsgatan 32C, 164 40 KISTA, Sweden Phone: +46-8-534-707-00

• Finland Anritsu AB Teknobulevardi 3-5, FI-01530 VANTAA, Finland Phone: +358-20-741-8100 Fax: +358-20-741-8111

• Denmark Anritsu A/S

Torveporten 2, 2500 Valby, Denmark Phone: +45-7211-2200 Fax: +45-7211-2210

• Russia Anritsu EMEA Ltd. Representation Office in Russia Tverskaya str. 16/2, bld. 1, 7th floor. Moscow, 125009, Russia Phone: +7-495-363-1694 Fax: +7-495-335-8962

• Spain Anritsu EMEA Ltd.

Representation Office in Spain Edificio Cuzco IV, Po. de la Castellana, 141, Pta. 5

28046, Madrid, Spain Phone: +34-915-726-761 Fax: +34-915-726-621

• United Arab Emirates Anritsu EMEA Ltd. Dubai Liaison Office

902, Aurora Tower, P O Box: 500311- Dubai Internet City Dubai, United Arab Emirates Phone: +971-4-3758479 Fax: +971-4-4249036

• India Anritsu India Private Limited

6th Floor, Indiqube ETA, No.38/4, Adjacent to EMC2, Doddanekundi, Outer Ring Road, Bengaluru – 560048, India Phone: +91-80-6728-1300 Fax: +91-80-6728-1301 Specifications are subject to change without notice.

Singapore

Anritsu Pte. Ltd. 11 Chang Charn Road, #04-01, Shriro House Singapore 159640 Phone: +65-6282-2400 Fax: +65-6282-2533

• P.R. China (Shanghai) Anritsu (China) Co., Ltd.

Room 2701-2705, Tower A, New Caohejing International Business Center No. 391 Gui Ping Road Shanghai, 200233, P.R. China Phone: +86-21-6237-0898 Fax: +86-21-6237-0899

• P.R. China (Hong Kong) Anritsu Company Ltd.

Unit 1006-7, 10/F., Greenfield Tower, Concordia Plaza, No. 1 Science Museum Road, Tsim Sha Tsui East, Kowloon, Hong Kong, P.R. China Phone: +852-2301-4980 Fax: +852-2301-3545

• Japan

Anritsu Corporation 8-5, Tamura-cho, Atsugi-shi, Kanagawa, 243-0016 Japan Phone: +81-46-296-6509 Fax: +81-46-225-8352

• Korea Anritsu Corporation, Ltd.

5FL, 235 Pangyoyeok-ro, Bundang-gu, Seongnam-si, Gyeonggi-do, 13494 Korea Phone: +82-31-696-7750 Fax: +82-31-696-7751

• Australia

Anritsu Pty. Ltd. Unit 20, 21-35 Ricketts Road, Mount Waverley, Victoria 3149, Australia Phone: +61-3-9558-8177 Fax: +61-3-9558-8255

• Taiwan Anritsu Company Inc.

7F, No. 316, Sec. 1, NeiHu Rd., Taipei 114, Taiwan Phone: +886-2-8751-1816 Fax: +886-2-8751-1817

1910