## www.tehencom.com

# **Anritsu** envision : ensure

# LMR Master™

Land Mobile Radio Modulation and Signal Analyzer, Vector Network Analyzer, and Spectrum Analyzer

## S412E

9 kHz to 1.6 GHz Spectrum Analyzer 500 kHz to 1.6 GHz Vector Network Analyzer



#### Introduction

The S412E is Anritsu's second generation solution for installing and maintaining public safety systems. Built on Anritsu's ninth generation handheld platform, the S412E combines a high performance receiver/spectrum analyzer with the world's most advanced handheld vector network analyzer plus a powerful vector signal generator with internally adjustable power from 0 dBm to -130 dBm.

#### Land Mobile Radio Signal Analyzer Highlights

- Analyzes Narrowband FM analog systems
- Analyzes P25 (TIA-102.CAAA-C), P25 Phase 2 (TIA-102.CCAA), DMR (MOTOTRBO<sup>™</sup>)<sup>a</sup>, NXDN<sup>™</sup>, dPMR, ITC-R PTC, and TETRA digital systems
- 100 kHz to 1.6 GHz frequency coverage (Optional extension to 6 GHz)
- Internal signal generator: 0.1 dB resolution, 0 dBm to -130 dBm (spec to -120 dBm)

a. Supports those features compliant with the ETSI DMR standard.

#### Spectrum Analyzer Highlights

- Measurements: Occupied Bandwidth, Channel Power, ACPR, C/I, Coverage Mapping
- Interference Analyzer: Spectrogram, Signal Strength, RSSI, Mapping
- 9 kHz to 1.6 GHz frequency coverage (Optional extension to 6 GHz)

#### **VNA Analyzer Highlights**

- 1-path, 2-port Vector Network Analyzer (VNA) w/ quad trace display
- 500 kHz to 1.6 GHz frequency coverage (Optional extension to 6 GHz)
- Intuitive Graphical User Interface (GUI) with convenient touchscreen
- VNA-quality error correction for directivity and source match

### **Signal Generator Highlights**

- 500 kHz to 1.6 GHz CW/FM/AM Modulation
- FM, 100 Hz to 10 kHz rate, adjustable deviation
- AM, 100 Hz to 10 kHz rate, adjustable depth

#### **Capabilities and Functional Highlights**

- Analog FM and digital LMR analyzer
- High accuracy internal power meter
- On-screen LMR Coverage Mapping (Outdoor and Indoor)
- GPS tagging of saved traces
- USB data transfer
- Complies with MIL-PRF-28800F Class 2 and MIL-STD-810G
- Certified for use in Explosive Atmosphere per MIL-PRF-28800F 8.4 inch daylight-viewable TFT LCD color resistive touchscreen – allows use while wearing gloves
- Touchscreen keyboard
- USB and Ethernet data transfer
- Web Remote Control
- Master Software Tools™
- 3 hour battery operation time

- 2.0 dB signal generator accuracy (typical)
- P25/P25p2, NXDN, and ETSI DMR BER test patterns including 1011, 1031, and V.52/O.153
- Duplex test: Simultaneous analysis and generation of analog or digital LMR signals
- Independent control of both receive/transmit frequencies and test patterns

**Specifications** 

- TETRA Base Station Receiver Sensitivity Measurements
- Dynamic Range: > 95 dB in 10 Hz RBW
- DANL: -152 dBm in 10 Hz RBW
- Phase Noise: –100 dBc/Hz max @ 10 kHz offset at 1 GHz
- Frequency Accuracy: 120 ppb standard (25 °C ± 25 °C);
   < 50 ppb after 3 minutes with GPS lock</li>
- Outstanding calibration stability, up to 16 hours
- Arbitrary data points up to 4001
- IF Bandwidth selections of 10 Hz to 100 kHz
- 100 dB transmission dynamic range
- 850 μs/data point sweep speed
- 0.1 dB resolution, 0 dBm to -130 dBm
- CW, FM with CTCSS/DCS/DTMF, FM with CTCSS/DCS/DTMF + Tone Modulation, FM + Tone Modulation



LMR Master™ S412E featuring 8.4 inch Daylight Viewable Touchscreen Compact Size: 273 mm x 199 mm x 91 mm, (10.7 in x 7.8 in x 3.6 in), Lightweight: 3.6 kg, (7.9 lb)

-				-					
5	n	ρ	C	ItI	са	tı	n	n	C
9	μ	C			CU		U		9

## **Table of Contents**

Spectrum Analyzer	4
Vector Network Analyzer	
Interference Analyzer (Option 25)	11
Channel Scanner (Option 27)	11
GPS Receiver (Option 31)	11
Ethernet Connectivity	11
Coverage Mapping (Option 431)	12
Electromagnetic Field Test (Option 444)	
CW Signal Generator	12
Internal Power Meter	
High Accuracy Power Meter (Option 19)	13
NBFM Analyzer and Coverage Mapping	14
P25/P25p2 Analyzer and P25/P25p2 Talk-Out Coverage (Options 521 and 522)	15
P25/P25p2 Signal Generator	
DMR (MOTOTRBO) Analyzer and DMR Talk-Out Coverage (Options 591 and 592)	17
dPMR Analyzer (Options 573 and 572)	18
NXDN Analyzer and NXDN Talk-Out Coverage (Options 531 and 532)	19
TETRA Analyzer and TETRA Coverage Mapping (Options 581 and 582)	20
PTC Analyzer and PTC Talk-Out Coverage (Options 721 and 722)	
AM/FM/PM Signal Analyzers (Option 509)	
LTE Signal Analyzers (Options 541, 542, 546, and 886)	
IEEE 802.16 Fixed WiMAX Signal Analyzers (Options 46 and 47)	
IEEE 802.16 Mobile WiMAX Signal Analyzers (Options 66, 67, and 37)	25
General Specifications	26
Master Software Tools	
easyTest Tools™	
Anritsu Tool Box and Line Sweep Tools	
Web Remote Control	
Programmable Remote Control	
Ordering Information – Options	
Standard Accessories	
Manuals, Related Literature	
Troubleshooting Guides	
Optional Accessories	32

#### Definitions

All specifications and characteristics apply to Revision 4 instruments under the following conditions, unless otherwise noted: Warm-Up Time After 15 minutes of warm-up time in VNA mode, where the instrument is left in the ON state. **Temperature Range** Over the 23 °C ± 5 °C temperature range, unless otherwise noted. **Reference Signal** When using internal reference signal. **Typical Performance** Typical specifications that are not in parenthesis are not tested and not warranted. They are generally representative of characteristic performance. Typical specifications in parenthesis () represent the mean value of measured units and do not include any guard-bands or uncertainties. They are not warranted. Uncertainty A coverage factor of x1 is applied to the measurement uncertainties to facilitate comparison with other industry handheld analyzers. Calibration Cycle Calibration is within the recommended 12 month period (residual specifications also require calibration kit calibration cycle adherence.) All specifications subject to change without notice. For the most current data sheet, please visit the Anritsu web site: www.anritsu.com

	Specification
📓 Spectrum Analyzer	
Measurements	
Smart Measurements	Field Strength (uses antenna calibration tables to measure dBm/m <sup>2</sup> or dBmV/m) Occupied Bandwidth (measures 99% to 1% power channel of a signal)
	Channel Power (measures the total power in a specified bandwidth)
	ACPR (Adjacent Channel Power Ratio)
	AM/FM/SSB Audio Demodulation (Wide/Narrow FM, AM, Upper/Lower SSB)
	C/I (carrier-to-interference ratio)
	Emission Mask
	Coverage Mapping (requires option 431)
Setup Parameters	
Frequency	Center/Start/Stop, Span, Frequency Step, Signal Standard, Channel #, Channel Increment
Amplitude	Reference Level (RL), Scale, Attenuation Auto/Level, RL Offset, Pre-Amp On/Off, Detection
Span	Span, Span Up/Down (1-2-5), Full Span, Zero Span, Last Span
Bandwidth File	RBW, Auto RBW, VBW, Auto VBW, RBW/VBW, Span/RBW
Save/Recall	Save, Recall, Delete, Directory Management Setups, Measurements, Limit Lines, Screen Shots Jpeg (save only), Save-on-Event
Save/Recall Save-on-Event	Crossing Limit Line, Sweep Complete, Save-then-Stop, Clear All
Delete	Selected File, All Measurements, All Mode Files, All Content
Directory Management	Sort Method (Name/Type/Date), Ascend/Descend, Internal/USB, Copy, Format USB
Application Options	Bias-Tee On/Off, Impedance (50 $\Omega$ , 75 $\Omega$ , Other)
Sweep Functions	
Sweep	Single/Continuous, Manual Trigger, Reset, Detection, Minimum Sweep Time, Trigger Type
Detection	Peak, RMS, Negative, Sample, Quasi-peak
Triggers	Free Run, External, Video, Change Position, Manual
Trace Functions	
Traces	Up to three Traces (A, B, C), View/Blank, Write/Hold, Trace A/B/C Operations
Trace A Operations	Normal, Max Hold, Min Hold, Average, # of Averages, (always the live trace)
Trace B Operations	$A \rightarrow B$ , $B \leftrightarrow C$ , Max Hold, Min Hold
Trace C Operations	A $\rightarrow$ C, B $\leftrightarrow$ C, Max Hold, Min Hold, A – B $\rightarrow$ C, B – A $\rightarrow$ C, Relative Reference (dB), Scale
Marker Functions	
Markers	Markers 1-6 each with a Delta Marker, or Marker 1 Reference with Six Delta Markers, Marker Table On/O
	All Markers Off
Marker Types	Style (Fixed/Tracking), Noise Marker, Frequency Counter Marker, Marker Auto-Position Peak Search,
	Next Peak (Right/Left), Peak Threshold %, Set Marker to Channel, Marker Frequency to Center, Delta Marl to Span, Marker to Reference Level
Marker Table	1-6 markers frequency and amplitude plus delta markers frequency offset and amplitude
Limit Line Functions	
Limit Line Functions Limit Lines	Upper/Lower, On/Off, Edit, Move, Envelope, Advanced, Limit Alarm, Default Limit
Limit Line Edit	Frequency, Amplitude, Add Point, Add Vertical, Delete Point, Next Point Left/Right
Limit Line Move	To Current Center Frequency, By dB or Hz, To Marker 1, Offset from Marker 1
Limit Line Envelope	Create Envelope, Update Amplitude, Points (41 max), Offset, Shape Square/Slope
Limit Line Advanced	Type (Absolute/Relative), Mirror, Save/Recall
Frequency	
Frequency Range	9 kHz to 1.6 GHz, (6 GHz with Option 6)
Tuning Resolution	1 Hz
Frequency Reference Aging	± 1.0 ppm/year
Frequency Reference Accuracy	$\pm$ 120 ppb (25 °C $\pm$ 25 °C) + aging, < 50 ppb + aging with GPS lock
Frequency Span	10 Hz to 1.6 GHz including zero span (10 Hz to 6 GHz with Option 6)
Sweep Time Sweep Time Accuracy	100 ms min, 7 μs to 3600 seconds in zero span ± 2% in zero span
Bandwidth	10 Hz to 2 MHz in 1, 2 conjunce $\pm 10\%$ (1 MHz may in zero chan) (-2 dP bandwidth)
Resolution Bandwidth (RBW)	10 Hz to 3 MHz in 1–3 sequence ± 10% (1 MHz max in zero-span) (–3 dB bandwidth) 1 Hz to 3 MHz in 1–3 sequence (–3 dB bandwidth) (auto or manually selectable)
Vidoo Bandwidth (VDM)	
Video Bandwidth (VBW) RBW with Quasi-Peak Detection	200 Hz, 9 kHz, 120 kHz (-6 dB bandwidth)

Charterum Analyzar					
Spectrum Analyzer (Cont	inued)				
Spectral Purity SSB Phase Noise @ 1 GHz	–100 dBc/Hz, –110 dBc/H –105 dBc/Hz, –112 dBc/H –115 dBc/Hz, –121 dBc/H	z typical @ 100 kHz offset			
Amplitude Ranges					
Dynamic Range Measurement Range	> 95 dB (2.4 GHz), 2/3 (TOI-DANL) in 10 Hz RBW DANL to +26 dBm ( $\geq$ 50 MHz) DANL to 0 dBm (< 50 MHz)				
RF In Port Damage Level Display Range	+33 dBm peak, ± 50 VDC,	Maximum Continuous Inpu ps, ten divisions displayed	ıt (≥ 10 dB attenuation)		
Reference Level Range Attenuator Resolution	-120 dBm to +30 dBm 0 to 55 dB, 5.0 dB steps				
Amplitude Units	Log Scale Modes: dBm, d Linear Scale Modes: nV, µ	BV, dBmv, dBμv ιV, mV, V, kV, nW, μW, mW, '	N, kW		
Amplitude Accuracy					
Single sine wave, input power < Ref level a	nd > DANL, Attenuation: Au	uto, Ambient: –10 °C to 50 °	Cafter 30 minute warm-up)		
9 kHz to 100 kHz	± 2.0 dB typical (Preamp	Off)			
> 100 kHz to 4.0 GHz > 4.0 GHz to 6 GHz	± 1.25 dB, ± 0.5 dB typica ± 1.50 dB, ± 0.5 dB typica				
Displayed Average Noise Level (D	ANL)				
	Prean (Reference Le	np Off evel –20 dBm)		np On evel –50 dBm)	
(RBW = 1 Hz, 0 dB attenuation)	Maximum	Typical	Maximum	Typical	
10 MHz to 2.4 GHz	–141 dBm	–146 dBm	–157 dBm	–162 dBm	
> 2.4 GHz to 4 GHz	–137 dBm	–141 dBm	–154 dBm	–159 dBm	
> 4 GHz to 5 GHz	–134 dBm	–138 dBm	–150 dBm	–155 dBm	
> 5 GHz to 6 GHz	–126 dBm	–131 dBm	–143 dBm	–150 dBm	
(RBW = 10 Hz, 0 dB attenuation)					
10 MHz to 2.4 GHz	-131 dBm	–136 dBm	–147 dBm	–152 dBm	
> 2.4 GHz to 4 GHz	-127 dBm	–131 dBm	–144 dBm	–149 dBm	
> 4 GHz to 5 GHz > 5 GHz to 6 GHz	–124 dBm –116 dBm	–128 dBm –121 dBm	–140 dBm –133 dBm	–145 dBm –140 dBm	
Spurs					
Residual Spurious	< –90 dBm (RF input term	ninated, 0 dB input attenuat	ion, > 10 MHz)		
Input-Related Spurious	< –75 dBc (0 dB attenuati	on, –30 dBm input, span < 1	.7 GHz, carrier offset > 4.5 M	MHz)	
Exceptions, typical	< –70 dBc @ < 2.5 GHz wi	th 2072.5 MHz Input			
	< -68 dBc @ F1 - 280 MH	z with F1 Input			
	< -70 dBc @ F1 + 190.5 M	•			
	< -52 dBc @ 7349 - 2F2 N < -55 dBc @ 190.5 ± F1/2	1Hz with F2 Input, where F2	< 2437.5 MHz		
「hird-Order Intercept (TOI) (Prea 800 MHz	mp Off, –20 dBm tones, 100 +16 dBm	0 kHz apart, 10 dB attenuati	on)		
2400 MHz	+20 dBm				
200 MHz to 2200 MHz	+25 dBm typical				
> 2.2 GHz to 5.0 GHz	+28 dBm typical				
> 5.0 GHz to 6.0 GHz	+33 dBm typical				
Second Harmonic Distortion (Pre	amp Off, 0 dB input attenu	ation, –30 dBm input)			
50 MHz	-56 dBc				
> 50 MHz to 200 MHz	-60 dBc typical				
> 200 MHz to 3000 MHz	–70 dBc typical				
/SWR					

## **Specifications**

#### le constant de la con

#### Block Diagram

As shown in the following simplified block diagram, the LMR Master has a 2-port, 1-path architecture that automatically measures two S-parameters with error-correction precision inherent to VNA operation. The magnitude and phase information gained from vector network data enables the LMR Master to make significant error corrections and provide improved field measurements.



Specifications	S	p	ec	ifi	са	ti	ons
----------------	---	---	----	-----	----	----	-----

## Wector Network Analyzer (Continued)

Measurements	
Measurement Parameters	S <sub>11</sub> , S <sub>21</sub>
Number of Traces	Four: TR1, TR2, TR3, TR4
Trace Format	Single, Dual, Tri, Quad. When used with Number of Traces, overlays are possible including a Single Format with Four trace overlays.
Graph Types	Log Magnitude, SWR, Phase, Real, Imaginary, Group Delay, Smith Chart, Log Mag/2 (1-Port Cable Loss), Linear Polar, Log Polar, Real Impedance, Imaginary Impedance
Domains	Frequency Domain, Distance Domain
Frequency	Start Frequency, Stop Frequency, Center Frequency, Span
Distance	Start Distance, Stop Distance
Frequency Sweep Type: Linear	Single Sweep, Continuous
Data Points	2 to 4001 (arbitrary setting); data points can be reduced without recalibration.
Limit Lines	Upper, Lower, 10 segmented Upper, 10 segmented Lower
Test Limits	Pass/Fail for Upper, Pass/Fail for Lower, Limit Audible Alarm
Data Averaging	Sweep-by-sweep
Smoothing	0 to 20 %
IF Bandwidth	10, 20, 50, 100, 200, 500, 1 k, 2 k, 5 k, 10 k, 20 k, 50 k, 100 k (Hz)
Reference Plane	The reference planes of a calibration (or other normalization) can be changed by entering a line length. Assumes no loss, flat magnitude, linear phase, and constant impedance.
Auto Reference Plane Extension	Instead of manually entering a line length, this feature automatically adjusts phase shift from the current calibration (or other normalization) to compensate for external cables (or test fixtures). Assumes no loss, flat magnitude, linear phase, and constant impedance.
Frequency Range	Frequency range of the measurement can be narrowed (reduces number of data points) within the calibration range without recalibration. When Interpolation is On, narrowed frequency range will retain original number of data points.
Group Delay Aperture	Defined as the frequency span over which the phase change is computed at a given frequency point. The aperture can be changed without recalibration. The minimum aperture is the frequency range divided by the number of points in calibration and can be increased to 20% of the frequency range.
Group Delay Range	< 180° of phase change within the aperture
Trace Memory	A separate memory for each trace can be used to store measurement data for later display. The trace data can be saved and recalled.
Trace Math	Complex trace math operations of subtraction, addition, multiplication, or division are provided.
Number of Markers	12, arbitrary assignments to any trace
Marker Types	Reference, Delta
Marker Readout Styles	Log Mag, Cable Loss (Log Mag/2), Log Mag and Phase, Phase, Real and Imaginary, SWR, Impedance, Admittance, Normalized Impedance, Normalized Admittance, Polar Impedance, and Group Delay
Marker Search	Peak Search, Valley Search, Find Marker Value
Calibration Type	Full S <sub>11</sub> , 1-Path, 2-Port (S <sub>11</sub> and S <sub>21</sub> ), Response S <sub>11</sub> , Response S <sub>21</sub>
Calibration Methods	Short-Open-Load-Through (SOLT)
Calibration Standards' Coefficients	Coax: N-Connector, K-Connector, 7/16, TNC, SMA, and four User Defined
Cal Correction Toggle	On/Off
Interpolation	On/Off (Interpolation may be activated before or after calibration)
Impedance Conversion (Smith Chart)	Support for 50 $\Omega$ and 75 $\Omega$ are provided.
Units	Meters, Feet
Bias Tee Settings	Internal, Off
Timebase Reference	Internal
File Storage Types	Measurement, Setup (with CAL), Setup (without CAL), S2P (Real/Imag), S2P (Lin Mag/Phase), S2P (Log Mag/Phase), JPEG
Languages	English, French, German, Spanish, Chinese, Japanese, Korean, Italian, Russian, and Portuguese

## **Specifications**

#### **Wector Network Analyzer** (Continued)

Corrected System Measurement Accuracy <sup>1</sup> — High Port Power, N-Type (OSLN50A-8 or OSLNF50A-8, TOSLN50A-8 or TOSLNF50A				
Frequency Range	Directivity (dB)	Source Match (dB)	Reflection Tracking (dB)	Transmission Tracking (dB)
< 20 MHz	≥ 42	≥ 30	± 0.01	± 0.01
20 MHz to < 3 GHz	≥ 42	≥ 30	± 0.05	± 0.01
3 GHz to 6 GHz	≥ 42	≥ 30	± 0.05	± 0.01





 Full 1-path, 2-port forward path calibration with isolation, high power, 10 Hz IFBW, no averaging, 10 minute warm-up. OSLN50A-8, OSLNF50A-8, TOSLN50A-8, or TOSLNF50A-8 calibration kit. Reflection and Transmission Tracking are typical.

**S412E** 

#### Vector Network Analyzer (Continued)

Corrected System Measurement Accuracy<sup>1</sup> — High Port Power, K-Type (OSLK50A-20 or TOSLKF50A-20. Compatible with 3.5 mm and SMA connectors)

Frequency Range	Directivity (dB)	Source Match (dB)	Reflection Tracking (dB)	Transmission Tracking (dB)
< 20 MHz	≥ 42	≥ 33	± 0.01	± 0.01
20 MHz to < 3 GHz	≥ 42	≥ 33	± 0.05	± 0.01
3 GHz to 6 GHz	≥ 42	≥ 33	± 0.05	± 0.01

#### Corrected Measurement Uncertainty (Transmission from Port 1 to Port 2)



 Full 1-path, 2-port forward path calibration with isolation, high power, 10 Hz IFBW, no averaging, 10 minute warm-up. TOSLK50A-20, TOSLKF50A-20 calibration kit. Reflection and Transmission Tracking are typical.

## Specifications

#### Vector Network Analyzer (Continued)

**Bias Tee (Option 10)** For tower mounted amplifier tests, the S412E with optional internal bias tees can supply both DC and RF signals on the center conductor of the cable during measurements. For frequency sweeps in excess of 2 MHz, the LMR Master can supply internal voltage control from +12 to +32 V in 0.1 V steps up to 450 mA. Bias is available on VNA Port 2 and the SPA Input (RF In) for use with antenna pre-amplifiers.

Frequency Range 2 MHz to 4/6 GHz at VNA Port 2 Internal Voltage/Current +12 V to +32 V at 450 mA (Steady state) Internal Resolution 0.1 V Bias Tee Selections Internal, Off

The Compact LMR Master offers optional integrated bias tee for supplying DC plus RF to the DUT as shown in this simplified block diagram.



#### **Vector Voltmeter (Option 15)**

A phased array system relies on phase matched cables for nominal performance. For this class of application, the LMR Master offers this special software mode to simplify phase matching cables at a single frequency. The similarity between the popular vector voltmeter and this software mode ensures minimal training is required to phase match cables. Operation is as simple as configuring the display for absolute or relative measurements. The easy-to-read large fonts show either reflection or transmission measurements using impedance, magnitude, or VSWR readouts. For instrument landing system (ILS) or VHF Omni-directional Range (VOR) applications, a table view improves operator efficiency when phase matching up to twelve cables. The S412E solution is superior because the signal source is included internally, precluding the need for an external signal generator.

 CW Frequency Range
 500 kHz to 1.6 GHz (6 GHz with Option 16)

 Measurement Display
 CW, Table (Twelve Entries, Plus Reference)

 Measurement Types
 Return Loss, Insertion

 Measurement Format
 dB/VSWR/Impedance

#### **Distance Domain**

Distance-to-Fault Analysis is a powerful field test tool to analyze cables for faults, including minor discontinuities that may occur due to a loose connection, corrosion, or other aging effects. By using Frequency Domain Reflectometry (FDR), the VNA's DTF mode exploits a user-specified band of full power operational frequencies (instead of DC pulses from TDR approaches) to more precisely identify discontinuities. The VNA converts S-parameters from frequency domain into distance domain on the horizontal display axis, using a mathematical computation called Inverse Fourier Transform. Connect a reflection at the opposite end of the cable and the discontinuities appear versus distance to reveal any potential maintenance issues. When access to both ends of the cable is convenient, a similar distance domain analysis is available on transmission measurements.

Distance Domain will improve your productivity with displays of the cable in terms of discontinuities versus distance. This readout can then be compared against previous measurements (from stored data) to determine whether any degradations have occurred since installation (or the last maintenance activity). More importantly, you will know precisely where to go to fix the problem and minimize or prevent downtime of the system.

Maximum Distance (4001 data points, 1.6 GHz span)	374.9 m (1,229.9 ft)	
Maximum Distance (4001 data points, 6.0 GHz span)	99.9 m (327.75 ft)	
Minimum Distance Resolution (1.6 GHz span)	18.7 cm (7.36 in)	
Minimum Distance Resolution (6.0 GHz span)	4.99 cm (1.97 in)	
Measurement Display	Return Loss, VSWR	
Measurement Format	dB, VSWR	

Specifications	S412E

**Interference Analyzer (Option 25)** (GPS Option 31 recommended)

#### Measurements

incubul childres	
Spectrum	Field Strength
	Occupied Bandwidth
	Channel Power
	Adjacent Channel Power Ratio (ACPR)
	AM/FM/SSB Demodulation (Wide/Narrow FM, Upper/Lower SSB - audio out only)
	Carrier-to-Interference ratio (C/I)
Spectrogram	Collect data up to one week
Signal Strength	Gives visual and aural indication of signal strength
Received Signal Strength Indicator (RSSI)	Collect data up to one week
Signal ID	Up to 12 signals
-	Center Frequency
	Bandwidth
	Signal Type: FM, GSM, W-CDMA, CDMA, Wi-Fi
	Closest Channel Number
	Number of Carriers
Signal-to-Nose Ratio (SNR)	> 10 dB
Interference Mapping	Triangulate location of interference with on-display maps
Application Option	Bias-Tee On/Off
	Impedance (50 $\Omega$ , 75 $\Omega$ , Other)
	Compatible with the MA2700A InterferenceHunter™ Handheld Direction Finding System
	· · ·

## [mi] Channel Scanner (Option 27)

GPS Receiver (Option 31)	(Antenna sold separately)
Application Options	Bias-Tee On/Off, Impedance (50 $\Omega$ , 75 $\Omega$ , Other)
Measurement Range	–110 dBm to +26 dBm
Frequency Accuracy	± 10 Hz + Frequency Reference
Custom Scan	Signal Standard, Channel, # of Channels, Channel Step Size, Custom Scan
Amplitude	Reference Level, Scale
Scanner	Scan Channels, Scan Frequencies, Scan Customer List, Scan Script Master™
Measurements	Graph/Table, Max Hold On/5 sec/Off, Freq/Channel, Current/Max, Single/Dual Color
Number of Channels	1 to 20 Channels

Setup	On/Off, Antenna Voltage 3.3/5.0 V, GPS Info
GPS Time/Location Indicator	Time, Latitude, Longitude and Altitude on display
	Time, Latitude, Longitude and Altitude with trace storage
GPS-Enhanced Frequency Accuracy	< 50 ppb with GPS On, 3 minutes after satellite is locked in selected mode (Applies to Spectrum Analyzer, Interference Analyzer, LMR Signal Analyzers)
Connector	SMA, Female

#### **Ethernet Connectivity**

Connector LAN Speed Mode Static IP settings	RJ45 10 Mbps Static, DHCP IP address Subnet Mask
Remote Control Data Upload	IP Gateway Remote capability provided with Web Remote Control and SCPI programming With Line Sweep Tools through Ethernet connection

12E	Specificatio
📗 Coverage Mapping (Opti	on 431)
Measurements	
Indoor Mapping	RSSI, ACPR
Outdoor Mapping	RSSI, ACPR
Setup Parameters	
Frequency	Center/Start/Stop, Span, Freq Step, Signal Standard, Channel #, Channel Increment
Amplitude	Reference Level (RL), Scale, Attenuation Auto/Level, RL Offset, Pre-Amp On/Off, Detection
Span	Span, Span Up/Down (1-2-5), Full Span, Zero Span, Last Span
BW	RBW, Auto RBW, VBW, Auto VBW, RBW/VBW, Span/VBW
Measurement Setup	ACPR, RSSI
Point Distance / Time Setup	Repeat Type Time Distance
Save Points Map	Save KML, JPEG, Tab Delimited
Recall Points Map	Recall Map, Recall KML Points only, Recall KML Points with Map, Recall Default Grid
💓 Electromagnetic Field Te	est (Option 444)
Measurements	
Setup	Limit lines, axis dwell time, measurement time, auto-logging, measurement units, trace display
Spectrum Analyzer	Field strength is measured
LTE OTA	P-SS, S-SS, and RS are measured and displayed based on each Cell ID received
Units	Spectrum Analyzer: dBm/m², dBV/m, dBmV/m, dBuV/m, V/m, W/m², dBW/m², A/m, dBA/m, W/cm² LTE OTA: dBm/m², V/m, W/m²
Results	Maximum, minimum, and average of all measurements conducted
Display	Measurement status, number of measurements taken, pass/fail indicators

Supported Antenna	
2000-1800-R	9 kHz to 300 MHz
2000-1792-R	30 MHz to 1.6 GHz
2000-1791-R	700 MHz to 1.6 GHz

#### Modes where EMF Measurements Available

Spectrum Analyzer LTE OTA (Option 546)

## 째 CW Signal Generator

Setup Parameters		
Generator	On/Off	
Tx Output Level	Level 0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm)	
Tx Pattern	CW, AM w/ 1 kHz, FM w/ 1 kHz	
RF Characteristics		
Power Level Accuracy	2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical	
Frequency Range	500 kHz to 1.6 GHz	
Frequency Accuracy	Same as Spectrum Analyzer	

S412E

#### **Internal Power Meter**

Frequency	Center/Start/Stop, Span, Frequency Step, Signal Standard, Channel #, Full Band
Amplitude	Maximum, Minimum, Offset, Relative On/Off, Units, Auto Scale
Average	Acquisition Fast/Med/Slow, # of Running Averages
Limits	Limit On/Off, Limit Upper/Lower
Frequency Range	10 MHz to 1.6 GHz (Standard), 10 MHz to 6 GHz (Option 6)
Span	1 kHz to 100 MHz
Display Range	–140 dBm to +30 dBm, $\leq$ 40 dB span
Measurement Range	–120 dBm to +26 dBm
Offset Range	0 dB to +100 dB
VSWR	2:1 typical
Maximum Power	Same as RF In Damage Level
Accuracy	Same as Spectrum Analyzer
Application Option	Impedance (50 $\Omega$ , 75 $\Omega$ , Other)

#### High Accuracy Power Meter (Option 19) (Requires external USB power sensor, sold separately)

Amplitude Average Zero/Cal Limits	Maximum, Minimum, Offset, Relative On/Off, Units, Auto Scale # of Running Averages, Max Hold Zero On/Off, Cal Factor (Center Frequency, Signal Standard) Limit On/Off, Limit Upper/Lower				
Power Sensor Model	MA24105A	MA24106A	MA24108A/18A/26A	MA24208A/18A	MA24330A/40A/50A
Description	Inline High Power Sensor	High Accuracy RF Power Sensor	Microwave USB Power Sensor	Microwave Universal USB Power Sensor	Microwave CW USB Power Sensor
Frequency Range	350 MHz to 4 GHz	50 MHz to 6 GHz	10 MHz to 8/18/26 GHz	10 MHz to 8/18 GHz	10 MHz to 33/40/50 GHz
Connector	Type N(f), 50 Ω	Type N(m), 50 Ω	Type N(m), 50 Ω (8/18 GHz) Type K(m), 50 Ω (26 GHz)	Type N(m), 50 Ω	Type K(m), 50 Ω (33/40 GHz) Type V(m), 50 Ω (50 GHz)
Dynamic Range	+3 dBm to +51.76 dBm (2 mW to 150 W)	–40 dBm to +23 dBm (0.1 μW to 200 mW)	–40 dBm to +20 dBm (0.1 μW to 100 mW)	–60 dBm to +20 dBm (1 nW to 100 mW)	–70 dBm to +20 dBm (0.1 nW to 100 mW)
Measurand	True-RMS	True-RMS	True-RMS, Slot Power, Burst Average Power	True-RMS, Slot Power, Burst Average Power	Average Power
Measurement Uncertainty	± 0.17 dB <sup>a</sup>	± 0.16 dB <sup>b</sup>	± 0.18 dB <sup>c</sup>	± 0.17 dB <sup>d</sup>	± 0.17 dB <sup>e</sup>
Data sheet (for complete specifications)	11410-00621	11410-00424	11410-00504	11410-00841	11410-00906

Notes:

a. Expanded uncertainty with K=2 for power measurements of a CW signal greater than +20 dBm with a matched load.

b. Total RSS measurement uncertainty (0 °C to 50 °C) for power measurements of a CW signal greater than -20 dBm with zero mismatch errors.

C. Expanded uncertainty with K=2 for power measurements of a CW signal greater than -20 dBm with zero mismatch errors.
 d. Power uncertainty expressed with two sigma confidence level for CW measurement after zero operation. Includes calibration factor and linearity over temperature uncertainties, but not the effects of mismatch, zero set and drift, or noise.
 e. Includes linearity over temperature uncertainties, but not the effects of calibration factor, mismatch, zero set and drift, and uncertainties.

noise

## **Specifications**

## NBFM Analyzer and Coverage Mapping

		NBFM Talk-Out Coverage
NBFM Analyzer	•	(requires Option 31 GPS and a suitable GPS antenna)
Carrier Power		RSSI
Carrier Frequency		THD
Frequency Error		SINAD
FM Deviation (Peak, Average, RMS)		External SINAD
Modulation Rate		
SINAD		
Quieting		
THD		
Occupied Bandwidth (% Int Pwr or > dBc metho	od)	
Decoded CTCSS/DCS/DTMF		
Encoded CTCSS/DCS/DTMF		
Graphs		
NBFM Analyzer		NBFM Talk-Out Coverage
Spectrum		Outdoor measured values are overlayed on a geo-tagged map, or displayed
Audio Spectrum		on a value vs. time graph. Captured data is exportable to both KML and CSV text (requires Option 31 GPS and a suitable GPS antenna).
Audio Waveform/Scope		Indoor measured values are referenced by creating touchscreen points on a
Summary Display		floorplan.
Setup Parameters		·
• Frequency	Receive Frequency, Transmit	: Frequency, Span, Offset
Amplitude	Reference level, Scale, Ext At	tenuation, Auto Range, Adjust Range
Setup	Tone Type (CTCSS, DCS, DTM	IF)
Filters	High Pass (300 Hz, 3 kHz, No	ne) and Low Pass (300 Hz, 3 kHz, 15 kHz, None)
	De-emphasis On/Off	
Measurement	NBFM Analyzer, NBFM Cover	rage, Quieting, SINAD
Auto Scan		k when RF In > +10 dBm, FM or CW signal
Tx Patterns		F, FM w/ CTCSS/DCS/DTMF + Tone Modulation, FM + Tone Modulation
NBFM Analyzer	Active Graph, Maximize Active Trace, Graph Type, Audio Span, Audio Sweep Time, Occupied Band Frequency Display (Carrier or Error)	
Graph Type	Spectrum, Audio Spectrum, A	Audio Waveform/Scope, Summary Display
NBFM Coverage		
(requires Option 31 GPS)	Display Type (Map or Time G	
	USB Memory File Format: .nbfm, .kml, both	
	Log data On/Off	
RF Measurements (temperature ran	-	
Received Power dBm	± 1.25 dB, ± 0.5 dB typical	co.
Frequency Error Hz	± 10 Hz + Frequency Referen	
SINAD/Quieting	Audio In port conforms to TIA-603-D for input voltage and impedance Deviation	
Additional Summary Measurements	Modulation Rate	
	Occupied Bandwidth	
Tone Decode	CTCSS/DCS (standard tones)	per TIA-603-D), DTMF

## **MBFM Signal Generator**

#### **Setup Parameters**

Generator	On/Off
TX Output Level	0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm)
Frequency Accuracy	Same as Spectrum Analyzer

S412E

## P25/P25p2 Analyzer and P25/P25p2 Talk-Out Coverage (Options 521 and 522)

Measurements P25/P25p2 Analy	zer	P25/P25p2 Talk-Out Coverage	
(Option 521)		(Option 522, requires Option 31 GPS)	
Received Power		BER	
Frequency Error		RSSI	
Modulation Fidelity		Modulation Fidelity	
NAC (hex)			
Symbol Rate Error			
BER (1011 for P25, 1031 for P25p2), O.153 (P25	), Voice, and Control Channel)		
Symbol Deviation			
Hexadecimal Display of Control Channel Traffic	:		
Graphs			
P25/P25p2 Analy (Option 521)	zer	P25/P25p2 Talk-Out Coverage (Option 522, requires Option 31 GPS)	
Constellation (P25 only)		Outdoor measured values are overlayed on a geo-tagged map, or displayed	
Linear Constellation		on a value vs time graph, and are exportable to both KML and CSV text	
Spectrum [Spans (kHz) = 25, 50, 100, 500, 1000	. 50001	(requires Option 31 GPS and a suitable GPS antenna).	
Histogram	,		
Eye Diagram		Indoor measured values are referenced by creating touchscreen points on a	
Demodulation Summary Display		floorplan.	
Base Station Control Channel Summary Displa	s (Active Control Channel		
Band Plan, Backup Control Channel, Adjacent			
TDMA Power Profile (P25p2 only)	, , , , , , , , , , , , , , , , , , ,		
Standards Compliance P25	Relevant sections of TIA-102	.CAAA-C	
P25 Phase 2	Relevant sections of TIA-102	.CCAA	
Setup Parameters			
Frequency	Receive Frequency, Transmi	t Frequency, Span, Offset	
Amplitude	Reference level, Scale, Ext At	ttenuation, Auto Range, Adjust Range	
Setup	P25 Modulation Types: C4FM	I, CQPSK	
		53 (V.52), Voice, Control Channel	
		es: Base Station (H-DQPSK) & Mobile Station (H-CPM)	
	Averaging WACN ID System	031, Silence, Voice, Control Channel n ID, Color Code, Descrambling (Off/On)	
Measurement	P25 Analyzer, P25 Coverage		
	, , ,	ve Trace, Graph Type, Symbol Span	
		ear Constellation, Spectrogram, Histogram, Eye Diagram,	
Demodulation Summary Dis		play, Base Station Control Channel Summary Displays (Active Control Channe Channel, Adjacent Site Summary)	
Eye Diagram Symbol Span	2, 3, 4, 5		
P25/P25p2 Coverage		25, .kml, both (Option 522, requires Option 31 GPS)	
Log Data			
RF Measurements (Option 521)	temperature range 15 °C to 35	5 °C)	
	± 1.25 dB, ± 0.5 dB typical		
Frequency Error Hz	± 10 Hz + Frequency Referen	nce	
Additional Summary Measurements	Modulation Fidelity (%)		
	BER/MER (%)		
	Symbol Deviation (Hz)		
	Network Access Code (Hex)		
	Symbol Rate Error (Hz)		

RSSI, BER, Modulation Fidelity

Specifications

## P25/P25p2 Signal Generator

#### **Setup Parameters**

On/Off
0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm)
P25: 1011, 1011 Cal, Interference, Silence, Busy, Idle, High Dev, Low Dev, O.153 (v. 52) p25_lsm: 1011, 511 (O.153/v.52), 1011 Cal, Interference, Silence, Busy, Idle, Fidelity CW, AM and FM
Base Station (H-DQPSK): 1031, 1031 Cal, Silence Mobile Station (H-CPM, Selectable timeslot): 1031, 1031 Cal, Silence CW, AM, FM
2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical
Same as Spectrum Analyzer
500 kHz to 1.6 GHz
< 1.25 % max, < 0.75 % typical

P25p2 Modulation Fidelity < 2.0 % max, < 1.75 % typical

S412E

## **DMR (MOTOTRBO) Analyzer and DMR Talk-Out Coverage (Options 591 and 592)**

DMR (MOTOTRBO) A	nalyzer	DMR Talk-Out Coverage	
(Option 591)		(Option 592, requires Option 31 GPS)	
Received Power		BER	
Frequency Error		RSSI	
Modulation Fidelity		Modulation Fidelity	
Color Code (decimal)			
RX Timeslot (Base Station only)			
Symbol Rate Error			
Symbol Deviation			
Base Station: 1031, 1031-1 % BER, 0.153, 0.153	3-1 % BER, Silence, tscc		
Mobile Station: 1031, 1031-1 % BER, 0.153, 0.1	53-1 % BER, Silence		
Repeater Receiver Sensitivity Test			
CW, AM, FM			
Graphs			
DMR (MOTOTRBO) Aı (Option 591)	nalyzer	DMR Talk-Out Coverage (Option 592, requires Option 31 GPS)	
Constellation		Outdoor measured values are overlayed on a geo-tagged map, or displayed	
Linear Constellation		on a value vs. time graph, and are exportable to both KML and CSV text	
Spectrum [Spans (kHz) = 25, 50, 100, 500, 1000	, 5000]	(requires Option 31 GPS and a suitable GPS antenna). Indoor measured values are referenced by creating touchscreen points or floorplan.	
Histogram			
Eye Diagram		nooi pian.	
Summary Display			
DMR Summary			
Power Profile			
Setup Parameters			
Frequency	Receive Frequency, Transmi	t Frequency, Span, Rx/Tx Coupling, Coupling Offset	
Amplitude	Reference level, Scale, Ext A	ttenuation, Auto Range, Adjust Range	
Setup	Modulation Type (Base Stati	ion, Mobile Station), BER pattern (1031, O.153, Voice, Silence)	
Measurement	DMR Analyzer, DMR Covera	ge, DMR Bit Capture	
DMR Analyzer	Active Graph, Maximize Acti	ve Trace, Graph Type, Symbol Span	
Graph Type	Constellation, Linear Conste Power Profile	llation, Spectrogram, Histogram, Eye Diagram, Summary, DMR Summary,	
Eye Diagram Symbol Span	2, 3, 4, 5		
DMR Coverage (Option 592, requires Option 31 GPS)	USB Memory File Format .dr	mr2, .kml, both	
	Log data On/Off		
•••	temperature range 15 °C to 3	5 °C)	
Received Power dBm	± 1.25 dB, ± 0.5 dB typical		
Frequency Error Hz	± 10 Hz + Frequency Referen		
Summary Measurements	Symbol Rate Error	Error, Modulation Fidelity, BER, Symbol Deviation, Color Code,	
DMR Summary Measurements	MS ID, Target ID, Talk Group ID, FID, Call Type, Base Station ID		

RSSI, BER, Modulation Fidelity

## 뺅 DMR Signal Generator

Setup Parameters		
Generator	On/Off	
Tx Output Level	0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm)	
Tx Pattern	Base Station: 1031, 1031-1 % BER, O.153, O.153-1 % BER, Silence, tscc Mobile Station: 1031, 1031-1 % BER, O.153, O.153-1 % BER, Silence CW, AM, FM	
RF Characteristics		
Power Level Accuracy	2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical	
Frequency Range	500 kHz to 1.6 GHz	
	1.25 % max, 0.75 % typical	
Mod Fidelity	1.25 /0 max, 0.75 /0 typical	

## Specifications

Monsuraments		
Measurements dPMR RF Analyze	er	dPMR Talk-Out Coverage
(Option 573)		(Option 572, requires Option 31 GPS)
Received Power		RSSI
Frequency Error		Modulation Fidelity
Adulation Fidelity		
symbol Rate Error		
Symbol Deviation		
Graphs		
dPMR RF Analyze (Option 573)	er	dPMR Talk-Out Coverage (Option 572, requires Option 31 GPS)
Constellation		Outdoor measured values are overlayed on a geo-tagged map and
inear Constellation		exportable to both KML and CSV text (requires Option 31 GPS and a suitable
Spectrum [Spans (kHz) = 25, 50, 100, 500, 1000,	, 5000]	GPS antenna).
listogram		Indoor measured values are referenced by creating touchscreen points on a floorplan.
iye Diagram		
Summary Display		
Setup Parameters		
Frequency	Receive Frequency, Transmi	
Amplitude	Reference level, Scale, Ext At	ttenuation, Auto Range, Adjust Range
Setup	Modulation Bandwidth (6.25	
Measurement	dPMR Analyzer, dPMR Cover	-
dPMR Analyzer		ve Trace, Graph Type, Symbol Span
Graph Type		llation, Spectrogram, Histogram, Eye Diagram, Summary
Eye Diagram Symbol Span	2, 3, 4, 5	
dPMR Coverage	USB Memory File Format .dp Log data On/Off	omr, .kml, both
· · ·	temperature range 15 °C to 35	5 °C)
Received Power dBm	± 1.25 dB, ± 0.5 dB typical	
Frequency Error Hz	± 10 Hz + Frequency Referen	nce
Additional Summary Measurements	Modulation Fidelity (%) Symbol Deviation (Hz) Symbol Rate Error (Hz)	
Coverage Measurements (Option	<b>572)</b> RSSI, Modulation Fidelity	
🎢 Signal Generator		
Setup Parameters		
Generator	On/Off	
Tx Output Loval	0.1 dB resolution, 0 dBm to	–130 dBm (spec to –120 dBm)
Tx Output Level	CW, AM, FM, 0.153	
Tx Output Level Tx Patterns	- , , , ,	
Tx Patterns RF Characteristics		
Tx Patterns <b>RF Characteristics</b> Power Level Accuracy	2.0 dB (CW Pattern, tempera	ture range 15 °C to 35 °C, –120 dBm to 0 dBm) typical
Tx Patterns RF Characteristics		

S412E

## minimizer and NXDN Talk-Out Coverage (Options 531 and 532)

Measurements			
NXDN Analyze (Option 531)	r	NXDN Talk-Out Coverage (Option 532, requires Option 31 GPS)	
Received Power		BER	
Frequency Error		RSSI	
Modulation Fidelity		Modulation Fidelity	
RAN (decimal)			
Symbol Rate Error			
BER (1031, O.153, Voice, and Control Channel)			
Symbol Deviation			
Graphs			
NXDN Analyze (Option 531)	r	NXDN Talk-Out Coverage (Option 532, requires Option 31 GPS)	
Constellation		Outdoor measured values are overlayed on a geo-tagged map and	
Linear Constellation		exportable to both KML and CSV text (requires Option 31 GPS and a suital GPS antenna).	
Spectrum [Spans (kHz) = 25, 50, 100, 500, 1000	), 5000]	Indoor measured values are referenced by creating touchscreen points on a	
Histogram		floorplan.	
Eye Diagram			
Summary Display			
Setup Parameters			
Frequency	Receive Frequency, Transmi	t Frequency, Span, Offset	
Amplitude		ttenuation, Auto Range, Adjust Range	
Setup	Modulation Bandwidth (6.25 kHz and 12.5 kHz), BER pattern (1031, O.153, Voice, Control Channel)		
Measurement	NXDN Analyzer, NXDN Cove	rage	
NXDN Analyzer	Active Graph, Maximize Activ	ve Trace, Graph Type, Symbol Span	
Graph Type	Constellation, Linear Conste	llation, Spectrogram, Histogram, Eye Diagram, Summary	
Eye Diagram Symbol Span	2, 3, 4, 5		
NXDN Coverage (Option 532, requires Option 31 GPS)	USB Memory File Format .nxdn, .kml, both Log data On/Off		
RF Measurements (Option 531)	(temperature range 15 °C to 35	5 °C)	
Received Power dBm	± 1.25 dB, ± 0.5 dB typical		
Frequency Error Hz	± 10 Hz + Frequency Reference		
Additional Summary Measurements	Modulation Fidelity (%) BER/MER (%)		
	Symbol Deviation (Hz)		
	Radio Access Number (RAN) Symbol Rate Error (Hz)	Decimal	
Coverage Measurements (Option	532)		
	RSSI, BER, Modulation Fideli	ty	

## minimized NXDN Signal Generator

Setup	Parame	t	er	s	

6.25 kHz, 12.5 kHz On/Off 0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm) 1031, O.153 (v. 52), High Dev, Low Dev, UDCH Pattern 10, CAC, 1031 DTS, FACCH3 DTS, Framed PN9, 1031 Cal, CW, AM, FM
2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical
500 kHz to 1.6 GHz
1.25 % max

Frequency Accuracy Same as Spectrum Analyzer

**Specifications** 

## TETRA Analyzer and TETRA Coverage Mapping (Options 581 and 582)

TETRA Analyze	r	TETRA Coverage
(Option 581)		(Option 582, requires Option 31 GPS)
Received Power Frequency Error Error Vector, RMS, and Peak Carrier Magnitude IQ Imbalance Magnitude & Phase Error Base Station Extended Color Code Base Station Receiver Sensitivity Test	e	RSSI EVM
Symbol Rate Error		
Graphs		
TETRA Analyze (Option 581)	r	TETRA Coverage (Option 582, requires Option 31 GPS)
Constellation Spectrum [Spans (kHz) = 25, 50, 100, 500, 1000 Eye Diagram Summary Display TETRA Summary	), 5000]	Outdoor measured values are overlayed on a geo-tagged map and exportable to both KML and CSV text (requires Option 31 GPS and a suitable GPS antenna). Indoor measured values are referenced by creating touchscreen points on a floorplan.
Setup Parameters		
Frequency	Receive Frequency, Tx Freq	uency, Rx Coupling, Coupling Offset, Span
Amplitude	Reference level, Scale, Ext A	ttenuation, Auto Range, Adjust Range, Tx Output Lvl, Tx Power Offset, Units
Setup	Mod Type, Rx Pattern, Tx Pa	attern, Squelch Lvl, Numeric Averaging
Measurements	TETRA Analyzer, TETRA Cov	erage, TETRA BS Sensitivity
TETRA Analyzer	Active Graph, Maximize Act	ive Graph, Graph Type, Symbol Span
Graph Type	Constellation, Spectrogram	, Eye Diagram, Summary, TETRA Summary
Eye Diagram Symbol Span	2, 3, 4, 5	
TETRA Coverage		
(Option 582, requires Option 31 GPS)	USB Memory File Format .te Log data On/Off	etra, .kml, or both
RF Measurements (Option 581)	(temperature range 15 °C to 3	5 °C)
Received Power dBm	± 1.25 dB, ± 0.5 dB typical	
Frequency Error Hz	± 10 Hz + Frequency Refere	nce
Additional Summary Measurements	Vector Error, RMS and Peak Residual Carrier Magnitude IQ Imbalance (dB) Phase Error Degrees Magnitude Error (%) Symbol Rate Error (Hz)	
TETRA Summary Measurements	Mobile Color Code (Decima Mobile Network Code (Deci Base Station Color Code (De Base Station Extended Colo Location Area Code (Decim Mobile Station Maximum Ti	mal) ecimal) r Code (Hex) al)

Coverage Measurements (Option 582) RSSI, Error Vector Magnitude

#### 📷 TETRA Signal Generator

#### **Setup Parameters**

Modulation Type Generator Tx Output Level	П/4 (Pi/4) DQPSK On/Off 0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm)
Base Station Test Patterns	tetra_bs_AllunallocPCH tetra_bs_idle_unallocPCH tetra_bs_busy_allocPCH T1_TCH_7p2
RF Characteristics	

Power Level Accuracy	2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical
Frequency Range	500 kHz to 1.6 GHz
EVM	3.5 % max
Frequency Accuracy	Same as Spectrum Analyzer

## S412E

## PTC Analyzer and PTC Talk-Out Coverage (Options 721 and 722)

PTC Analyzer	PTC Talk-Out Coverage
(Option 721)	(Option 722, requires Option 31 GPS)
Received Power Frequency Error II/4 DQPSK: Error Vector Magnitude, BER, IQ Imbalance, Phase Error, Magnitude Error, Symbol Rate Error	BER RSSI Modulation Fidelity

Graphs	
PTC Analyzer	PTC Talk-Out Coverage
(Option 721)	(Option 722, requires Option 31 GPS)
Constellation	Outdoor measured values are overlayed on a geo-tagged map, or displayed
Linear Constellation	on a value vs time graph, and are exportable to both KML and CSV text
Spectrum [Spans (kHz) = 25, 50, 100, 500, 1000, 5000]	(requires Option 31 GPS and a suitable GPS antenna).
Histogram Eye Diagram Summary Display	Indoor measured values are referenced by creating touchscreen points on a floorplan.

Setup l	Parameters
---------	------------

Frequency	Receive Frequency, Transmit Frequency, Span, Offset
Amplitude	Reference level, Scale, Ext Attenuation, Auto Range, Adjust Range
Setup	RX Pattern (0.153/V.52, PN9 Normal), Symbol Rate (Half Rate 8 ksps, Full Rate 16 ksps), TX Pattern (0.153 Continuous, PN9 Normal Types 1-4, PN9 Normal Continuous), CW, AM 1 kHz tone, FM 1 kHz tone
Measurement	PTC Analyzer, PTC Coverage
PTC Analyzer	Active Graph, Maximize Active Trace, Graph Type, Symbol Span
Graph Type	Constellation, Linear Constellation, Spectrogram, Histogram, Eye Diagram, Summary
Eye Diagram Symbol Span	2, 3, 4, 5
PTC Coverage (Option 722)	USB Memory File Format .ptc, .kml, both (requires Option 31 GPS)
Log data	On/Off
RF Measurements (Option 721) (	temperature range 15 °C to 35 °C)
Received Power dBm	± 1.25 dB, ± 0.5 dB typical
Frequency Error Hz	± 10 Hz + Frequency Reference
Additional Summary Measurements	Error Vector Magnitude %
-	BER %
	IQ Imbalance dB
	Phase Error degrees
	Magnitude Error %
	Symbol Rate Error (Hz)

**Coverage Measurements (Option 722)** 

RSSI, BER, Modulation Fidelity

## PTC Signal Generator

Setup Parameters	
Modulation Type	П/4 DQPSK
Symbol Rate (ksps)	8 (Half Rate), 16 (Full Rate)
Generator	On/Off
Tx Output Level	0.1 dB resolution, 0 dBm to –130 dBm (spec to –120 dBm)
Tx Pattern	PN9 Continuous, PN9 Burst, CW, AM, FM
RF Characteristics	
Power Level Accuracy	2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical
Frequency Range	500 kHz to 1.6 GHz
EVM	3.5 % max
Frequency Accuracy	Same as Spectrum Analyzer
RF Characteristics Power Level Accuracy Frequency Range EVM	PN9 Continuous, PN9 Burst, CW, AM, FM 2.0 dB (CW Pattern, temperature range 15 °C to 35 °C, –120 dBm to 0 dBm) typical 500 kHz to 1.6 GHz 3.5 % max

## Specifications

## AM/FM/PM Signal Analyzers (Option 509)

Measu	irements						
Display Type	RF Spectrum AM/FM/PM	Audio Spectrum (AM)	Audio Spectrum (FM/PM)	Audio Waveform (AM)	Audio Waveform (FM/PM)	Summary (AM)	Summary (FM/PM)
Graphic Display	Power (dBm) vs. Frequency	Depth (%) vs. Modulation Frequency	Deviation (kHz/rad) vs. Modulation Frequency	Depth (%) vs. Time	Deviation (kHz/rad) vs. Time	None	None
Numerical Displays	Carrier Power Carrier Frequency Occupied Bandwidth	AM Rate RMS Depth (Pk-Pk)/2 Depth SINAD <sup>a</sup> THD <sup>a</sup> Distortion/Total Vrms <sup>a</sup>	FM/PM Rate RMS Deviation (Pk-Pk)/2 Deviation SINAD <sup>a</sup> THD <sup>a</sup> Distortion/Total Vrms <sup>a</sup>	AM Rate RMS Depth (Pk-Pk)/2 Depth SINAD <sup>a</sup> THD <sup>a</sup> Distortion/Total Vrms <sup>a</sup>	FM/PM Rate RMS Depth (Pk-Pk)/2 Depth SINAD <sup>a</sup> THD <sup>a</sup> Distortion/Total Vrms <sup>a</sup>	RMS Depth (AM) Peak + Depth Peak – Depth (Pk-Pk)/2 Depth Carrier Power Carrier Frequency Occupied Bandwidth AM Rate SINAD <sup>a</sup> THD <sup>a</sup> Distortion/Total Vrms <sup>a</sup>	RMS Deviation (FM/PM) Peak + Depth Peak - Depth (Pk-Pk)/2 Depth Carrier Power Carrier Frequency Occupied Bandwidth AM Rate SINAD <sup>a</sup> THD <sup>a</sup> Distortion/Total Vrms <sup>a</sup>

a. Requires Sinewave modulation

Setup Parameters	
Frequency	Center Freq, Span, Freq Step, Signal Standard, Channel, Channel Increment, Set Carrier Freq
Amplitude	Scale, Power Offset, Adjust Range
Setup	Demod Type (AM, FM, PM), IFBW, Auto IFBW
Measurements	RF Spectrum AM/FM/PM, Audio Spectrum (AM/FM/PM), Audio Waveform (AM/FM/PM), Summary (AM/FM/PM), Average
Marker	On/Off, Delta, Peak Search, Marker Freq to Center, Marker to Ref Lvl, Marker Table, All Markers Off
Specifications	
AM	Modulation Rate: ± 1 Hz (< 100 Hz), ± 2% (> 100 Hz) Depth: ± 5% for modulation rates 10 Hz to 100 kHz
FM	Modulation Rate: ± 1 Hz (< 100 Hz); ± 2% (100 Hz to 100 kHz) Deviation Accuracy: ± 5% (100 Hz to 100 kHz, IFBW must be greater than 95 % occupied BW)
РМ	Modulation Rate: ± 1 Hz (< 100 Hz); ± 2% (100 Hz to 100 kHz) Deviation Accuracy: ± 5% (deviation 0 to 93 Rad, rate 10 Hz to 5 kHz, IFBW must be greater than 95 % occupied BW)
IF Bandwidth	1 kHz to 300 kHz in 1-3 sequence
Frequency Span	RF Spectrum: 10 kHz to 10 MHz
	Audio Spectrum: 2 kHz, 5 kHz, 10 kHz, 20 kHz
RBW/VBW	30
Span/RBW	100
Sweep time	50 μs to 50 ms (Audio Waveform)

## [TTE Signal Analyzers (Options 541, 542, 546, and 886)

Measurements		Domodulation	Ower the Air (OTA)	Decc/Epil	
RF (Option 541)		Demodulation (Options 542 and 886)	Over-the-Air (OTA) (Option 546)	Pass/Fail (User Editable)	
Channel Spectrum	Power	vs. Resource Block (RB)	Scanner	View Pass/Fail Limits	
Channel Power	RB Po	wer (PDSCH)	Cell ID (Group, Sector)	All, RF, Modulation	
Occupied Bandwidth	Active	RBs, Utilization %,	S-SS Power, RSRP, RSRQ, SINR		
ACPR	Chann	el Power, Cell ID	Dominance	Available Measurements	
Spectral Emission Mask	OSTP,	Frame EVM by modulation	Modulation Results – On/Off	Channel Power	
Category A or B (Opt 1)	Conste		Tx Test	Occupied Bandwidth	
RF Summary	QPSK,	16QAM, 64QAM	Scanner	ACLR	
2	256QA	M Demod (Option 886)	RS Power of MIMO antennas	Frequency Error	
	Modu	lation Results	(2x2, 4x4)	Carrier Frequency	
	Ref Sig	gnal Power (RS)	Cell ID, Average Power	Dominance	
	Sync S	ignal Power (SS)	Delta Power (Max-Min)	EVM peak, rms	
	EVM –	rms, peak, max hold	Graph of Antenna Power	RS Power	
	Frequ	ency Error – Hz, ppm	Modulation Results – On/Off	RS EVM	
	Carrie	r Frequency	Mapping	SS, P-SS, S-SS Power	
	Cell ID	)	On-screen	SS, P-SS, S-SS EVM	
	Control	Channel Power	S-SS Power, RSRP, RSRQ, or SINR	PBCH Power	
	Bar Gr	aph or Table View	Scanner	PBCH EVM	
	RS, P-5	55, S-SS	Modulation Results – Off	PCFICH Power	
	PBCH,	PCFICH, PHICH, PDCCH		PCFICH EVM	
		Power (Table View)		PHICH Power, EVM	
	EVM			PDCCH Power, EVM	
	Modu	lation Results		Cell, Group, Sector ID	
		Alignment		OSTP	
		ition Summary		Tx Time Alignment	
		es EVM by modulation		TX Time Alignment	
		a Icons			
		ts active antennas (1/2)			
	Dettet				
Setup Parameters					
	Frequency	E-UTRA bands 1 – 5, 7 – 14, 1	7 – 21, 23 – 32, 66A (tunable 10 MHz to	6.0 GHz)	
			annel #, Closest Channel, Decrement/In	crement Channel	
	Bandwidth	1.4, 3, 5, 10 MHz			
	Span	Auto, 1.4, 3, 5, 10, 15, 20, 30	MHz		
	Amplitude	Scale/Division, Power Offset	, Auto Range, Adjust Range		
	Sweep	Single/Continuous, Trigger S	Sweep		
	EVM Mode	Auto, PBCH only			
2	Save/Recall	Setup, Measurement, Screen Shot (save only), to Internal/External Memory			
Measurement Summa	ary Screens	Overall Measurements, RF Measurements, Modulation Measurements			
RF Measurements (Opti	on 541)				
<b>RF Channel Power Accuracy</b>		$\pm$ 1.5 dB, $\pm$ 1.0 dB typical, (RF input –50 dBm to +10 dBm) (Option 541)			
Demodulation Measure	ments (O	otion 542)			
Frequ	iency Error	± 10 Hz + Frequency Referer	nce, 99 % confidence level		
Residual	EVM (rms)	2.0 % typical (E-UTRA Test M	odel 3.1, RF Input –50 dBm to +10 dBm	) for BW $\leq$ 10 MHz	
Over-the-Air (OTA) Mea	surement	s (Option 546)			
	Scanner	Six strongest signals if prese			
		Auto Save — Sync Signal Pov	wer and Modulation Results with GPS ta	agging	
	Auto Save	Scanner — three strongest s	signals if present		
		RS Power — strongest signa	I		
	Mapping	Map On-screen S-SS Power,	RSRP, RSRQ, or SINR of Cell ID with stro	ongest signal	
		Converse three strengtheres	ianals if present		
		Scanner — three strongest s	ta: *.kml, *.mtd (tab delimited)		

## **Specifications**

### [ITEE 802.16 Fixed WiMAX Signal Analyzers (Options 46 and 47) (Requires Option 6)

RF (Option 46)		Demodulation (Option 47)	Over-the-Air (OTA)	Pass/Fail (User Editable)
Channel Spectrum Channel Power Occupied Bandwidth Power vs. Time Channel Power Preamble Power Data Burst Power Crest Factor ACPR			There are no additional OTA Measurements. RF Measurements and Demodulation can be made OTA.	Channel Power Occupied Bandwidth Burst Power Preamble Power Crest Factor Frequency Error Carrier Frequency EVM RCE Base Station ID
Setup Parameters Bandwidth Cyclic Prefix Ratio (CP) Span Frame Length Frequency Amplitude Sweep Save/Recall		Scale/Division, Power Offse Single/Continuous, Trigger	nannel #, Closest Channel, Decrement/Inc et, Auto Range, Adjust Range	
Measurement Summary S			Measurements, Signal Quality Measurem	ients
RF Measurements (Option RF Channel Power Ac		mperature range 15 °C to 35 ± 1.5 dB, ± 1.0 dB typical, (F	°C) RF input –50 dBm to +20 dBm)	

**Demodulation (Option 47)** (temperature range 15 °C to 35 °C)

Frequency Error 0.07 ppm + Frequency Reference, 99 % confidence level Residual EVM (rms) 3 % typical, 3.5 % max (RF Input –50 dBm to +20 dBm)

**S412E** 

#### IEEE 802.16 Mobile WiMAX Signal Analyzers (Options 66, 67, and 37) (Requires Option 6, Option 37 requires Option 31 for full functionality) TMW

RF (Option 66)		Demodulation (Option 67)	Over-the-Air (OTA) (Option 37)	Pass/Fail (User Editable)
Channel Spectrum	Constellation		Channel Power Monitor	Channel Power
Channel Power	RCE (F	MS/Peak)	Preamble Scanner (Six)	Occupied Bandwidth
Occupied Bandwidth	EVM (I	RMS/Peak)	Preamble	Downlink Bust Power
Power vs. Time	Frequ	ency Error	Relative Power	Uplink Burst Power
Channel Power	CINR		Cell ID	Preamble Power
Preamble Power	Base S	itation ID	Sector ID	Crest Factor
Downlink Burst Power	Sector		PCINR	Frequency Error
Uplink Burst Power		l Flatness	Dominant Preamble	Carrier Frequency
ACPR	-	ent Subcarrier Flatness	Base Station ID	EVM
		Subcarrier/Symbol		RCE
		MS/Peak)		Sector ID
	-	RMS/Peak)		
		ency Error		
	CINR	<b></b>		
		itation ID		
	Sector			
	DL-MA	P (Tree View)		
Setup Parameters				
	Zone Type	PUSC		
DL-MAP Aut	21	Convolutional Coding (CC	), Convolutional Turbo Coding (CTC)	
ŗ	Bandwidths	3.50, 5.00, 7.00, 8.75, 10.0		
Cyclic Prefix Ratio (CP)		1/8		
Span		5, 10, 20, 30 MHz		
Frai	me Lengths	5, 10 ms		
De	modulation	Auto, Manual, FCH		
	Frequency	Center, Signal Standard, Channel #, Closest Channel, Decrement/Increment Channel		
	Amplitude	Scale/Division, Power Offs	set, Auto Range, Adjust Range	
	Sweep	Single/Continuous, Trigge	er Sweep	
	Save/Recall	Setup, Measurement, Scr	een Shot (save only), to Internal/Exterr	al Memory
Measurement Summ	ary Screens	Overall Measurements, R	F Measurements, Signal Quality Measu	irements
RF Measurements (Opt	ion 66) (T	emperature range 15 °C to 3	35 °C)	
RF Channel Pow	er Accuracy	± 1.5 dB, ± 1.0 dB typical,	(RF input –50 dBm to +20 dBm)	
Demodulation (Option	<b>67)</b> (Temp	erature range 15 °C to 35 °C	)	
Freq	Frequency Error		ference, 99 % confidence level	
Residual EVM (rms)		2.5 % typical, 3.0 % max, (RF Input –50 dBm to +20 dBm)		
Over-the-Air (OTA) Mea	surement	s (Option 37)		
Channel Pov	ver Monitor	Over time (one week), me	asurement time interval 1 to 60 sec	
Pream	ble Scanner	Six Strongest Preambles		
Auto Save		Yes		
	Auto Save			

12E	Specificatio
neral Specifications	
Setup Parameters	
System	Status (Temperature, Battery Info, Serial Number, Firmware Version, Options Installed) Self Test, Application Self Test, GPS (see Option 31)
System Options	Name, Date and Time, Brightness, Volume
	Language (English, French, German, Spanish, Chinese, Japanese, Korean, Italian, Russian, Portuguese) Reset (Factory Defaults, Master Reset, Update Firmware)
File	Save, Recall, Delete, Directory Management
Save/Recall	Setups, Measurements, Screen Shots jpeg (save only)
Delete	Selected File, All Measurements, All Mode Files, All Content
Directory Management	Sort Method (Name/Type/Date), Ascend/Descend, Internal/USB, Copy, Format USB
Internal Trace/Setup Memory	2,000 traces, 2,000 setups
External Trace/Setup Memory	Limited by size of USB Flash drive
Mode Switching	Auto-Stores/Recalls most recently used Setup Parameters in the Mode
Connectors	
VNA Port 1, VNA Port 2	Type N, female, 50 $\Omega$
VNA Port Damage Level	23 dBm, ± 50 VDC
RF In Port	Type N, female, 50 $\Omega$
RF In Port Damage Level	+33 dBm peak, $\pm$ 50 VDC, Maximum Continuous Input ( $\geq$ 10 dB attenuation)
Signal Generator Port	Type N, female, 50 $\Omega$
Signal Generator Port Damage Level	+27 dBm, ± 16 VDC
GPS	SMA, female
External Power	5.5 mm barrel connector, 12.5 VDC to 15 VDC, < 4.0 A
USB Interface (2)	Type A (Connect USB Flash Drive and Power Sensor)
USB Interface	5-pin mini-B, Connect to PC for data transfer
Ethernet Interface	RJ45 connector for Ethernet 10-Base T
Headset Jack	3.5 mm mini-phone plug
External Reference In	BNC, female, 1 MHz, 1.2288 MHz, 1.544 MHz, 2.048 MHz, 2.4576 MHz, 4.8 MHz, 4.9152 MHz, 5 MHz, 9.8304 MHz, 10 MHz, 13 MHz, and 19.6608 MHz at –10 dBm to +10 dBm
Audio In (SINAD/Quieting)	BNC, female, Impedance 50 k $\Omega$ , Maximum Voltage > 1.77 Vrms (TIA-603-D compliant)
External Trigger/Clock Recovery	BNC, female, Maximum Input ± 5 VDC
Display	
Туре	Resistive TFT Touchscreen
Size	8.4 inch daylight viewable color LCD
Resolution	800 x 600
Pixel Defects	No more than five defective pixels (99.9989% good pixels)
Power	
Field Replaceable Battery	Li-Ion, 7500 mAh rated capacity
	40 W on battery power only
DC Power	Universal 110/220 V AC/DC Adapter 55 W running with AC/DC adapter while charging battery
Life Time Charging Cycles	> 300 (80 % of initial capacity)
Battery Operation	3.6 hours, typical
Battery Charging Limits	0 °C to +45 °C, Relative Humidity $\leq$ 80 %

eneral Specifications (Continu	ed)
Regulatory Compliance	
European Union	EMC 2014/30/EU, EN 61326:2013, CISPR 11/EN 55011, IEC/EN 61000-4-2/3/4/5/6/8/11 Low Voltage Directive 2014/35/EU Safety EN 61010-1:2010 RoHS Directive 2011/65/EU applies to instruments with CE marking placed on the market after July 22, 201
Australia and New Zealand	RCM AS/NZS 4417:2012
South Korea	KCC-REM-A21-0004
Environmental	MIL-PRF-28800F Class 2
Operating Temperature Range	–10 °C to 55 °C
Storage Temperature Range	−51 °C to 71 °C
Maximum Relative Humidity	95 % RH at 30 °C, non-condensing
Vibration, Sinusoidal	5 Hz to 55 Hz
Vibration, Random	10 Hz to 500 Hz
Half Sine Shock	30 g <sub>n</sub>

4600 meters, operating and non-operating MIL-PRF-28800F, Section 4.5.6.3

MIL-STD-810G, Method 511.5, Procedure 1

273 mm x 199 mm x 91 mm (10.7 in x 7.8 in x 3.6 in)

Standard three-year warranty (battery one-year warranty)

Withstands up to ± 15 kV

3.6 kg, (7.9 lb)

Altitude

Size Weight

Duration

**Explosive Atmosphere** 

RF Port Center Pin

ESD

Size and Weight

Warranty

412E	Specification
aster Software Tools (for your	PC)
Database Management	
Full Trace Retrieval	Retrieve spectrum analyzer traces from instrument into one PC directory
Trace Catalog	Index all traces into one catalog
Trace Rename Utility	Rename measurement traces
Group Edit DAT File Converter	Titles, subtitles, plot scaling, markers and limit lines, simultaneously on similar files Converts HHST files to MST file format and vice-versa
Data Analysis	
Trace Math and Smoothing	Compare multiple traces
Data Converter Measurement Calculator	Convert from/to Return Loss, VSWR, Cable Loss, DTF and also into Smith Charts Translates into other units
Report Generation	
Report Generator	Includes GPS, power level, and calibration status along with measurements
Edit Graph	Change scale, limit lines, and markers
Report Format	Create reports in HTML for PDF format
Export Measurements	Export measurements to *.s2p, *.jpg or *.csv format
Notes	Annotate measurements
Mapping (GPS Required) Spectrum Analyzer Mode	MapInfo, MapPoint
Folder Spectrogram (Spectrum Mo	nitoring for Interference Analysis and Spectrum Clearing)
Folder Spectrogram – 2D View	Creates a composite file of multiple traces
· · · · · · · · · · · · · · · · · · ·	Peak Power, Total Power, Peak Frequency, Histogram, Average Power (Max/Min)
	File Filter (Violations over limit lines or deviations from averages)
	Playback
Video Folder Spectrogram – 2D View	Create AVI file to export for management review/reports
Folder Spectrogram – 3D View	Views (Set Threshold, Markers)
	- 3D (Rotate X, Y, Z Axis, Level Scale, Signal ID)
	- 2D View (Frequency or Time Domain, Signal ID)
	- Top Down Playback (Frequency and/or Time Domain)
List/Parameter Editors	A DE DELLA STATISTICA DE DES DES SECONDES DE SE
Traces	Add, delete, and modify limit lines and markers
Antennas, Cables, Signal Standards	Modify instrument's Antenna, Cable, and Signal Standard List
Product Updates	Auto-checks Anritsu website for latest revision firmware
Languages Display	Customize non-English language menus Modify display settings
Script Master™	
Channel Scanner Mode	Automate scan up to 1200 channels, repeat for sets of 20 channels, repeat all channels
Connectivity	
Connections	Connect to PC using USB, LAN, or Direct Ethernet connection
Network Search Download	Find all Anritsu handheld instruments on local network Download measurements and live traces to PC for storage and analysis
Upload	Upload measurements and other files from PC to instrument
Export	Measurements can be saved in various formats, depending on the measurement type, including JPEG, C
Export	and Anritsu DAT format
Printing	Print individual or all measurement screens
easyTest Tools <sup>™</sup> (for your PC)	
Instrument Modes	
	Cable & Antenna Analyzer Spectrum Analyzer
Commands	
Display Image	Allows putting a custom image on the instrument screen
Recall Setup	Places the instrument into a known state; auto-advance to next command available
Prompt	Displays instructional messages on the instrument screen; timed advance to next command available;
	instrument users can be allowed or disallowed from making setup adjustments
	Allows automatic or manual saving of traces; auto-advance to next command available

ecifications		S41
💡 🛛 Anritsu To	ol Box and I	Line Sweep Tools (for your PC)
	he next generatio	ee PC based program that increases productivity for people who deal with numerous Cable and Antenna n of Anritsu's familiar Handheld Software Tools (HHST) and shares its uncomplicated user interface, giving
Trace Capture		
Brow	se to Instrument	View and copy traces from the test equipment to your PC using Windows Explorer
C	Open Legacy Files	Open DAT files captured with Handheld Software Tools v6.61
0	pen Current Files	Open VNA or DAT files
	Capture Plots To	The Line Sweep Tools screen, DAT files, Database, or JPEG
Traces		
	Trace Types	Return Loss, VSWR, DTF-RL, DTF-VSWR, Cable Loss, Smith Chart, and PIM
	Trace Formats	DAT, VNA, CSV, PNG, BMP, JPG, HTML, Data Base, and PDF
<b>Report Generation</b>		
F	Report Generator	Includes GPS location along with measurements
	Report Format	Create reports in HTML or PDF format
	Report Setup	Report Title, Company, Prepared for, Location, Date and Time, Filename, Company logo $^1$
	Trace Setup	One Trace Portrait Mode, Two Trace Portrait Modes, One Trace Landscape Mode
Trace Validation		
	Presets	7 presets allow "one click" setting of up to 6 markers and one limit line
	Marker Controls	6 regular Markers, Marker Peak, Marker Valley, Marker between, and frequency entry
	Delta Markers	6 Delta markers
	Limit Line	Enable and drag or value entry. Also works with presets
Ν	lext Trace Button	Next Trace and Previous Trace arrow keys allow quick switching between traces
Tools		
	Cable Editor <sup>2</sup>	Allows creation of custom cable parameters
	Distance to Fault <sup>3</sup>	Converts a Return Loss trace to a Distance to Fault trace
	ement Calculator	Converts Real, Imaginary, Magnitude, Phase, RL, VSWR, Rho, and Transmit power
Signal	Standard Editor <sup>2</sup>	Creates new band and channel tables
	Renaming Grid	36 user definable phrases for creation of file names, trace titles, and trace subtitles
Connectivity	Connections	Ethernet, USB cable, and USB memory stick

#### Web Remote Control

Control	Full instrument control through a browser – all instrument functions except power switch and rotary knob
Connections	RJ45 Ethernet jack
	Third party Wi-Fi router
Protocol	HTTP/TCP/IP
Physical Layer	Cat 5 Cable, Wi-Fi router compatible
Software Required	HTML 5-compliant browser – Google Chrome, Mozilla Firefox
Operating System	iOS, Windows, Linux, Android operating systems that can host the HTML 5-compliant browser
Remote Hardware	PCs, tablets, and smart phones with Ethernet or Wi-Fi connection and an HTML 5-compliant browser
Download	Individual instrument files downloaded via browser Multiple instrument files and directories zipped and downloaded via browser File downloads are not supported by iOS Screen capture capability
Display Modes	Normal: All modes and displays supported Fast: Spectrum traces update faster (up to 5 updates per second)
Password	The instrument can be password protected Passwords may be used to manage who is controlling the instrument
Users/Instruments	One user/device can view and control many instruments

#### **Programmable Remote Control**

Functionality	Many instrument functions are programmable. See the Programming Manual for details.
Programming Language	Standard Commands for Programmable Instruments (SCPI)
Interfaces	Ethernet, USB
Available Drivers	LabView. Visit NI.com for driver

Optionally set by user
 Instrument type/model must match original
 Only \*.dat and \*.vna file types supported

## Specifications

## **Ordering Information – Options**

	<b>S412E</b> 500 kHz to 1.6 GHz	<b>Description</b> Vector Network Analyzer
	9 kHz to 1.6 GHz	Spectrum Analyzer
يىلىلاس	10 MHz to 1.6 GHz	Power Meter
~~~~	500 kHz to 1.6 GHz	CW Signal Generator
	10 MHz to 1.6 GHz	NBFM Analyzer
	Options	
	S412E-0010	High Voltage Variable Bias Tee
	S412E-0031	GPS Receiver (requires suitable GPS antenna)
and the	S412E-0019	High-Accuracy Power Meter (requires External Power Sensor)
	S412E-0025	Interference Analyzer (Option 31 recommended)
Intali	S412E-0027	Channel Scanner
	S412E-0006	6 GHz Coverage on Spectrum Analyzer
	S412E-0016	6 GHz Coverage on Vector Network Analyzer
MAG	S412E-0015	Vector Voltmeter
	S412E-0431	Coverage Mapping (requires Option 31)
	S412E-0444	EMF Measurements (requires Anritsu Isotropic Antenna)
re	S412E-0509	AM/FM/PM Analyzer
	S412E-0521 S412E-0522	P25/P25p2 Analyzer Measurements P25/P25p2 Coverage Measurements (requires Options 31 and 521)
NXON	S412E-0531 S412E-0532	NXDN Analyzer Measurements NXDN Coverage Measurements (requires Options 31 and 531)
DPMR	S412E-0573	dPMR RF Analyzer Measurements
	S412E-0572	dPMR Coverage Measurements (requires Options 31 and 573)
TETRA	S412E-0581	TETRA Analyzer Measurements
	S412E-0582	TETRA Coverage Measurements (requires Options 31 and 581)
DMA	S412E-0591	DMR (MOTOTRBO) Analyzer Measurements
- 4200	S412E-0592	DMR (MOTOTRBO) Coverage Measurements (requires Options 31 and 591)
PTC	S412E-0721 S412E-0722	PTC Analyzer PTC Coverage Measurements (requires Options 31 and 721)
	S412E-0541 S412E-0542	LTE RF Measurements LTE Modulation Quality
	S412E-0886	LTE 256QAM Demodulation (Requires Option 542)
	S412E-0546	LTE Over-the-Air Measurements (requires Option 31)
FW	S412E-0046	IEEE 802.16 Fixed WiMAX RF Measurements (requires Option 6)
	S412E-0047	IEEE 802.16 Fixed WiMAX Demodulation (requires Option 6)
MW	S412E-0066	IEEE 802.16 Mobile WiMAX RF Measurements (requires Option 6)
	S412E-0067 S412E-0037	IEEE 802.16 Mobile WiMAX Demodulation (requires Option 6) IEEE 802.16 Mobile WiMAX Over-the-Air Measurements
		(requires Option 6; Option 31 required for full functionality)
	S412E-0098 S412E-0099	Standard Calibration (ANSI Z540-1-1994) Premium Calibration (ANSI Z540-1-1994) plus printed test data
		· · · · · · · · · · · · · · · · · · ·

Specifications		S412E
Standard Accessories	(Included with instrument)	

	Part Number	Description
B Alterative and a second and a second and a second a s	2000-1691-R	Stylus with Coiled Tether
	2000-1797-R	Screen Protector Film, 8.4 inch (2, one installed)
	2000-1654-R	Soft Carrying Case
	633-75	Rechargeable 7500 mAh Li-Ion Battery
	40-187-R	AC-DC Adapter
	806-141-R	Automotive Power Adapter, 12 VDC, 60 W
	3-2000-1498	USB A-type to Mini USB B-type cable, 3.05 m (10 ft)
		Standard Three Year Warranty (one year on battery) Certificate of Conformance

### Manuals, Related Literature (Soft copy at www.anritsu.com)

it minitianinitisa.ee	
Part Numbe	er Description
10580-0031	8 LMR Master User Guide
10580-0028	9 Vector Network Analyzer Measurement Guide
10580-0024	3 Land Mobile Radio Measurement Guide
10580-0024	1 Cable and Antenna Analyzer Measurement Guide
10580-0024	4 Spectrum Analyzer Measurement Guide - Interference Analyzer, Channel Scanner, Gated Sweep, CW Signal Generator, AM/FM/PM Analyzer, Interference Mapping, Coverage Mapping
10580-0024	0 Power Meter Measurement Guide - High Accuracy Power Meter
10580-0023	4 3GPP Signal Analyzer Measurement Guide - GSM/EDGE, W-CDMA/HSDPA, TD-SCDMA/HSDPA, LTE
10580-0023	6 WiMAX Signal Analyzer Measurement Guide - Fixed WiMAX, Mobile WiMAX
10580-0031	9 Programming Manual

## Troubleshooting Guides (Soft copy at www.anritsu.com) Part Number Description



Fart Number	Description
11410-00551	Spectrum Analyzers
11410-00472	Interference
11410-00566	LTE eNode Testing
11410-00473	Cable, Antenna, and Component Troubleshooting Guide
11410-00427	Understanding Cable & Antenna Analysis White Paper

## **Specifications**

#### **Optional Accessories**

#### **Backpack and Transit Case**



#### Part Number Description

67135	Anritsu Backpack (For Handheld Instrument and PC)
760-243-R	Large Transit Case with Wheels and Handle
	56 cm x 45.5 cm x 26.5 cm (22.07" x 17.92" x 10.42")
760-271-R	Transit Case for Portable Directional Antennas and Port Extender 52.4 cm x 42.8 cm x 20.6 cm (20.62" x 16.87" x 8.12") (for 2000-1777-R, 2000-1778-R, 2000-1779-R, 2000-1798-R)

USB Power Sensors (for complete ordering information, see the respective data sheets of each sensor) Model Number Description



MA24105A	Inline Dual Directional High Power Sensor, 350 MHz to 4 GHz, +3 dBm to +51.76 dBm
MA24106A	High Accuracy RF Power Sensor, 50 MHz to 6 GHz, +23 dBm to –40 dBm
MA24108A	Microwave USB Power Sensor, 10 MHz to 8 GHz, +20 dBm to –40 dBm
MA24118A	Microwave USB Power Sensor, 10 MHz to 18 GHz, +20 dBm to –40 dBm
MA24126A	Microwave USB Power Sensor, 10 MHz to 26 GHz, +20 dBm to –40 dBm
MA24208A	Microwave Universal USB Power Sensor, 10 MHz to 8 GHz, +20 dBm to –60 dBm
MA24218A	Microwave Universal USB Power Sensor, 10 MHz to 18 GHz, +20 dBm to –60 dBm
MA24330A	Microwave CW USB Power Sensor, 10 MHz to 33 GHz, +20 dBm
MA24340A	Microwave CW USB Power Sensor, 10 MHz to 40 GHz, +20 dBm
MA24350A	Microwave CW USB Power Sensor, 10 MHz to 50 GHz, +20 dBm
MA25100A	RF Power Indicator

#### MA8100A NEON Signal Mapper



#### Model Number Description

louer Number	Description
MA8100A-000	TRX NEON® Signal Mapper with Anritsu Integration and Tracking Unit. Includes 3-Month TRX NEON Trial Software License with 3 months of maintenance and support and 3 months of Cloud Service
MA8100A-001	TRX NEON® Signal Mapper with Anritsu Integration and Tracking Unit.Includes 1 year TRX NEON Software License with 1 years of maintenance and support and 1 years of Cloud Service
MA8100A-003	TRX NEON® Signal Mapper with Anritsu Integration and Tracking Unit.Includes 3 year TRX NEON Software License with 3 years of maintenance and support and 3 years of Cloud Service
MA8100A-005	TRX NEON® Signal Mapper with Anritsu Integration and Tracking Unit.Includes 5 year TRX NEON Software License with 5 years of maintenance and support and 5 years of Cloud Service
MA8100A-100	TRX NEON® Signal Mapper with Anritsu Integration and Tracking Unit. Includes Perpetual TRX NEON Software License with 3 years of maintenance and support and 3 years of Cloud Service.
2300-574	1 year TRX NEON Software License with 1 year of maintenance and support and 1 year of Cloud Service
2300-575	3 year TRX NEON Software License with 3 years of maintenance and support and 3 years of Cloud Service
2300-576	5 year TRX NEON Software License with 5 years of maintenance and support and 5 years of Cloud Service
2300-606	Perpetual TRX NEON Software License with 3 years of maintenance and support and 3 years of Cloud Service

#### Baseband Audio Generator and Oscilloscope



#### Model Number Description

2000-1897-R	USB Baseband Audio generator and 2-Channel oscilloscope
	10 MHz bandwidth, 8 kS buffer memory, 16 protocol serial decoder, USB connected and powered
2000-1898-R	USB Low Distortion Baseband Audio generator and 2-Channel oscilloscope
	16-bit resolution, low distortion (96 dB SFDR), low noise (8.5 μV RMS), 5 MHz bandwidth, 16 MS buffer memory, low-distortion signal generator, arbitrary waveform generator, USB powered

Part Number       Description         Marzona       Handheid Interference Hunter (For full specifications, ref Marzona)         Marzona       High Power Ts/Rx Input Protection Module         G3237       Rechargeable Li-In Batteries         2000-1374       External Daal Charger for Li-Ion Batteries         2000-1378       Screen Protector Film         66864       Rack Mount Kir, Master Platform         2000-1689       EMI Near Field Probe Kit         Will Temperature N-Type Coaxial Calibration Kits       -10° to +55° C (see individual data sheets on www.anritsu.com)         Part Number       Description         OSLN50A8       High Performance Type Nrm), DC to 8 GHz, 50 O         OSLN50A8       High Performance with Through, Type Nrth, DC to 8 GHz, 50 O         OSLN50A8       High Performance with Through, Type Nrth, DC to 8 GHz, 50 O         OSLN50A8       High Performance with Through, Type Nrth, DC to 8 GHz, 50 O         OSLN50A8       High Performance with Through, Type Nrth, DC to 20 GH         TOSLN50A8       High Performance with Through, Type K(m), DC to 20 GH         TOSLN50A9       Part Number       Description         Stanza       Part Number       Description         ToslxF50A-20       High Performance with Through, Type K(m), DC to 20 GH         ToslxF50A-20       Pert Number	ous Accessories		
MA2200A       Handheid Interference Hunter (Gr rull specifications, ref MA2200A         MA2520A       High Power Tx/Rx Input Protection Module         633-75       Rechargeable Livon Battery, 7500 mAh         2000-17374       External Dual Charger for Livon Batteries         2001-17374       External Dual Charger for Livon Batteries         2000-17878       Screen Protector Plin         6668       Rack Mount Kit, Master Plafform         2000-1689       EMI Near Field Probe Kit <b>ull Temperature N-Type Coaxial Calibration Kits</b> -10 °C to +55 °C (see individual data sheets on www.anritsu.com) <b>Part Number Description</b> OSLN50A8       High Performance Type N(h), DC to 8 GHz, 50 Q         OSLN50A8       High Performance With Through, Type N(h), DC to 8 GHz, 20 Q         TOSLN50A8       High Performance With Through, Type N(h), DC to 8 GHz, 20 Q         TOSLN50A8       High Performance with Through, Type N(h), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(h), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(h), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(h), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(h), DC to 20 GH         22N50       Precision N(m) Short/Open, 18 GHz         2		art Number	Description
MA25200A       High Power TXPR. Input Protection Module 633-75         Rechargeable Li-Jon Battery, 7500 mAh         2000-1374       External Dual Charger for Li-Jon Battery.         2000-1374       External Dual Charger for Li-Jon Battery.         2000-1374       External Dual Charger for Li-Jon Battery.         2000-1689       EMI Near Field Probe Kit         2011       Temperature N-Type Coaxial Calibration Kits       -10 °C to +55 °C (See individual data sheets on www.anritsu.com)         Part Number       Description         OSLN50A-8       High Performance Type N(h), DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance With Through, Type N(n), DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance With Through, Type N(n), DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance With Through, Type N(n), DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(n), DC to 20 GHz, 50 Ω         TOSLK50A-20       High Performance with Through, Type K(n), DC to 20 GHz, 50 Ω         TOSLK50A-20       High Performance With Through, Type K(n), DC to 20 GHz, 50 Ω         Coaxial Calibration Components, Other 50 Ω, 75 Ω       Precision N(m) Short/Open, 18 GHz, 20 Ω, N(n)         280502       Precision Termination, DC to 18 GHz, 50 Ω, N(n)         280502       Precision Termination, DC to 18 GHz, 50 Ω, N(n)         280502			Handheld Interference Hunter (For full specifications, refer to the
63.75       Rechargeable Li-Ion Battery, Stom Ark         2000-1374       Excrean Protector Flm         66864       Rack Mount KI, Master Platform         2000-1689       EMI Near Field Probe Kit         all Temperature N-Type Coaxial Calibration Kits       -10 °C to +55 °C (see individual data sheets on www.anritsu.com)         Part Number       Description         OSLN50A-8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance with Through, Type N(f), DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(f), DC to 20 GH         TOSLN50A-8       High Performance with Through, Type N(f), DC to 20 GH         TOSLN50A-8       High Performance with Through, Type N(f), DC to 20 GH         TOSLN50A-8       High Performance with Through, Type N(f), DC to 20 GH         TOSLN50A-8       High Performance ND         TOSLN50A-8       High Performance ND         Bigh Performance ND       Secretors         Precision N(f) Short/Open, 18 GHz       22N50         Precision N(f) Short/Open, 18 GHz       22N50         Precision N(f) Short/Op			· · ·
2000-1737-8       External Dual Charger for LHon Batteries         2000-1737-8       Screen Protector Film         2000-1737-8       Screen Protector Film         2000-1737-8       Screen Protector Film         2000-1737-8       External Dual Charger for LHon Batteries         2001-1737-8       High Performance Type N(m), DC to 8 GHz, 50 0         2011-1750-18       High Performance With Through, Type N(f), DC to 8 GHz, 50 0         2011-18       Charger Description         2011-18       Charger Description         2020-130       Charger Description         2020-131       Chailer Stop A20         2020-131       Precision N(m) Short/Open, 18 GHz         2020-131       Part Number         20205       Precision N(m) Short/Open,			5
2000-1737.8 Screen Protector Film 66864 Rack Mount Kit, Master Platform 2000-1689 EMI Near Field Probe Kit all Temperature N-Type Coaxial Calibration Kits - 10 °C to +55 °C (see individual data sheets on www.anritsu.com) Part Number Description OSLNSGA8 High Performance Type N(n), DC to 8 GHz, 50 Ω OSLNSGA8 High Performance with Through, Type N(n), DC to 8 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 8 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 8 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 8 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 8 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 8 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 20 GHz, 0 SLNSGA8 High Performance with Through, Type N(n), DC to 20 GHz, 0 SLNSGA8 High Performance with Through, Type K(n), DC to 20 GHz, 0 SLNSGA20 High Performance with Through, Type K(n), DC to 20 GHz, 0 SLNSGA20 High Performance with Through, Type K(n), DC to 20 GHz, 0 SLNSGA20 High Performance with Through, Type K(n), DC to 20 GHz, 0 SLNSGA20 High Performance with Through, Type K(n), DC to 20 GHz, 0 SLNSGA20 Precision N(n) Short/Open, 18 GHz 2 SNS0 Precision N(n) Short/Open, 18 GHz 2 SNS0 Precision Termination, DC to 18 GHz, 50 Ω, N(n) 2 SNF50 Precision Termination, DC to 18 GHz, 50 Ω, N(n) 2 SNF50 Precision Termination, DC to 16 GHz, 50 Ω, 2 SON75A Precision Termination, DC to 16 GHz, 50 Ω, 2 SNF50 Precision Termination, DC to 16 GHz, 50 Ω, 2 SNF50 Precision Termination, DC to 16 GHz, 50 Ω, 2 SNF50 Precision Termination, N(n) DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n) DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n) DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n), DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n), DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n), DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n), DC to 3 GHz, 75 Ω, 2 SNF50 Precision Termination, N(n), DC to 18 GHz, 1 SN54R Termination, N(n), DC to 18 GHz, 1 SN54R	-9		
66864       Rack Mount Kit, Master Platform         2000-1689       EMI Near Field Probe Kit         all Temperature N-Type Coaxial Calibration Kits       -10 °C to +55 °C (see individual data sheets on www.anritsu.com)         Part Number       Description         OSLN50A.8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN50A.8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN50A.8       High Performance with Through, Type N(m), DC to 8 GHz         TOSLN50A.8       High Performance with Through, Type N(n), DC to 8 GHz         TOSLN50A.8       High Performance with Through, Type N(n), DC to 8 GHz         TOSLN50A.8       High Performance with Through, Type N(n), DC to 20 GHz         TOSLN50A.20       High Performance with Through, Type K(n), DC to 20 GHz         TOSLK50A.20       High Performance with Through, Type K(n), DC to 20 GHz         TOSLK50A.20       High Performance with Through, Type K(n), DC to 20 GHz         TOSLK50A.20       High Performance with Through, Type K(n), DC to 20 GHz         TOSLK50A.20       High Performance With Through, Type K(n), DC to 20 GHZ         Deaxial Calibration Components, Other 50 Q, 75 Ω       Precision Termination, DC to 18 GHz         22N50       Precision Termination, DC to 18 GHz         22N50       Precision Termination, DC to 18 GHz         22N50.20       Precision Termination,			-
2000-1689 EMI Near Field Probe Kit all Temperature N-Type Coaxial Calibration Kits -10 °C to +55 °C (see individual data sheets on www.anritsu.com) Part Number Description OSLN50A-8 High Performance Type N(m), DC to 8 GHz, 50 Ω OSLN50A-8 High Performance with Through, Type N(m), DC to 8 GHz, TOSLN50A-8 High Performance with Through, Type N(m), DC to 8 GHz, TOSLN50A-8 High Performance with Through, Type N(m), DC to 8 GHz, TOSLN50A-8 High Performance with Through, Type N(m), DC to 8 GHz, TOSLN50A-8 High Performance with Through, Type N(m), DC to 2 GHz, TOSLN50A-9 High Performance with Through, Type K(m), DC to 20 GH TOSLK50A-20 High Performance with Through, Type K(m), DC to 20 GH TOSLK50A-20 High Performance with Through, Type K(f), DC to 20 GH TOSLK50A-20 High Performance with Through, Type K(f), DC to 20 GH TOSLK50A-20 High Performance with Through, Type K(f), DC to 20 GH TOSLK50A-20 High Performance with Through, Type K(f), DC to 20 GH TOSLK50A-20 High Performance with Through, Type K(f), DC to 20 GH TOSLK50A-20 Precision N(f) Short/Open, 18 GHz 22NF50 Precision N(f) Short/Open, 18 GHz 22NF50 Precision Termination, DC to 18 GHz, 50 Ω, N(m) 22NF50 Precision Termination, DC to 18 GHz, 50 Ω, N(m) 22NF50 Precision Termination, DC to 18 GHz, 50 Ω, N(m) 22NF50 Precision Termination, DC to 18 GHz, 50 Ω, N(m) 22NF50 Precision Termination, DC to 18 GHz, 50 Ω, 12N50-28 Precision Termination, DC to 18 GHz, 50 Ω, 12N50-75 Precision Termination, DC to 13 GHz, 75 Ω, 22NF5 Open/Short, N(f), DC to 3 GHz, 75 Ω, 22NF5 Open/Short, N(f), DC to 3 GHz, 75 Ω, 22NF5 Open, TNC(f), DC to 18 GHz, 1091-554 Open, TNC(f), DC to 18 GHz 1091-554 R Termination, N(f), DC to 3 GHz, 75 Ω, 1091-554 R Termination, N(f), DC to 18 GHz 1091-554 R Termination, N(f), DC to 18 GHz 1091-554 R Termination, N(f), DC to 18 GHz			
Part Number       Description         OSLN50A-8       High Performance Type N(fh, DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance Type N(fh, DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(fh, DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(fh, DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(fh, DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(fh, DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(fh, DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(fh, DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(fh, DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(fh, DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(fh, DC to 20 GH         TOSLK50A-20       Precision N(fh) Short/Open, 18 GHz         22N50       Precision N(fh) Short/Open, 18 GHz         22N50       Precision Termination, DC to 18 GHz, 50 Ω, N(fh)         SM/PLNF-1       Precision Termination, DC to 18 GHz, 50 Ω, N(fh)         SM/PLNF-1       Precision N(fh) Load, 42 dB, 6 GHz         2000-1618R       Open/Short/Load, 716 DIN(fh), DC to 3 GHz, 50 Ω         2000-1618R       Open/Short/N(fh, DC to 3 GHz, 50 Ω <t< td=""><td></td><td></td><td></td></t<>			
Part Number       Description         OSLN50A-8       High Performance Type N(M), DC to 8 GHz, 50 Ω         OSLN50A-8       High Performance Type N(M), DC to 8 GHz, 50 Ω         TOSLN50A-8       High Performance with Through, Type N(M), DC to 8 GHz,         TOSLN50A-8       High Performance with Through, Type N(M), DC to 8 GHz,         TOSLN50A-8       High Performance with Through, Type N(M), DC to 8 GHz,         TOSLN50A-8       High Performance with Through, Type N(M), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(M), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(M), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(M), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(M), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(M), DC to 20 GH         TOSLK50A-20       Precision N(M) Short/Open, 18 GHz         22N50       Precision N(M) Short/Open, 18 GHz         22N50       Precision Termination, DC to 18 GHz, 50 Ω, N(M)         SM/PLINF1       Precision Termination, DC to 18 GHz, 50 Ω         2000-1618R       Open/Short/Load, 716 DINM), DC to 50 GHz 50 Ω         2000-1618R       Open/Short/Load, 716 DINM, DC to 3 GHz, 50 Ω         2000-1618R       Open/Short/Load, 716 DINM, DC to 3 GHz, 50 Ω			
OSLN50A-8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN550A-8       High Performance Type N(m), DC to 8 GHz, 50 Ω         OSLN550A-8       High Performance With Through, Type N(m), DC to 8 GHz,         III Temperature K-Type Coaxial Calibration       Kits       K-type constalled with 3.5 mm and SMA connectors.         Part Number       Description         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       Precision Termination, Type K(m), DC to 20 GH         TOSLK50A-20       Precision N(m) Short/Open, 18 GHz         22N50       Precision N(m) Short/Open, 18 GHz         22N50       Precision Termination, DC to 18 GHz, 50 Ω, N(m)         28N50-2       Precision Termination, DC to 18 GHz         2000-1618-8       Open/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω         2000-1619-8       Open/Short/Load, 716 DIN(			
OSLNFS0A-8       High Performance Type N(f), DC to 8 GHz, 50 Ω         TOSLNS0A-8       High Performance with Through, Type N(m), DC to 8 GHz         TOSLNS0A-8       High Performance with Through, Type N(m), DC to 8 GHz         TOSLNS0A-8       High Performance with Through, Type N(m), DC to 8 GHz         TOSLNS0A-8       High Performance with Through, Type N(m), DC to 8 GHz         TOSLNS0A-8       High Performance with Through, Type N(m), DC to 20 GH         TOSLNS0A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH         TOSLK50A-20       Precision N(m) Short/Open, 18 GH2         22N50       Precision N(m) Short/Open, 18 GH2         22N50       Precision N(m) Short/Open, 18 GH2         28N50-2       Precision N(m) Short/Open, 18 GH2         28N50-2       Precision N(m) Short/Load, 716 DIN(m), DC to 6.0 GH2 50 Ω         2000-1618-8       Openr/Short/Load, 716 DIN(m), DC to 6.0 GH2 50 Ω         2000-1618-8       Openr/Short/Load, 716 DIN(m), DC to 6.0 GH2 50 Ω         2000-1618-8       Openr/Short/Load, 716 DIN(m), DC to 6.0 GH2 50 Ω         2000-1618-7       Openr/Short/Load, 716 DIN(m), DC to 6.0 GH			•
TOSLN50A-8       High Performance with Through, Type N(f), DC to 8 GHz, TOSLNF50A-8         III Temperature K-Type Coaxial Calibration       Kits       K-type connectors are compatible with 3.5 mm and SMA connectors.         Part Number       Description         TOSLK50A-20       High Performance with Through, Type N(f), DC to 20 GHz         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GHz         Deaxial Calibration Components, Other 50 Ω, 75 Ω       Part Number         Part Sumper       22N50         Precision N(f) Short/Open, 18 GHz       22NF50         22NF50       Precision N(f) Short/Open, 18 GHz         28N50-2       Precision N(f) Short/Open, 18 GHz         2000-1618-R       Open/Short/Load, 716 DIN(f), DC to 3 GHz, 50 Ω, N(m)         28N50-2       Precision Termination, DC to 18 GHz         2000-1619-R       Open/Short/Load, 716 DIN(f), DC to 3 GHz, 50 Ω         2000-1619-R       Open/Short/Load, 716 DIN(f), DC to 3 GHz, 75 Ω         2007-1618-R       Open/Short, N(f), DC to 3 GHz, 75 Ω			
all Temperature K-Type Coaxial Calibration Kits       K-type connectors are compatible with 3.5 mm and SMA connectors.         Part Number       Description         TOSLK50A-20       High Performance with Through, Type K(m), DC to 20 GH TOSLK50A-20         High Performance with Through, Type K(m), DC to 20 GH TOSLK50A-20       High Performance with Through, Type K(f), DC to 20 GHz         Deaxial Calibration Components, Other 50 Q, 75 Ω       Part Number       Description         22N50       Precision N(m) Short/Open, 18 GHz       22N50         22N50       Precision N(m) Short/Open, 18 GHz       28N50-2         28N50-2       Precision Termination, DC to 18 GHz, 50 Ω, N(m)       28N50-2         28N50-2       Precision Termination, DC to 18 GHz, 50 Ω, N(m)       28NF50-2         28NF50-2       Precision N(f) Load, 42 dB, 6 GHz       2000-1619.R         2000-1619.R       Open/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω       2000-1619.R         2001-1619.R       Open/Short, N(m), DC to 3 GHz, 75 Ω       22NF75         22NF75       Precision Termination, N(m), DC to 3 GHz, 75 Ω       22NF75         22NF75       Precision Termination, N(m), DC to 3 GHz, 75 Ω       22NF75         22NF75       Precision Termination, N(m), DC to 3 GHz, 75 Ω       22NF75         22NF75       Open/Short, N(f), DC to 3 GHz, 75 Ω       26NF75A       760			
Part NumberDescriptionTOSLK50A-20High Performance with Through, Type K(m), DC to 20 GH TOSLKF50A-20baxial Calibration Components, Other 50 Ω, 75 Ω Part NumberDescription22N50Precision N(m) Short/Open, 18 GHz 22N5028N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-3Precision Termination, DC to 18 GHz, 50 Ω, N(f) SM/PLNF128N50-4Precision N(f) Load, 42 dB, 6 GHz 2000-1618-R2000-1618-ROpen/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω 2000-1618-R2000-1619-ROpen/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω 22N752000-1619-ROpen/Short, N(m), DC to 3 GHz, 75 Ω 22N752001-1619-ROpen/Short, N(m), DC to 3 GHz, 75 Ω 26N75A2001-1619-ROpen, TNC(f), DC to 18 GHz, 75 Ω 26N75A2001-1619-ROpen, TNC(f), DC to 18 GHz 1091-55-R1091-55-ROpen, TNC(f), DC to 18 GHz 1091-56-R1091-56-RShort, TNC(m), DC to 18 GHz 1091-54-R1091-56-RShort, TNC(f), DC to 18 GHz 1091-54-R1091-56-RShort, TNC(f), DC to 18 GHz1091-56-RShort, TNC(f), DC to 18 GHz1091-56-R<	Т	OSLNF50A-8	High Performance with Through, Type N(f), DC to 8 GHz, 50 $\Omega$
Part NumberDescriptionTOSLK50A-20High Performance with Through, Type K(m), DC to 20 GH TOSLKF50A-20baxial Calibration Components, Other 50 Ω, 75 Ω Part NumberDescription22N50Precision N(m) Short/Open, 18 GHz 22N5028N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-2Precision N(f) Short/Open, 18 GHz 28N50-228N50-3Precision Termination, DC to 18 GHz, 50 Ω, N(f) SM/PLNF128N50-4Precision N(f) Load, 42 dB, 6 GHz 2000-1618-R2000-1618-ROpen/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω 2000-1618-R2000-1619-ROpen/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω 22N752000-1619-ROpen/Short, N(m), DC to 3 GHz, 75 Ω 22N752001-1619-ROpen/Short, N(m), DC to 3 GHz, 75 Ω 26N75A2001-1619-ROpen, TNC(f), DC to 18 GHz, 75 Ω 26N75A2001-1619-ROpen, TNC(f), DC to 18 GHz 1091-55-R1091-55-ROpen, TNC(f), DC to 18 GHz 1091-56-R1091-56-RShort, TNC(m), DC to 18 GHz 1091-54-R1091-56-RShort, TNC(f), DC to 18 GHz 1091-54-R1091-56-RShort, TNC(f), DC to 18 GHz1091-56-RShort, TNC(f), DC to 18 GHz1091-56-R<			
TOSLKF50A-20       High Performance with Through, Type K(f), DC to 20 GHz,         Deaxial Calibration Components, Other 50 Ω, 75 Ω       Part Number       Description         22N50       Precision N(m) Short/Open, 18 GHz       22N50         22N50       Precision N(m) Short/Open, 18 GHz       22N50         28N50-2       Precision Termination, DC to 18 GHz, 50 Ω, N(m)         28N50-2       Precision Termination, DC to 18 GHz, 50 Ω, N(f)         SM/PL-1       Precision N(m) Load, 42 dB, 6 GHz         2000-1618-R       Open/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short, N(m), DC to 3 GHz, 75 Ω         22N75       Open/Short, N(m), DC to 3 GHz, 75 Ω         22N75       Open/Short, N(m), DC to 3 GHz, 75 Ω         22N75       Open/Short, N(m), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(m), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision		•••	•
Deaxial Calibration Components, Other 50 Ω, 75 Ω         Part Number       Description         22N50       Precision N(m) Short/Open, 18 GHz         22NF50       Precision Termination, DC to 18 GHz, 50 Ω, N(m)         28NF50-2       Precision Termination, DC to 18 GHz, 50 Ω, N(f)         SM/PL-1       Precision N(m) Load, 42 dB, 6 GHz         2000-1618-R       Open/Short/Load, 7/16 DIN(m), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short, N(m), DC to 3 GHz, 75 Ω         22NF50       Open/Short, N(m), DC to 3 GHz, 75 Ω         2000-1619-R       Open/Short, N(m), DC to 3 GHz, 75 Ω         2000-1619-R       Open/Short, N(m), DC to 3 GHz, 75 Ω         2001-1619-R       Open, Thort, N(m), DC to 3 GHz, 75 Ω         2001-1619-R       Open, Thort, N(m), DC to 3 GHz, 75 Ω         2001-1619-R       Open, Thort, N(m), DC to 3 GHz, 75 Ω         2001-1619-R       Open, Thort, N(m), DC to 3 GHz, 75 Ω         2001-1619-R       Open, Thort, N(m), DC to 3 GHz, 75 Ω         2001-1619-R       Open, Thort, N(m), DC to 18 GHz         2001-1619-R       Open, Thort, N(m), DC to 18 GHz         2001-1619-R       Open, Thort, NC(m), DC to 18 GHz         2001-1619-R       Open, Thort, NC(m), DC to 18 GHz         2001-1619-R       Open, Thort, NC(m), DC to 18 GHz         1091-54-R	Ti Ti	OSLK50A-20	High Performance with Through, Type K(m), DC to 20 GHz, 50 $\Omega$
Part Numbe         Description           22NN50         Precision N(m) Short/Open, 18 GHz           22NN50         Precision N(f) Short/Open, 18 GHz           28NN502         Precision N(f) Short/Open, 18 GHz, 50 Ω, N(m)           28NN502         Precision Termination, DC to 18 GHz, 50 Ω, N(m)           28NN502         Precision N(m) Load, 42 dB, 6 GHz           SM/PLNF         Precision N(f) Load, 42 dB, 6 GHz           2000-1618         Open/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω           2000-1618         Open/Short/Load, 716 DIN(m), DC to 6.0 GHz 50 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1619         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 3 GHz, 75 Ω           2000-1618         Open/Short, N(m), DC to 18 GHz           2000-1618         Open, TNC(f), DC to	ТО	SLKF50A-20	High Performance with Through, Type K(f), DC to 20 GHz, 50 $\Omega$
28N50-2Precision Termination, DC to 18 GHz, 50 Ω, N(m)28N50-2Precision Termination, DC to 18 GHz, 50 Ω, N(f)SM/PL-1Precision N(m) Load, 42 dB, 6 GHzSM/PLNF-1Precision N(f) Load, 42 dB, 6 GHz2000-1618-ROpen/Short/Load, 7/16 DIN(m), DC to 6.0 GHz 50 Ω2000-1619-ROpen/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω2000-1619-ROpen/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω2000-1619-ROpen/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω2000-1619-ROpen/Short, N(m), DC to 3 GHz, 75 Ω22NF75Open/Short, N(m), DC to 3 GHz, 75 Ω26NF75APrecision Termination, N(m), DC to 3 GHz, 75 Ω26NF75APrecision Termination, N(f), DC to 3 GHz, 75 Ω1091-55-ROpen, TNC(f), DC to 18 GHz1091-56-RShort, TNC(m), DC to 18 GHz1091-54-RShort, TNC(m), DC to 18 GHz1091-54-RTermination, TNC(f), DC to 18 GHz1015-54-RTermination, TNC(f), DC to 18 GHz		art Number 22N50	Precision N(m) Short/Open, 18 GHz
28NF50-2         Precision Termination, DC to 18 GHz, 50 Ω, N(f)           SM/PL.         Precision N(m) Load, 42 dB, 6 GHz           SM/PLNF-1         Precision N(f) Load, 42 dB, 6 GHz           2000-1618-R         Open/Short/Load, 7/16 DIN(m), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short, N(m), DC to 3 GHz, 75 Ω           22NF7         Open/Short, N(f), DC to 3 GHz, 75 Ω           26NF75A         Precision Termination, N(f), DC to 3 GHz, 75 Ω           26NF75A         Open, TNC(f), DC to 18 GHz           1091-55-R         Open, TNC(f), DC to 18 GHz           1091-56-R         Short, TNC(f), DC to 18 GHz           1091-56-R         Short, TNC(m), DC to 18 GHz           1091-56-R         Short, TNC(m), DC to 18 GHz           1091-56-R         Short, TNC(m), DC to 18 GHz			
SM/PL-1         Precision N(m) Load, 42 dB, 6 GHz           SM/PLNF-1         Precision N(f) Load, 42 dB, 6 GHz           2000-1618-R         Open/Short/Load, 7/16 DIN(m), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω           2000-1619-R         Open/Short/Load, 7/16 DIN(f), DC to 3 GHz, 75 Ω           22NF7         Open/Short, N(m), DC to 3 GHz, 75 Ω           26NF75A         Precision Termination, N(f), DC to 3 GHz, 75 Ω           26NF75A         Open, TNC(f), DC to 18 GHz           1091-55-R         Open, TNC(f), DC to 18 GHz           1091-56-R         Short, TNC(f), DC to 18 GHz           1091-56-R         Short, TNC(m), DC to 18 GHz           1091-54-R         Termination, TNC(f), DC to 18 GHz			
SM/PLNF-1       Precision N(f) Load, 42 dB, 6 GHz         2000-1618-R       Open/Short/Load, 7/16 DIN(m), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short, N(m), DC to 3 GHz, 75 Ω         22NF7       Open/Short, N(f), DC to 3 GHz, 75 Ω         26NF75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         26NF75A       Open, TNC(f), DC to 18 GHz         1091-55-R       Open, TNC(m), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-54-R       Termination, TNC(f), DC to 18 GHz         1091-54-R       Termination, TNC(f), DC to 18 GHz	T		
2000-1618-R       Open/Short/Load, 7/16 DIN(m), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         12N50-75B       Matching Pad, DC to 3 GHz, 50 Ω to 75 Ω         22N75       Open/Short, N(m), DC to 3 GHz, 75 Ω         22NF75       Open/Short, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(m), DC to 3 GHz, 75 Ω         26NF75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         1091-55-R       Open, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-54-R       Short, TNC(m), DC to 18 GHz         1091-54-R       Termination, TNC(f), DC to 18 GHz         1091-54-R       Termination, TNC(f), DC to 18 GHz			
2000-1619-R       Open/Short/Load, 7/16 DIN(f), DC to 6.0 GHz 50 Ω         12N50-75B       Matching Pad, DC to 3 GHz, 50 Ω to 75 Ω         22N75       Open/Short, N(m), DC to 3 GHz, 75 Ω         22NF75       Open/Short, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(m), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         1091-55-R       Open, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-54-R       Short, TNC(m), DC to 18 GHz         1091-54-R       Termination, TNC(f), DC to 18 GHz			
12N50-75B       Matching Pad, DC to 3 GHz, 50 Ω to 75 Ω         22N75       Open/Short, N(m), DC to 3 GHz, 75 Ω         22NF75       Open/Short, N(f), DC to 3 GHz, 75 Ω         22NF75       Open/Short, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(m), DC to 3 GHz, 75 Ω         1091-55-R       Open, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-54-R       Short, TNC(m), DC to 18 GHz         1015-54-R       Termination, TNC(f), DC to 18 GHz			•
22NF75       Open/Short, N(f), DC to 3 GHz, 75 Ω         26N75A       Precision Termination, N(m), DC to 3 GHz, 75 Ω         26NF75A       Precision Termination, N(f), DC to 3 GHz, 75 Ω         1091-55-R       Open, TNC(f), DC to 18 GHz         1091-53-R       Open, TNC(m), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-56-R       Short, TNC(f), DC to 18 GHz         1091-54-R       Short, TNC(m), DC to 18 GHz         1091-54-R       Termination, TNC(f), DC to 18 GHz	Ten		
26N75A         Precision Termination, N(m), DC to 3 GHz, 75 Ω           26NF75A         Precision Termination, N(f), DC to 3 GHz, 75 Ω           1091-55-R         Open, TNC(f), DC to 18 GHz           1091-53-R         Open, TNC(m), DC to 18 GHz           1091-56-R         Short, TNC(m), DC to 18 GHz           1091-56-R         Short, TNC(f), DC to 18 GHz           1091-54-R         Short, TNC(m), DC to 18 GHz           1091-54-R         Termination, TNC(f), DC to 18 GHz			
26NF75A         Precision Termination, N(f), DC to 3 GHz, 75 Ω           1091-55-R         Open, TNC(f), DC to 18 GHz           1091-53-R         Open, TNC(f), DC to 18 GHz           1091-56-R         Short, TNC(f), DC to 18 GHz           1091-54-R         Short, TNC(f), DC to 18 GHz           1091-54-R         Short, TNC(f), DC to 18 GHz           1015-54-R         Termination, TNC(f), DC to 18 GHz			
1091-55-R         Open, TNC(f), DC to 18 GHz           1091-53-R         Open, TNC(m), DC to 18 GHz           1091-56-R         Short, TNC(f), DC to 18 GHz           1091-54-R         Short, TNC(m), DC to 18 GHz           1015-54-R         Termination, TNC(f), DC to 18 GHz			
1091-53-R         Open, TNC(m), DC to 18 GHz           1091-56-R         Short, TNC(f), DC to 18 GHz           1091-54-R         Short, TNC(m), DC to 18 GHz           1015-54-R         Termination, TNC(f), DC to 18 GHz	and the second second		
1091-56-R         Short, TNC(f), DC to 18 GHz           1091-54-R         Short, TNC(m), DC to 18 GHz           1015-54-R         Termination, TNC(f), DC to 18 GHz	ON		
1091-54-R Short, TNC(m), DC to 18 GHz 1015-54-R Termination, TNC(f), DC to 18 GHz			
1015-54-R Termination, TNC(f), DC to 18 GHz			

		-
Adapters	Part Number	Description
		SMA(m) to N(m), DC to 18 GHz, 50 $\Omega$
		SMA(f) to N(m), DC to 18 GHz, 50 $\Omega$
		SMA(n) to N(f), DC to 18 GHz, 50 $\Omega$
		SMA(f) to N(f), DC to 18 GHz, 50 $\Omega$
		BNC(f) to N(m), DC to 1.3 GHz, 50 Ω
	510-90-R	7/16 DIN(f) to N(m), DC to 7.5 GHz, 50 Ω
	510-91-R	7/16 DIN(f) to N(f), DC to 7.5 GHz, 50 Ω
	510-92-R	7/16 DIN(m) to N(m), DC to 7.5 GHz, 50 $\Omega$
		7/16 DIN(m) to N(f), DC to 7.5 GHz, 50 Ω
	510-96-R	7/16 DIN(m) to 7/16 DIN (m), DC to 7.5 GHz, 50 $\Omega$
		7/16 DIN(f) to 7/16 DIN (f), DC to 7.5 GHz, 50 $\Omega$
		Adapter, DC to 18 GHz, TNC(f) to N(f), 50 $\Omega$
		Adapter, DC to 18 GHz, TNC(m) to N(f), 50 $\Omega$
		Adapter, DC to 18 GHz, TNC(f) to N(m), 50 $\Omega$
		Adapter, DC to 18 GHz, TNC(m) to N(m), 50 Ω
		Adapter, DC to 18 GHz, TNC(m) to SMA(f), 50 $\Omega$ Adapter, DC to 18 GHz, TNC(m) to SMA(m), 50 $\Omega$
		Adapter, DC to 18 GHz, TNC(m) to SMA(m), 50 $\Omega$
		Adapter, DC to 18 GHz, TNC(m) to TNC(n), 50 $\Omega$
		N(m) to N(m), DC to 11 GHz, 50 $\Omega$ , 90 degrees right angle
recision Adapters	Part Number	Description
		Precision Adapter, N(m) to N(m), DC to 18 GHz, 50 $\Omega$
	54111130	Precision Adapter, N(f) to N(f), DC to 18 GHz, 50 $\Omega$
ilters	Part Number	Description
		806 MHz to 869 MHz, N(m) to SMA(f), 50 $\Omega$
		824 MHz to 849 MHz, N(m) to SMA(f), 50 Ω
		880 MHz to 915 MHz, N(m) to SMA (f), 50 Ω
The second and		890 MHz to 915 MHz Band, 0.41 dB loss, N(m) to SMA(f), 50 Ω
		1850 MHz to 1910 MHz, N(m) to SMA (f), 50 $\Omega$
		1710 MHz to 1790 MHz Band, 0.34 dB loss, N(m) to SMA(f), 50 $\Omega$
		1910 MHz to 1990 MHz Band, 0.41 dB loss, N(m) to SMA(f), 50 $\Omega$
	1030-112-R	2400 MHz to 2484 MHz, N(m) to SMA (f), 50 $\Omega$
	1030-155-R	2500 MHz to 2700 MHz, N(m) to N(f), 50 $\Omega$
Attenuators		
	Part Number	•
		20 dB, 5 W, DC to 12.4 GHz, N(m) to N(f)
		20 dB, 5 W, DC to 18 GHz, N(m) to N(f)
		30 dB, 50 W, DC to 18 GHz, N(m) to N(f)
		30 dB, 50 W, DC to 8.5 GHz, N(m) to N(f)
		30 dB, 150 W, DC to 3 GHz, N(m) to N(f)
		40 dB, 100 W, DC to 8.5 GHz, N(m) to N(f), Uni-directional 40 dB, 100 W, DC to 18 GHz, N(m) to N(f), Uni-directional
-		40 dB, 150 W, DC to 3 GHz, N(m) to N(f)
	1010-120 <b>-</b> K	

Part Number Description

 15NNF50-1.5C
 1.5 m, DC to 6 GHz, N(m) to N(f), 50 Ω

 15NN50-1.5C
 1.5 m, DC to 6 GHz, N(m) to N(m), 50 Ω

 15NDF50-1.5C
 1.5 m, DC to 6 GHz, N(m) to 7/16 DIN(f), 50 Ω

 15ND50-1.5C
 1.5 m, DC to 6 GHz, N(m) to 7/16 DIN(m), 50 Ω

 15NNF50-3.0C
 3.0 m, DC to 6 GHz, N(m) to N(f), 50 Ω

 15NN50-3.0C
 3.0 m, DC to 6 GHz, N(m) to N(f), 50 Ω

## Specifications

S412E

#### **Phase-Stable Test Port Cables, Armored**



#### Part Number Description

InterChangeable Adaptor Phase Stable Test Port Cables, Armored w/Reinforced Grip (Recommended for cable and antenna line sweep applications. It uses the same ruggedized grip as the Reinforced Grip series cables. Now you can also change the adapter interface on the grip

15RCN50-1.5-R 1.5 m, DC to 6 GHz, N(m), N(f), 7/16 DIN(m), 7/16 DIN(f), 50 Ω 15RCN50-3.0-R 3.0 m, DC to 6 GHz, N(m), N(f), 7/16 DIN(m), 7/16 DIN(f), 50 Ω



nritsu

#### **Directional Antennas**

to four different connector types)



#### Part Number Description

2000-1777-R	0.09 MHz to 20 MHz, N(f), –160 dBi to –42 dBi, Log Periodic
2000-1778-R	20 MHz to 200 MHz, N(f), –40 dBi to –3 dBi, Log Periodic
2000-1779-R	200 MHz to 500 MHz, N(f), –13 dBi to –4 dBi, Log Periodic
2000-1812-R	450 MHz to 512 MHz, N(f), 7.1 dBi, Yagi
2000-1659-R	698 MHz to 787 MHz, N(f), 10.1 dBi, Yagi
2000-1411-R	822 MHz to 900 MHz, N(f), 12.1 dBi, Yagi
2000-1412-R	885 MHz to 975 MHz, N(f), 12.3 dBi, Yagi
2000-1660-R	1425 MHz to 1535 MHz, N(f), 14.3 dBi, Yagi
2000-1413-R	1710 MHz to 1880 MHz, N(f), 12.3 dBi, Yagi
2000-1414-R	1850 MHz to 1990 MHz, N(f), 11.4 dBi, Yagi
2000-1416-R	1920 MHz to 2170 MHz, N(f), 14.1 dBi, Yagi
2000-1415-R	2400 MHz to 2500 MHz, N(f), 14.1 dBi, Yagi
2000-1726-R	2500 MHz to 2700 MHz, N(f), 14.1 dBi, Yagi
2000-1715-R	698 MHz to 2500 MHz, N(f), 6 dBi to 7 dBi (typical), Bi-Blade
2000-1747-R	300 MHz to 5000 MHz, N(f), 4 dBi to 7 dBi (typical), Log Periodic
2000-1519-R	500 MHz to 3000 MHz, Log Periodic
2000-1748-R	1000 MHz to 18000 MHz, N(f), 6 dBi to 7 dBi (typical), Log Periodic

#### **Isotropic Antennas**



#### Part Number Description

2000-1791-R	Isotropic Antenna, 700 MHz to 6000 MHz, N(m)
2000-1792-R	Isotropic Antenna, 30 MHz to 3000 MHz, N(m)
2000-1800-R	Isotropic Antenna, 9 kHz to 300 MHz, N(m)

412E		Specification
Portable Antennas		
	Part Number	Description
	2000-1200-R	806 MHz to 866 MHz, SMA(m), 50 Ω*
	2000-1473-R	870 MHz to 960 MHz, SMA(m), 50 Ω*
IN Autor	2000-1035-R	896 MHz to 941 MHz, SMA(m), 50 $\Omega$ (1/2 wave)*
	2000-1030-R	1710 MHz to 1880 MHz, SMA(m), 50 Ω (1/2 wave)*
a state of the sta	2000-1474-R	1710 MHz to 1880 MHz with knuckle elbow (1/2 wave)*
	2000-1031-R	1850 MHz to 1990 MHz, SMA(m), 50 Ω (1/2 wave)*
	2000-1475-R	1920 MHz to 1980 MHz and 2110 MHz to 2170 MHz, SMA(m), 50 $\Omega^{\star}$
	2000-1032-R	2400 MHz to 2500 MHz, SMA(m), 50 Ω (1/2 wave)*
	2000-1361-R	2400 MHz to 2500 MHz, 5000 MHz to 6000 MHz, SMA(m), 50 $\Omega^{\star}$
	2000-1636-R	Antenna Kit (Consists of: 2000-1030-R, 2000-1031-R, 2000-1032-R, 2000-1200-R, 2000-1035-R, 2000-1361-R, and carrying pouch)
	2000-1616	20 MHz to 21000 MHz, N(f), 50 Ω
	2000-1487	Telescoping Whip Antenna, BNC **
		* Requires 1091-27-R SMA(f) to N(m) adapter ** Requires 1091-172-R BNC(f) to N(m) adapter

#### GPS Antennas (active)



#### Part Number Description

2000-1652-R	Magnet Mount, SMA(m), 3 VDC to 5 VDC with 1 ft cable
2000-1528-R	Magnet Mount, SMA(m), 3 VDC to 5 VDC with 4.6 m (15 ft) extension cable
2000-1760-R	Mini GPS Antenna, SMA(m), 25 dB gain, 2.5 VDC to 3.7 VDC

## Training at Anritsu

Anritsu has designed courses to help you stay up to date with technologies important to your job. For available training courses, visit: www.anritsu.com/training

# **Anritsu** envision : ensure

#### United States

Anritsu Company 1155 East Collins Blvd, Suite 100 Richardson, TX 75081, U.S.A. Toll Free: 1-800-267-4878 Phone: +1-972-644-1777 Fax: +1-972-671-1877

#### • Canada

Anritsu Electronics Ltd. 700 Silver Seven Road, Suite 120 Kanata, Ontario K2V 1C3, Canada Phone: +1-613-591-2003 Fax: +1-613-591-1006

#### • Brazil

Anritsu Electrônica Ltda. Praça Amadeu Amaral, 27 - 1 Andar 01327-010 Bela Vista, São Paulo, SP, Brazil Phone: +55-11-3283-2511 Fax: +55-11-3288-6940

#### • Mexico

Anritsu Company, S.A. de C.V. Av. Ejército Nacional No. 579 Piso 9, Col. Granada 11520 México, D.F., México Phone: +52-55-1101-2370 Fax: +52-55-5254-3147

#### • United Kingdom

Anritsu EMEA Ltd. 200 Capability Green Luton, Bedfordshire LU1 3LU United Kingdom Phone: +44-1582-433280 Fax: +44-1582-731303

#### • France

Anritsu S.A. 12 Avenue du Québec Bâtiment Iris 1-Silic 612 91140 Villebon-sur-Yvette, France Phone: +33-1-60-92-15-50 Fax: +33-1-64-46-10-65

#### • Germany

Anritsu GmbH Nemetschek Haus, Konrad-Zuse-Platz 1 81829 München, Germany Phone: +49-89-442308-0

Fax: +49-89-442308-55

List Revision Date: 20160317

#### • Italy

Anritsu S.r.l. Via Elio Vittorini 129 00144 Roma, Italy Phone: +39-06-509-9711 Fax: +39-06-502-2425

#### • Sweden Anritsu AB

Anritsu AB Kistagången 20B 164 40 KISTA, Sweden Phone: +46-8-534-707-00 Fax: +46-8-534-707-30

## • Finland

Anritsu AB Teknobulevardi 3-5 FI-01530 Vantaa, Finland Phone: +358-20-741-8100 Fax: +358-20-741-8111 • Denmark

#### Anritsu A/S

Anritsu A/S Kay Fiskers Plads 9 2300 Copenhagen S, Denmark Phone: +45-7211-2200 Fax: +45-7211-2210 • Russia

#### Anritsu EMEA Ltd.

Representation Office in Russia Tverskaya str. 16/2, bld. 1, 7th floor Moscow, 125009, Russia

#### Phone: +7-495-363-1694 Fax: +7-495-935-8962

• Spain

#### Anritsu EMEA Ltd.

Representation Office in Spain Edificio Cuzco IV, Po. de la Castellana, 141, Pta. 8 28046, Madrid, Spain Phone: +34-915-726-761 Fax: +34-915-726-621

#### • United Arab Emirates

Anritsu EMEA Ltd.

#### Dubai Liaison Office 902, Aurora Tower, P O Box: 500311- Dubai Internet City Dubai, United Arab Emirates Phone: +971-4-3758479 Fax: +971-4-4249036

#### • India

Anritsu India Private Limited 2nd & 3rd Floor, #837/1, Binnamangla 1st Stage Indiranagar, 100ft Road, Bangalore - 560038, India Phone: +91-80-4058-1300 Fax: +91-80-4058-1301

#### • Singapore

Anritsu Pte. Ltd. 11 Chang Charn Road, #04-01, Shriro House Singapore 159640 Phone: +65-6282-2400 Fax: +65-6282-2533

#### • P.R. China (Shanghai)

Anritsu (China) Co., Ltd.

27th Floor, Tower A New Caohejing International Business Center No. 391 Gui Ping Road Shanghai, Xu Hui Di District Shanghai 200233, P.R. China Phone: +86-21-6237-0898 Fax: +86-21-6237-0899

#### P.R. China (Hong Kong)

Anritsu Company Ltd. Unit 1006-7, 10/F., Greenfield Tower Concordia Plaza No. 1 Science Museum Road, Tsim Sha Tsui East Kowloon, Hong Kong, P. R. China Phone: +852-2301-4980 Fax: +852-2301-3545

#### • Japan

Anritsu Corporation 8-5, Tamura-cho, Atsugi-shi Kanagawa, 243-0016 Japan Phone: +81-46-296-1221 Fax: +81-46-296-1238

#### Korea

Anritsu Corporation, Ltd. SFL, 235 Pangyoyeok-ro, Bundang-gu, Seongnam-si Gyeonggi-do, 13494 Korea Phone: +82-31-696-7750 Fax: +82-31-696-7751

#### • Australia

Anritsu Pty. Ltd. Unit 20, 21-35 Ricketts Road, Mount Waverley, Victoria 3149, Australia Phone: +61-3-9558-8177 Fax: +61-3-9558-8255

#### • Taiwan

Anritsu Company Inc. 7F, No. 316, Sec. 1, Neihu Rd, Taipei 114, Taiwan Phone: +886-2-8751-1816 Fax: +886-2-8751-1817

Data subject to change without notice. For the most recent specifications, visit: www.anritsu.com. S412E TDS, PN: 11410-00486, Rev. AD Copyright November 2017, Anritsu Company, USA. All Rights Reserved. ® Anritsu All trademarks are registered trademarks of their respective companies. Anritsu utilizes recycled paper and environmentally conscious inks and toner.